




AKAI


LCD COLOR TV-SET

Model:
LTA-26N573HCA





SERVICE MANUAL


LTA-26N573HCA PICTURE BOM

PART NO	Descriptions	USAGE	UNIT	PHOTO	
	cabinet AS OF	1	PCS		
	PANEL	1	PCS		
	AC POWER CABLE	1	PCS		
2--1	MIAN BOARD AND KEY BOARD CONNECTING CABLE(B077)	1	PCS		

2--2	POWER SUPPLY AND PANEL CONNECTING CABLE(0025)	1	PCS			
2--3	PANEL CABLE	1	PCS			
2--4	POWER SUPPLY AND MAIN BOARD CONNECTING CABLE(0047)	1	PCS			
2--5	MAIN BOARD AND REMOTE CONTROL BOARD CONNECTING CABLE (B015)	1	PCS			
3	MAILA BOARD	1	PCS			
5	TV KEY BRACKET	1	PCS	 		

6	BATTERY	2	PCS			
7--6	SCREW B3X10C	4	PCS			
7--3	SCREW B4X12F	12	PCS			
7--4	SCREW B3X8F	9	PCS			
7--5	SCREW M4X8 (2835)	4	PCS			
7--1	SCREW MB3X6	8	PCS			
7--8	SCREW MB4X12	2	PCS			

7--2	SCREW M3X6 (6560)	3	PCS			
8	STAND RUBBER FOOT	0	PCS			
9	PLASTIC BIGHT	3	PCS			
10	NORMAL TAPE	200MM	PCS			
11	BLACK ACID TAPE	300MM	PCS			
12	ACCESSORY POCKET	1	PCS			
13	STAND COVER BOARD	1	PCS			
14	BARE TV KEY BOARD	1	PCS			
14--1	KRY SWITCH	6	PCS			
14--2	RESISTANCE 1K	2	PCS			
14--3	RESISTANCE 3.3K	2	PCS			
14--5	3pin linker	1	PCS			
15	BARE REMOTE RECEIVERED BOARD	1	PCS			
15--1	5pin linker	1	PCS			
15--5	2pin linker	1	PCS			
15--4	Aluminum electrolyte capacitor	1	PCS			
15--2	INFRA-RED RECEIVE	1	PCS			
20	TV switch BOARD	1	PCS			
20--1	KRY SWITCH	1	PCS			
20--2	RESISTANCE 6.8K	1	PCS			


20--3	2pin fast linker	1	PCS		
20--4	4pin fast linker	1	PCS		
	REMOTE CONTROL		PCS		
17	MAIN BOARD	1	PCS		
18	POWER BOARD	1	PCS		
	GIFT BOX	4	PCS		
	CUSION (left and right)	1	PCS		

B.TR901 Trouble Shooting


Europe Multiple HDMI+DVB-T

- Power Supply Trouble**
- Function Trouble**
- Display Trouble**
- Audio Trouble**


1. Power Supply Trouble




2. Function Trouble




3. Function Trouble (HDMI)




4. Function Trouble (PC)




5. Function Trouble (TV)




6. Display Trouble




7. Audio Trouble






Title		
Size	Number	Revision
B		
Date:		
File:		




07_DEMO

Title	
Size	Number
B	Revision
Date:	
File:	



08_DVB

Size	Number	Revision
C		
D		



Title	
Size	Revision
B	
Date:	
File:	


12_INPUT

DVD&1

DVD_POWER

2 AV 3456

PC



Title	
Size	Number
B	Revision
Date:	File:

ITEM	NAME	MATERIAL SPEC	QTY
1	CAPACITANCE	3pF-0603-NPO-±5%-50V	2
2	CAPACITANCE	10pF-0603-NPO-±5%-50V	3
3	CAPACITANCE	18pF-0603-NPO-±5%-50V	2
4	CAPACITANCE	22pF-0603-NPO-±5%-50V	13
5	CAPACITANCE	30pF-0603-NPO-±5%-50V	2
6	CAPACITANCE	39pF-0603-NPO-±5%-50V	6
7	CAPACITANCE	56pF-0603-NPO-±5%-50V	4
8	CAPACITANCE	100pF-0603-NPO-±5%-50V	5
9	CAPACITANCE	150pF-0603-X7R-±10%-50V	8
10	CAPACITANCE	330pF-0603-X7R-±10%-50V	4
11	CAPACITANCE	390pF-0603-X7R-±10%-50V	2
12	CAPACITANCE	1000pF-0603-X7R-±10%-50V	9
13	CAPACITANCE	1500pF-0603-X7R-±10%-50V	3
14	CAPACITANCE	2700pF-0603-X7R-±10%-50V	2
15	CAPACITANCE	0.01uF-0603-X7R-±10%-50V	12
16	CAPACITANCE	0.047uF-0603-X7R-±10%-25V	1
17	CAPACITANCE	0.1uF-0603-Y5V-+80%-20%-50V	177
18	CAPACITANCE	0.22uF-0603-Y5V-+80%-20%-16V	1
19	CAPACITANCE	0.47uF-0603-Y5V-+80%-20%-16V	2
20	CAPACITANCE	1uF-0603-Y5V-+80%-20%-10V	42
21	CAPACITANCE	10uF-0805-Y5V-+80%-20%-10V	7
22	CAPACITANCE	0ohm-1206-±5%-1/4W	1
23	CAPACITANCE	8R2ohm-1206-±5%-1/4W	2
24	CAPACITANCE	0ohm-0603-±5%-1/10W	17
25	CAPACITANCE	10ohm-0603-±5%-1/10W	13
26	CAPACITANCE	22ohm-0603-±5%-1/10W	5

27	CAPACITANCE	33ohm-0603-±5%-1/10W	13
28	CAPACITANCE	56ohm-0603-±5%-1/10W	6
29	CAPACITANCE	75ohm-0603-±5%-1/10W	28
30	CAPACITANCE	100ohm-0603-±5%-1/10W	38
31	CAPACITANCE	220ohm-0603-±5%-1/10W	3
32	CAPACITANCE	330ohm-0603-±1%-1/10W	1
33	CAPACITANCE	390ohm-0603-±5%-1/10W	1
34	CAPACITANCE	499ohm-0603-±1%-1/10W	1
35	CAPACITANCE	510ohm-0603-±5%-1/10W	8
36	CAPACITANCE	1Kohm-0603-±5%-1/10W	20
37	CAPACITANCE	1K2ohm-0603-±5%-1/10W	2
38	CAPACITANCE	1K8ohm-0603-±5%-1/10W	2
39	CAPACITANCE	2K2ohm-0603-±5%-1/10W	11
40	CAPACITANCE	3K6ohm-0603-±5%-1/10W	2
41	CAPACITANCE	4K7ohm-0603-±5%-1/10W	45
42	CAPACITANCE	5K6ohm-0603-±5%-1/10W	3
43	CAPACITANCE	6K8ohm-0603-±5%-1/10W	2
44	CAPACITANCE	10Kohm-0603-±5%-1/10W	32
45	CAPACITANCE	12Kohm-0603-±5%-1/10W	7
46	CAPACITANCE	15Kohm-0603-±1%-1/10W	4
47	CAPACITANCE	22Kohm-0603-±5%-1/10W	2
48	CAPACITANCE	33Kohm-0603-±5%-1/10W	6
49	CAPACITANCE	36Kohm-0603-±5%-1/10W	2
50	CAPACITANCE	39Kohm-0603-±5%-1/10W	2
51	CAPACITANCE	47Kohm-0603-±1%-1/10W	2
52	CAPACITANCE	47Kohm-0603-±5%-1/10W	16
53	CAPACITANCE	68Kohm-0603-±5%-1/10W	1
54	CAPACITANCE	100Kohm-0603-±5%-1/10W	21

55	CAPACITANCE	150Kohm-0603-±5%-1/10W	2
56	CAPACITANCE	270Kohm-0603-±5%-1/10W	8
57	CAPACITANCE	1Mohm-0603-±5%-1/10W	3
58	CAPACITANCE	4*22ohm-0402-±5%-1/16W	4
59	CAPACITANCE	4*100ohm-0402-±5%-1/16W	1
60	BLOCK	4*4K7ohm-0402-±5%-1/16W	2
61	PRESS DIODE	33V-LL-34-1/2W	2
62	DIODE	BA792	1
63	DIODE	LL4148-LL-34	8
64	DYNATRON	PMBT3904	15
65	DYNATRON	PMBT3906	4
66	DYNATRON	A03407	1
67	DYNATRON	TL432-CSF	1
68	ESD SAFETY DIODE	MLVS0603M07	14
69	ESD SAFETY DIODE	BAV99LT1 (A7)-SOT-23	19
70	MAGNETISM	GZ1608D121T (F)	27
71	MAGNETISM	MMZ1608S121A	1
72	MAGNETISM	MMZ1608S800A	1
73	MAGNETISM	GZ3216D121T (F)	4
74	INDUCTANCE	SDFL1608Q1R0KT (F)	4
75	HDMI	HMR41-AK5200 19PIN/0.5	2
76	IC	UR133L-3.3V-C	1
77	IC	STL8110GCH300	1
78	IC	APS1006ET5	1
79	IC	AIC1084-18PM (TR)	1
80	IC	AIC1084-33PM (TR)	1
81	IC	AZ1117H-2.5 (TR) E1	1
82	IC	AZ1117H-3.3 (TR) E1	1


83	IC	FM24C02	2
84	IC	AT24C64N	1
85	IC	MC4558L	1
86	IC	W25X80VSSIG	1
87	IC	SN74LVC14	1
88	IC	74HC4052D	2
89	IC	SN74CBT3257CD-S0-16	1
90	IC	R2S15102NP	1
91	IC	S29AL016D70TFI02	1
92	IC	TDA9886TS	1
93	IC	UM6K1N	2
94	IC	PS321TQFP80G	1
95	IC	WJCE6353 S L9G5	1
96	IC	EM6A9160TS-4G	1
97	IC	HY57V641620ETP-7	1
98	IC	ZR39160PQCG	1
99	IC	SVP-AX32-LF	1
100	B. TR901E	双面-2*(289.0*113.0)-FR4-1.6	1
1	ELECTROANALYSIS	2. 2uF-50V-±20%-4*7-105℃	1
2	ELECTROANALYSIS	10uF-25V-±20%-4*7-105℃	4
3	ELECTROANALYSIS	47uF-16V-±20%-4*7-105℃	15
4	ELECTROANALYSIS	100uF-16V-±20%-6*7-105℃	8
5	ELECTROANALYSIS	100uF-25V-±20%-6*7-105℃	1
6	ELECTROANALYSIS	220uF-16V-±20%-6*7-105℃	1
7	ELECTROANALYSIS	470uF-16V-±20%-8*12-105℃	4
8	ELECTROANALYSIS	470uF-35V-±20%-10*13-105℃	3
9	ELECTROANALYSIS	1000uF-16V-±20%-10*13-105℃	1
10	MINI BOX	334-63V-±5%	4

11	INDUCTANCE	CH8010U-470K-037-G	2
12	INDUCTANCE	DR2W4*5. 5-6. 8uH	1
13	INDUCTANCE	EC0410-101K-R-L-F	2
14	DIODE	1N4001-DO-41	3
15	DIODE	1N5822	1
16	PIN	2*18PIN-2. 0-D-H-M	1
17	SOCKET	4PIN-2. 0-D-H-G	2
18	SOCKET	4PIN-2. 0-D-H-蓝色-G	1
19	SOCKET	5PIN-2. 0-D-H-G	1
20	SOCKET	6PIN-2. 0-D-H-G	1
21	SOCKET	3PIN-2. 0-D-H-G	1
22	SOCKET	3PIN-2. 54-D-H-G	1
23	SOCKET	4PIN-2. 54-D-H-G	1
24	SOCKET	4PIN-2. 54-D-H-红色-G	1
25	SOCKET	10PIN-2. 54-D-H-G	1
26	PIN	4MHz-±30PPM-20PF-HC-49S	1
27	PIN	20. 250MHz-±30PPM-20PF-HC-49S	1
28	PIN	20. 480MHz-±30PPM-20PF-HC-49S	1
29	PIN	24MHz-±30PPM-20PF-HC-49S	1
30	FILTER	VF389A1D-VIDEO	1
31	FILTER	AF389A2D-AUDIO	1
32	FUSE	3G3A-250V	2
33	DB15 JACK	D351-015F-001-SHORT-G	1
34	S-VIDEO	DSW-3. 5-401	1
35	SCART	RC-2101(CS-104)-BEND	2
36	8 DIGITAL AV JACK	AV8-8. 4-13D(UP BLUE GREEN RED WHITE, BOTTOM RED YELLOW RED WHITLE	1
37	TUNER	DTT-8A1C/T1146	1
38	SILICAL GEL	0. 1g	1


39	DISPERSING HEAT	28*28*11	1
40	SCREEN	70. 5*51. 5*18. 5	1
41	PIN	3PIN-2. 54-D-H-M	1
42	CAP	2PIN-2. 54 (BLACK)	1

HOW TO ENTER FACTORY MODE and adjust the LVDS Mapping


1. Press SOUND key and set sound mode at CINIMA mode ;




2. Press TIMER key and set sleep time at 120 ;



3. Press green color key not power off function key you'll see that the screen displays the factory mode information as the following picture.



4. Press number key 1, the screen displays as follow :



5. press number key 2 to adjust white balance.
6. press number key 3 to exit.