



AKAI

COLOUR TV SET

Models:
LTA-26C903
LTA-32C903

SERVICE MANUAL



CONTENTS

CHAPTER ONE FEATURES AND COMPOSITIONS	1
Models for LS08 Chassis	1
Main Features	1
Unit IC Compositions	2
PCB Assembly	3
CHAPTER TWO MAIN ICs FUNCTION INTRODUCTION	5
GENERAL INTRODUCTION	5
ICs FUNCTION INTRODUCTION IN DETAILS	5
Main Tuner (TMI4-C22P2RW)	5
Sub Tuner (TAD5-C2IP1RW)	5
GM150	6
TDA8759	10
TPA3002D2	13
SM5301AS	15
SAA7115	17
UOC (TDA15063H)	19
CHAPTER THREE SIGNAL FLOW ANALYSIS AND KEY POINT MEASURE DATA	22
Signal Flow Analysis	22
Manostat Pin Voltage in Main Board Schedule	25
Main Components and Socket Locations and Definitions	25
Main Components Description	27
Main Points Wave Illustrations	27
CHAPTER FOUR SYMPTOMS AND CORRECTION	33
CHAPTER FIVE LISTS OF BREAKABLE AND MAINTENANCE PARTS	34
CHAPTER SIX FACTORY SETUP AND NOTICE	36
APPENDIX (Schematic Diagram)	40
1. Schematic Circuit Diagrams	
2. Final Assembly Diagram (Take CHD-W320F8 for Example)	
3. Final Wiring Connection Diagram (Take CHD-W320F8 for Example)	

Designs and specifications are subject to change without notice

CHAPTER ONE FEATURES AND COMPOSITIONS

Models for LS08 Chassis:

CHD-W260F8、CHD-W260F8P、CHD-TD260F8
CHD-W270F8、CHD-W270F8P、CHD-TD270F8
CHD-W320F8、CHD-W320F8P、CHD-TD320F8
CHD-W370F8、CHD-W370F8P、CHD-TD370F8

Main Features:

- Radio Frequency input; support CATV
Capable of receiving the full-append cable programs in 470MHZ
- Two-way AV input
Capable of receiving PAL, NTSC, SECAM color systems; Very convenient to watch VCR (video cassette recorder), Pickup Camera, other Disc's programs
- AV output
Capable of transmitting signal of different AV/RF systems to other AV receivers through the current AV cable
- Y/C component signal input (same to S-Video input)
Convenient to receive the Y/C high definition component signal from DVD
- HDTV input
Capable of receiving the high definition YPbPr signal in 480i, 480p, 576i, 720p, 1080i, and 1080p formats
- VGA input
 - a. Convenient to connect with the host computer
 - b. Use as the display terminal
 - c. Connect the 3.5mm(diameter) audio cord to your computer's audio main board, you can listening the beautiful music transmitted from your host computer
- DVI input
Convenient to receive DVI signal
- PIP, POP, PBP function
- Turn on with intelligence
- Zoom mode
- LTI, CTI, and black field
- BBE sound technology
- Trusurround sound technology
- Full-light display
- Picture amending display function
- Super definition display panel
- 3:2, 2:2 Pull Down
- TV program scan function
- Timer function
Automatically off at certain preset time, and enters into the standby mode
- Blue background noise reduction
In TV, AV (S-Video), YCbCr, and YPbPr modes, screen displays soft blue background if there is no signal input
- Auto Off if no signal input
In TV mode, the LCD TV will automatically power off within 15 minutes and enter into the Power

Energy Saving Mode if there is no signal input.

- Multi Language On-Screen Display menu

Ordinary and graphical user interface makes the menu operation more user-friendly

- Power Energy Saving Mode (power management mode)

In PC mode, the LCD TV will automatically power off within 30 seconds and enter into the Power Energy Saving Mode if there is no VGA signal input. It will automatically exit from the Power Energy Saving Mode and work again when it received a valid VGA signal or press any button on the panel/remote control.

- Plug and Play

It is no need to equip any installation software when the product is used as computer terminal display equipment

- Legerity, convenience, low power consumption

- Digital Photo Album Function(Only for CHD-W260F8P/CHD-W270F8P/ CHD-W320F8P/ CHD-W370F8P)

- Built-in DVD Module (Only for CHD-TD260F8 /CHD-TD270F8/CHD-TD320F8/CHD-TD370F8)

(1)Entirely Compatible to DVD、SVCD、VCD、CD、MP3

(2)Compatible to PAL/NTSC Discs

(3)High quality digital audio coaxial input enable you to feel as if sit in the theatre with the perfect classical hi-fidelity experience


(4)Automatically delete unsuitable parts according to the chosen play levels (max.8)(only for DVD discs with play level control)

(5)As many as 32 subtitles

(6)As many as 8 audios

Unit IC Compositions:

LS08 chassis LCD TV is mainly composed of regulator IC、RF IC、video processor IC、Power Amplify IC、 Analog Video IC、 System Control IC and Key Control IC, see this IC frame as below:



PCB Assembly:

It is mainly composed of TV Board、Remote Control Receiver(Signal Receiver) 、Side AV Board、K Board and Main Board. Hereunder function introduction to every PCB Assembly:

Number	Parts	Description
1	Main Board Assembly	It is the core of signal processing for LCD TV, which takes responsibility of transforming outer signal into the uniform digital signal identified by LCD display with use of System Control IC. TV and AV signals input from TV Board are decoded by UOCIII to transport RGB signal which is to be transformed by TDA8759 modulus to transport 24bit RGB digital signal, then it is to be transformed by GM1601/GM1501 to produce LVDS signal displayed on the screen, in addition, signals input from VGA、DVI would directly enter into GM1501 procedure 、format transformation and on screen display.

2	TV Board Assembly	It is mainly composed of two tuners (main and sub tuners) 、 AV/S 、 HD signal terminals and some peripheral processing IC. The main tuner demodulates RF signal to IF signal, and the sub tuner produces CVBS signal, all signals are sent to the main board after transfer.
3	Remote Control Receiver Assembly	is composed of one indicator light and one remote control receiver, which enable Users operate the TV conveniently and know its current working status simply with a remote control..
4	Built-in Power Board Assembly	It can transform AC 220V into DC for ICs, including +24V, +12V, +5V and +5VS power supply in standby mode.
5	K Board Assembly	It consists of 7 function buttons by which users can operate the TV freely.
6	Screen Assembly	Screens for LS08 have the built-in adverse transformer which change DC into high voltage AC signal to lighten the back light; The LCD screen is used to display the image after the image signal has been processed by the main board.
7	Side AV Board	It is used for earphone output, AV input, S input

CHAPTER TWO

MAIN ICs FUNCTION INTRODUCTION

GENERAL INTRODUCTION:

TV Board			
Number	Location	Type	Main Function
1	UT1	TMI4-C22P2RW	Audio and image intermediate frequency signal output
2	UT2	TAD5-C2IP1RW	Sub picture CVBS signal output
Main Board			
3	U302, U303	24LC21A T/SN	EEPROM
4	U701	24LC32A T/SN	Buffer
5	U306,U307,UA3	FSAV330QSCX	Switch selection
6	K201	K7262N	Audio surface filter
7	K202	K9352N	Audio surface filter
8	U6	TPA3002D2PHPR	Audio amplifier
9	U801	AM29LV800DT-70EC	Flash, control program inside
10	U700	GM1501-BD	Video processor
11	U201	TDA15063H-N1B06557	AV decoder
12	U402	SAA7115HL/V1	Sub channel video decoder
13	U305	SM5302AS-G-ET	High definition signal filter
14	U400	TDA8759HV/8/C1	Video signal modulus transformer
15	U5	TDA9178T/N1	Video signal picture amendment
16	U600	MT46V2M32LG-4	Frame buffer

.ICs FUNCTION INTRODUCTION IN DETAILS

Main Tuner (TMI4-C22P2RW)

Pin	Definition	Description
1	AGC	Auto gain control
2	UT	NC
3	ADD	Ground
4	SCL	IIC bus (Clock)
5	SDA	IIC bus (Data)
6	NC	NC
7	+5V	Power supply
8	NC	NC
9	30V	To produce 0~30V tune voltage
10	NC	NC
11	IF	Intermediate frequency TV signal Intermediate frequency TV signal

Sub Tuner (TAD5-C2IP1RW):

Pin	Definition	Description
1	AGC	Auto gain control
2	NC	NC

3	ADD	Ground
4	SCL	IIC bus (Clock)
5	SDA	IIC bus (Data)
6	NC	NC
7	+5V	Power supply
8	NC	NC
9	33V	To produce 0~30V tune voltage
10	NC	NC
11	IF	Intermediate frequency output (NC)
12	IF	Intermediate frequency output (NC)
13	SW0	Band control
14	SW1	Band control
15	NC	NC
16	SIF	NC
17	AGC	Auto gain control
18	VEDIO	CVBS signal output
19	+5V	Power supply
20	AUDIO	NC

GM1501

GM1501 is a kind of processing chassis for dual channels image and video, which is mainly used for LCD displays and integrative TV products. With the resolution of WUXGA, it not only supports PIP technique, but possesses some IC functions applied to image catch 、process and clock display. It integrates high velocity AD converter, PLL, high reliability DVI receiver, X86 series miccontrol and LCDS inverter. See the features as below:

Main Features

- High quality image zoom function;
- Analog RGB signal input interface;
- Intelligent output signal auto identification;
- Integrated high-power PLL output;
- High-reliable self-adaptive DVI input interface;
- 4:4:4/4:2:2/CCR656/601 8/16/24bit digital video interface;
- Embedded IC for adjustments of gain、contrast、brightness、color saturation、hue and fleshtone;
- Efficiency in reducing EMI electromagnetism inference;
- Inclined grain processing with small angle;
- High quality video processing;
- Programmable output format;
- Embedded LVDS transport;
- Advanced OSD;
- Embedded micro controller

Pin Description :

Pin	Name	Description
Analog Signal Input Port		

L3	AVSYNC	ADC vertical synchronization signal input
L4	AHSYNC	ADC horizontal synchronization signal input
N2	VGA-SCL	VGA lock input
N1	VGA-SDA	VGA digital input
D1、D2	RED+、RED-	Red analog signal input
C3	SOG	Green synchronization signal
C1、C2	GREEN+、-	Green analog signal input
B1、B2	BLUE+、BLUE-	Blue analog signal input
A2,B3,E3,D3	ADC3.3	ADC3.3Vpower supply
A3, A4	ADC1.8	ADC1.8Vpower supply
A5, B4	ADC-DGND	ADC digital ground
C4, D4, E1, E2, E4	ADC-AGND	ADC analog ground
DVI Input Output Port		
N4	DVI-SCL	DDC interface , serial clock signal
N3	DVI-SDA	DDC interface , serial data signal
A6, B6	RXC+, RXC-	DVI clock input signal
A8~A10 B8~B10	RX0+~RX2+ RX0-~RX2-	DVI input port
B11	REXT	Exterior exit resistance
C6~C11	DVI-3.3	DVI 3.3V power supply
D6、D8~D10	DVI-1.8	DVI 1.8V power supply
A7,A11,B5,B7,C7,D7 D11	DVI-GND	DVI ground
Low Bandwidth ADC Port		
C13	LBADC-33	ADC3.3Vpower supply
A12, B12, C12	LBADC_IN1~ LBADC_IN3	ADC analog input channel
D12	LBADC_RETURN	Channel analog ground
D13	LBADC-GND	Power supply voltage analog ground
OCM IC Port		
AA1~AA3,Y1~Y3, W1~W3,V1~V4, U1~U4,T1~T3	OCMADDR0~ OCMADDR19	Address input output port
AB1~AB3,AC1~AC3, AD1~AD4,AE1~AE3, AF1~AF3	OCMDATA0~ OCMDATA15	Data input output port
OCM Port Control Signal		
R1, T4, P1, P2	ROM_CSn~ ROM_CS2n	Part selection signal
R2	OCM_REn	Read enable signal
R3	OCM_WEn	Write enable signal
L1 L2	OCM_INT2 OCM_INT1	Interrupt
M1	OCM_UDO	OCM data output
M2	OCM_UDI	OCM data input
D25	OCM_TIMER1	OCM timer input

Standard Definition Video Control Port		
D16	SVCLK	SV pels clock input
C14	SVHSYNC	SV horizontal synchronization signal input
B14	SVVSYNC	SV vertical synchronization signal input
A14	SVODD	Scan status input
A17	SVDV	SV data input
Standard Definition Video Data Port		
D14,D15,A15,A16, B15,B16,C15,C16	SVDATA7~ SVDATA0	SV ITU656 data input
Video Control Port		
A20	VCLK	Video pels clock signal
D19	VHS_CS SYNC	Video horizontal synchronization signal input
C20	VVS	Video vertical synchronization signal input
B20	VODD	Scan status input
D20	VDV (VSOG)	Video data input
B17	VCLAMP	Video clamp enable output
A21,A22,A23,B21, B22,C21,C22,D21	VGRN7~ VGRN0	Green signal or Y signal input
C17,C18,C19,A18 A19,B18,B19,D18	VRED7~ VRED0	Red signal or V/Cr/Pr signal input
B23,B24,B25,A24 A25,C23,C24,D24	VBLU7~ VBLU0	Blue signal or U/Cb/Pb signal input
Screen Control Port		
A26	PPWR	Screen power control
B26	PBIAS	Screen bias control
D26, C25, C26	PWM2 ~PWM0	Pulse width modulation output
AC7	DCLK	Pels clock output
AC16	OEXTR	Connect external LVDS bias resistance
LVDS Port		
AE14~AE16,AE19~ AE23,AF13~AF16 AF19~AF23,AF11	A0~-A3-, A0+~A3+ B0~-B3-, B0+~B3+	Low voltage difference data input
AD14,AD11,AE13 AE11,AC11,AF10	LVDS_SHIELD[5] ~ LVDS_SHIELD[0]	Low voltage difference protect output
AE12,AF12, AF20,AE20	AC+,AC-,BC+,BC-	Low voltage difference protect input
Screen Port Power Supply		
AD12,AD13,AC12	LVDSB_3.3	LVDS B channel power supply
AC13,AC14,AC15	LVDSB_GND	B channel ground
AC20,AC21,AC22	LVDSA_3.3	LVDS A channel power supply
AD19,AC19,AC20	LVDSA_GND	A channel ground
AE17	VDDD33_LVDS	Analog power supply
AD17	VSSD33_LVDS	Analog ground
Clock Composite and Power Supply		
G4	XTAL	crystal oscillator interface


F2	VDDD33_PLL,	Digital power supply
H1	VDDD33_SDDS	
J1	VDDD33_DDDS	
G2	VSSD33_PLL	Digital ground
J4	VSSD33_SDDS	
K4	VSSD33_DDDS	
F4	VDDA33_RPLL	Analog power supply
G1	VDDA33_FPLL	
H3	VDDA33_SDDS	
J3	VDDA33_DDDS	
F3	VSSA33_RPLL	Analog ground
H4	VSSA33_FPLL	
H2	VSSA33_DDDS	
J2	VSSA33_DDDS	
G3	TCLK	Reference clock signal input
K2	ACS_RSET_HD	External resistance port
System Signal		
K1	RESETn	Reset signal
M3, M4	IR0, IR1	
P4	MSTR_SCL	Main clock output signal
P3	MSTR_SDA	Main data output/input signal 信号
R4	EXTCLK	External clock input

Frame Storage Interface

U24,U23	FSCLKp,FSCLKn	Fine storage clock output
V24,V25	FSRAS,FSCAS	Address output
V26	FSWE	Write enable port
W26	FSCKE	Read enable port
J24	FSVREF	Reference voltage input
K26	FSVREFVSS	Reference voltage ground
W25	FSVREF	Reference voltage input
W24	FSVREFVSS	Reference voltage ground
L26	FSDQS	Data filter
F24~F26,G23~G26 H24~H26,J25,J26, R24~R26,P24~P26 N23~N26,.....	FSDATA31~ FSDATA0	Data input output port
T24,T25,U25,U26	FSDQM3~ FSDQM0	Data output mark
Y26 Y25	FSBKSEL1, FSBKSEL0	Layer address
AA24~AA26 AB24~AB26, AC24~AC26 AD24~AD26	FSADDR11~ FSADDR0	Range address output
E23, F23, H23, J23, L23,M23,P23, R23, T23,V23,W23,Y23,	FS_2.5	2.5V power supply

AA23,AB23,AC23		
K23	VDDA18_DLL	1.8V power supply
K25	VSSA18_DLL	Power supply ground
Digit power supply		
K10,K11,K16,K17, L11,L16,T11,T16, T17,U10,U11,U16,U17	CORE_1.8	1.8V power supply
D23, W4,Y4, AA4, AB4,AC4,AC6,D17, D22,AC8,AC10	IO_3.3	3.3V power supply
K12,K13,K14,K15, L10,L12,L13,L14, L15,L17,M10,M11, M12,M13.....	D_GND	Power ground
A1, AC, D5, AC17, K3, F1	NO_CONNECT	NC

GM1501Internal Diagram:



TDA8759:

TDA8759 is a triple 8-bit video converter interface. The IC converts a RGB analog signal into a 24bit RGB or YUV or YCbCr digital signal , or converts a YUV or YCbCr analog signal into a YUV or RGB digital signal with a sampling rate up to 81 Msps. The IC supports resolutions from 480i and VGA to HDTV and XGA.


Main Features:

- Triple 8-bit Analog-to-Digital Converter (ADC)
- Three independent analog video sources up to 81 Msps selectable by I2C-bus
- Auto check on interval scan video signal
- 1.8V and 3.3V supplies
- Low gain variation with temperature
- Output format RGB 4:4:4, YUV 4:4:4, YUV 4:2:2, CCIR 656 or YUV 4:2:2 semi-planar standard on

output bus;

- I²C bus control
- Programmable clock phase adjustment cells
- Amplifier bandwidth of 100 MHz
- Integrated PLL divider
- Power-Down mode

TDA8759 Internal Diagram:



Pin Description:

Pin	Name	Description
1	HREF	Horizontal reference output
2	VCLK	Video clock output
3,13,21,29, 37,45,164	VDDO	Video port output supply voltage

4,14,22,30 38,46,165	OGND	Video port output ground
7, 8, 9, 10, 15, 16, 17, 18	VPA0~VPA7	Video port A
11,116,130,132	VDDC	Power supply port
12,117,159	CGND	Ground
23~28,31,32	VPB0~VPB7	Video port B
35,36,39~44	VPC0~VPC7	Video port C
47,53,57,58,55 60,66,70,71,75 81,83,85,86,	AGND	Analog ground
48,54,59,61,67 69,76,82,85,87,88	VDDA	Power supply port
49	REFB/Pb	Blue/blue-chrominance channel reference input
52,51,50	B/Pb1~ B/Pb3	Blue/blue-chrominance channel analog input
56	BIAS	Bias input
62	REFG/Y	Green/green-chrominance channel reference input
65,64,63	G/Y1~G/Y3	Green/green-chrominance channel analog input
74,73,72	SOG/Y1~SOG/Y3	Sync on green//brightness channel input
77	REFR/Pr	Red/red-chrominance channel reference input
80,79,78	R/Pr1~ R/Pr3	Red/red-chrominance channel analog input
89~92,97~101 112,121,122, 124,125,160~163	TST0~TST17	Reserved for test
93	PD	Power-down control input
94	OE	Output enable input
96	A0	I ² C bus address control input
102	COAST	PLL control input
103	GAIN	Gain input
104	CLAMP	Clamp input
105~107	VSYNC1~VSYNC3	Vertical synchronization input
108~110	H(C)SYNC1~ H(C)SYNC3	Horizontal (composite)synchronization input
111	CKEXT	External clock input
113	TCLK	Reserved for test
114	DIS	I ² C bus disable control input
118	SDA	I ² C bus data input/output
119	SCL	I ² C bus clock input
120,126,127,131 133,142,148,	IGND	Input digital ground
123,138,139,145 151,157	VDDI	Input digital supply voltage
166	PL	PLL disable belock output
167	DE	Data enable output

168	HS	Horizontal synchronization input
169	VS	vertical synchronization input
170	CS	Color synchronization output
171	ORR/V	Red / chrominance ADC output
172	ORB/U	Blue /chrominance ADC output
173	ORG/Y	Green / chrominance ADC output
174	VAI	Video dynamic indication output
175	FREF	Scan output
17	VREF	Vertical channel reference input

TPA3002D2:

The TPA3002D2 is a 9-W (per channel) efficient, Class-D audio amplifier for driving bridged-tied stereo speakers. The TPA3002D2 can drive stereo speakers as low as 8 . The high efficiency of the TPA3002D2 eliminates the need for external heatsinks when playing music.

Main Features:


- 9W /Ch into an 8Ω load from 12Vsupply;
- Efficient, class D operation eliminates heatsinks and reduces power supply requirements;
- 32-step DC volume control from -40db~36db;
- Line outputs for external headphone;
- Thermal and short-circuit protection

Pins Functions:

Pin	Name	Description
26, 30	AGND	Analog ground for digital/analog cells in core
33	AVCC	High-voltage analog power supply (8~14V)
29	AVDD	5V regulated output capable of 100mA output
7	AVDDREF	Reference 5V output
13	BSLN	Bootstrap I/O left channel
24	BSLP	
48	BSRN	
37	BSRP	Bootstrap I/O right channel
28	COSC	
6	LINN	
5	LINP	Negative differential audio input for left channel
16, 17	LOUTN	Positive differential audio input for left channel
20, 21	LOUTP	Class-D 1/2-H-bridge negative output for left channel
34	MODE	Class-D 1/2-H-bridge positive output for left channel
35	MODE_OUT	Input for MODE control. A logic high on this pin places the amplifier in the variable output mode and the Class-D outputs are disabled. A logic low on this pin places the amplifier in the Class-D mode and Class-D stereo outputs are enabled. Variable outputs (VAROUTL and VAROUTR) are still enabled in Class-D mode to be used as line-level outputs for external amplifiers.
		Output for control of the variable output amplifiers. When the MODE pin

		(34) is a logic high, the MODE_OUT pin is driven low. When the MODE pin (34) is a logic low, the MODE_OUT pin is driven high. This pin is intended for MUTE control of an external headphone amplifier. Leave unconnected when not used for headphone amplifier control.
18,19,42,43	PGNDR,PGNDL	Power ground for left channel H-bridge Power ground for right channel H-bridge
14,15,22,23	PVCCL	Power supply for left channel H-bridge (tied to pins 22 and 23 internally), not connected to PVCCR or AVCC.
38,39,46,47	PVCCR	PVCCL 22, 23 – Power supply for left channel H-bridge (tied to pins 14 and 15 internally), not connected to PVCCR or AVCC. PVCCR 38,39 – Power supply for right channel H-bridge (tied to pins 46 and 47 internally), not connected to PVCCL or AVCC. PVCCR 46, 47 – Power supply for right channel H-bridge (tied to pins 38 and 39 internally), not connected to PVCCL or AVCC.
12	REFGND	Ground for gain control circuitry. Connect to AGND. If using a DAC to control the volume, connect the DAC ground to this terminal.
32	RINP	Positive differential audio input for right channel
2	RINN	Negative differential audio input for right channel
27	ROSC	Current setting resistor for ramp generator. Nominally equal to 1/8*
44,45,40,41	ROUTN, ROUTP	Class-D 1/2-H-bridge negative output for right channel ROUTP 40, 41 O Class-D 1/2-H-bridge positive output for right channel
1	SD	Shutdown signal for IC (low = shutdown, high = operational). TTL logic levels with compliance to VCC.
9	VARDIFF	DC voltage to set the difference in gain between the Class-D and VAROUT outputs. Connect to GND or AVDDREF if VAROUT outputs are unconnected.
10	VARMAX	DC voltage that sets the maximum gain for the VAROUT outputs. Connect to GND or AVDDREF if VAROUT outputs are unconnected.
31	VAROUTL	Variable output for left channel audio. Line level output for driving external HP amplifier.
32	VAROUTR	VAROUTR 32 O Variable output for right channel audio. Line level output for driving external HP amplifier.
25	VCLAMPL	VCLAMPL 25 – Internally generated voltage supply for left channel bootstrap capacitors.
36	VCLAMPR	Internally generated voltage supply for right channel bootstrap capacitors.
11	VOLUME	DC voltage that sets the gain of the Class-D and VAROUT outputs.
8	VREF	Analog reference for gain control section.
4	V2P5	2.5-V Reference for analog cells, as well as reference for unused audio input when using single-ended inputs.

TPA3002D2 Internal Diagram:




SM5301AS :

order Butterworth lowpass filter configuration. The filter characteristics have been optimized for minimal overshoot and flat group delay, it has a variable cutoff frequency and guaranteed driver-stage channel gain difference and phase difference values.

Main Features:

- supply voltage: $5V \pm 10\%$;
- _DC voltage level restore sync clamp function
- Output buffer gain switching function: 0, 6dB (input-to-output AC signal gain)
- Channel-to-channel gain difference: 0.5dB($\pm 5\%$ supply voltage variation);
- Channel-to-channel phase difference: 3.5 degree
- Output signal harmonic distortion (all channels): 1.5%
- Cutoff frequency: 5.8 to 37MHz variable

SM5301AS Internal Diagram:



Pin Description:

Pin	Name	Description
2	GSG1	GOUT/UOUT output buffer gain set input
1	GINA/UINA	Analog GINA or UINA signal input. Sync signal is input on SYNCIN pin. Analog GINB or UINB signal input. Sync signal is input on SYNCIN pin.
3	GINB/UINB	
5	BINA/VINA	Analog BINA or VINA signal input. Sync signal is input on SYNCIN pin. Analog BINB or VINB signal input. Sync signal is input on SYNCIN pin
7	BINB/VINB	
6	GSB1	BOUT/VOUT output buffer gain set input
9	DISABLE	Power save function. Built-in pull-down resistor.
10,13,16,19	GND	Ground
11	BOUT/VOUT	B/V signal output
14	GOUT/UOUT	Analog 5V supply
17	ROUT/YINB	R/Y signal output
12,15,18,24	VCC	Analog 5V supply
20	RFC	LPF (lowpass filter) cutoff frequency setting resistor connection
21	VFC	LPF (lowpass filter) cutoff frequency setting voltage input
22	MUXSEL	Input select signal
23	SYNCIN	Filter channel external H-Sync signal input.
26	GSR1	ROUT/YOUT output buffer gain set input
25	RINA/YINA	Analog RINA or YINA signal input. Sync signal is input on SYNCIN pin. Analog RINB or YINB signal input. Sync signal is input on SYNCIN pin.
27	RINB/YINB	

4,8,28	NC	No connection(leave open or connect to ground)
--------	----	--


SAA7115:

The SAA7115 is a video capture device for various applications ranging from small screen products like e.g. digital set top boxes, personal video recording applications to big screen devices like e.g. LCD projectors due to it's improved comb filter performance and 10 bit video output capabilities.

Main Features:

- Six analog inputs, internal analog source selectors;
- Two improved 9 Bit CMOS analog-to-digital converter in differential CMOS style;
- Automatic Clamp Control (ACC) for CVBS, Y and C;
- Enhanced Horizontal and vertical Sync Detection;
- PAL delay line for correcting PAL phase errors;
- Automatic TV/VCR detection;

SAA7115 Internal Diagram:



Pin Function:

Pin	Name	Description
1,8,11,17,23,25,33 43,51,58,68,75,83 93	VDD	Supply voltage port
2	TDO	Test Data Output for Boundary Scan Test (2)
3	TDI	Test Data Input for Boundary Scan Test (with internal pull-up)(2)
4	XTOUT	crystal oscillator output signal, auxiliary signal
6	XTALO	24.576 (32.11) MHz crystal oscillator output; not connected if XTALI is

7	XTALI	driven by an external single-ended oscillator. Input terminal for 24.576 (32.11) MHz crystal oscillator or connection of external oscillator with TTL compatible square wave clock signal.
6	VXDD	Crystal oscillator power supply
10,12,14,16	AI21~AI24	Analog signal input 21~24
13	AI2D	differential input for ADC channel 2 (pins AI24, AI23, AI22, AI21) differential input for ADC channel 1 (pins AI12, AI11)
19	AI1D	
20	AI11	analog input 11
18	AI12	analog input 12
5,9,15,21,24,26,38 50,63,76,88,100	AGND VSS	ground
22	AOUT	Analog test output (do not connect)
27	CE	Chip Enable or RESET input (with internal pull up)
28	LLC	line-locked system clock output (27 MHz nominal), for backward compatibility, do not use for new applications line locked clock/2 output (13.5 MHz nominal) for backward compatibility, do not use for new applications
29	LLC2	
30	RESON	RESet Output Not signal
31	SCL	IIC serial clock line (with inactive output path)
32	SDA	IIC serial data line
34	RTS0	real time status or sync information, controlled by subaddr. “11h and 12h” RTS1 35 O real time status or sync information, controlled by subaddr. “11h and 12h”
35	RTS1	
36	RTCO	Real time control output
37	AMCLK	Audio master clock output
39	ASCLK	Audio serial clock output
40	ALRCLK	Audio left/right clock output
41	AMXCLK	Audio master external clock input
42	ITRDY	Target ready input, image port(with internal pull up)
45	ICLK	clock output signal for image-port, LCLK of LPB image port mode, or optional asynchron. backend clock input
46	IDQ	output data qualifier for image port (<i>optional: gated clock output</i>)
47	ITRI	image-port output control signal, effects all I-port pins incl. ICLK, enable and active polarity is under software control (bits IPE in subaddr. “87”) output path used for Testing : scan output
48	IGP0	

49	IGP1	general purpose output signal 0; image-port (controlled by subaddr. "84", "85") general purpose output signal 1; image-port (controlled by subaddr. "84", "85"), same functions as IGP0
52	IGPV	multi purpose vertical reference output signal; image-port (controlled by subaddr. "84", "85")
53	IGPH	multi purpose horizontal reference output signal; image-port (controlled by subaddr. "84", "85")
54~57,59~62	IPD0~IPD7	image port data output
64~67,69~72	HPD0~HPD7	Host port data I/O, carries UV chrominance information in 16 bit video I/O modes
80	XTRI	X-port output control signal, effects all X-port pins (XPD[7:0], XRH, XRV, XDQ and XCLK) enable and active polarity is under software control (bits XPE in subaddr. "83")
81,82,84,85,89,90,86,87	XPD0~XPD7	expansion-port data expansion-port data
91	XRV	vertical reference I/O expansion-port: In ten bit video output mode: this signal represents the video bit 0.
92	XRH	horizontal reference I/O expansion-port: In ten bit video output mode: this signal represents the video bit 1.
94	XCLK	clock I/O expansion port
95	XDQ	data qualifier I/O expansion port
96	XRDY	task flag or read signal from scaler, controlled by XRQT (subaddr. 83H)
97	TRSTN	Test ReSeT Not for Boundary Scan Test (with internal pull-up); for board design without Boundary Scan connect TRSTN to 'ground'(1)
98	TCK	Test Clock for Boundary Scan Test (with internal pull-up)(2)
99	TMS	Test Mode Select for Boundary Scan Test or Scan Test (with internal pull-up)(2)

UOCIII(TDA15063H):

The UOCIII series combines the functions of a Video Signal Processor (VSP) together with a FLASH embedded TEXT/Control/Graphics -Controller (TCG -Controller) and US Closed Caption decoder.

Main Features:

- DVB/VSF IF circuit for preprocessing of digital TV signals;
- Video switch with 3 external CVBS inputs and a CVBS output;
- Automatic Y/C signal detector;
- Adaptive digital (4H/2H) PAL/NTSC comb filter for optimum separation of the luminance and the chrominance signal;
- Picture improvement features with peaking (with switchable center frequency, depeaking, variable positive/negative peak ratio, variable pre-/overshoot ratio and video dependent coring), dynamic skin tone control, gamma control and blue and black stretching. All features are available for CVBS, Y/C and RGB/YPBPR signals.

The mono intercarrier sound circuit has a selective FM-PLL demodulator which can be switched to the different FM sound frequencies (4.5/5.5/6.0/6.5 MHz). The quality of this system is such that the external band-pass filters can be omitted. In the stereo versions of UOCIII the use of this demodulator is optional for special applications.

Normally the FM demodulators of the stereo demodulator/decoder part are used (see below).

- The FM-PLL demodulator can be set to centre frequencies of 4.72/5.74 MHz so that a second sound channel can be demodulated. In such an application it is necessary that an external bandpass filter is inserted.

- The vision IF and mono intercarrier sound circuit can be used for the demodulation of FM radio signals. With an external FM tuner also signals with an IF frequency of 10.7 MHz can be demodulated. For the QIP90 versions this is valid only for the “stereo” versions

- Built-in adaptable brightness delay circuit

- switchable brightness signal transmission rate


Pin Description:

Pin	Name	Description
1,2,12,18,28,40 68,81,89,92,95,101 121,125	VSS,GND	ground
3,4,45,69,82,88,90, 91,93,94,96,100, 110,117,118,124	VDD	Power supply
5	VREF_POS_LSL	SDAC input signal
6	VREF_NEG_LSL+HPL	
7	VREF_POS_LSR+HPR	
8	VREF_NEG_HPL+HPR	
9	VREF_POS_HPR	
10	XTALIN	Crystal oscillator input
11	XTALOUT	Crystal oscillator output
13	VGUARD/SWIO	V-guard input / I/O switch
14	DECDIG	decoupling digital supply
15	VP1	decoupling digital supply
16	PH2LF	phase-2 filter
17	PH1LF	phase-1 filter
19	SECPLL	SECAM PLL decoupling
20	DECBG	bandgap decoupling
21	EWD/AVL	East-West drive output or AVL capacitor
22	VDRB	vertical drive B output
23	VDRA	vertical drive A output
24	VIFIN1	IF input 1
25	VIFIN2	IF input 2
27	IREF	reference current input
29	SIFIN1/DVBIN1	SIF input 1 / DVB input 1 SIF
30	SIFIN2/DVBIN2	
31	AGCOUT	tuner AGC output

32	EHTO	EHT / overvoltage protection input
33	AVL/SWO/SSIF/REFO/REFIN	Automatic Volume Levelling / switch output reference output / external reference signal DVB operation
34	AUDIOIN5L	audio-5 input (left signal)
35	AUDIOIN5R	audio-5 input (right signal)
36	AUDOUTSL	audio output for SCART/CINCH (left signal)
37	AUDOUTSR	audio output for SCART/CINCH (right signal)
38	DECSDEM	decoupling sound demodulator
39	QSSO/AMOUT/AUDEEM	QSS intercarrier output / AM output / deemphasis
41	PLLIF	PLL filter
42	SIFAGC/DVBAGC	AGC sound IF / internal-external AGC for DVB applications
43	DVBO/IFVO/FMRO	Digital Video Broadcast output / IF video output
44	DVBO/FMRO	
46	AGC2SIF	AGC capacitor second sound IF
47	VP2	2nd supply voltage TV processor (+5 V)
48	IFVO/SVO/CVBSI	video output / selected CVBS output / CVBS
49	AUDIOIN4L	audio-4 input (left signal)
50	AUDIOIN4R	audio-4 input (right signal)
51	CVBS4/Y4	CVBS/Y input
52	C4	chroma-4 input
53	AUDIOIN2L/SSIF	Audio input
54	AUDIOIN2R	
56	AUDIOIN3L	
57	AUDIOIN3R	
30	AUDOUTLSL	
61	AUDOUTLSR	
62	AUDOUTHPL	
63	AUDOUTHPR	
58	CVBS3/Y3	CVBS/Y input
59	C2/C3	chroma-2/3 input
55	CVBS2/Y2	CVBS/Y input
64	CVBSO/PIP	CVBS/PIP signal output
65	SVM	scan velocity modulation output
66	FBISO/CSY	flyback input/sandcastle output or composite H/V
67	HOUT	horizontal output
70	VIN (R/PRIN2/CX)	V-input for YUV interface
71	UIN (B/PBIN2)	U-input for YUV interface
72	YIN (G/YIN2/CVBS-YX)	Y-input for YUV interface
73	YSYNC	Y-input for sync separator
74	YOUT	Y-output (for YUV interface)
75	UOUT (INSSW2)	U-output for YUV interface
76	VOUT (SWO1)	V-output for YUV interface
77	INSSW3	3rd RGB / YPBPR insertion input

78	R/PRIN3	3rd R input / PR input
79	G/YIN3	G input / Y input
80	B/PBIN3	3rd B input / PB input
83	BCLIN	beam current limiter input
85	RO	Red output
86	GO	Green output
87	BO	Blue output
97	INT0/P0.5	external interrupt 0 or port 0.5 (4 mA current sinking direct drive of LEDs)
98,99,102~109 111~116,119,120 122,123,126~ 128	P0.0~ P0.4 P1.0~P1.7,P2.0~P2.5, P3.0~P3.3	Data port

UOCIII Internal Diagram:



CHAPTER THREE SIGNAL FLOW ANALYSIS AND KEY POINT MEASURE DATA

The chapter mainly introduces the receipt and dispose of the AV signal , the power supply system and system control process of this TV.

Signal Flow Analysis

1.Video signal flow:

the AV/S and IF signal which is demodulated by main demodulator are sent by TV plank into video decode chassis UOCIII for decoding ,then the output analog video signal is sent into analog-to-digital converter TDA8759HV/8/C1 for A/D transform to produce R、 G、 B digital signals which are transformed in format by GM1601/GM1501, then, it transformed the different input formats into the uniform up-screen signal format.

The signal demodulated by sub demodulator is directly sent into submenu video decoder SAA7115HL/V1 for video decoding and A/D conversion, then again sent into GM1601/GM1501 to do format transform, the output up-screen is used for submenu display.

After selection, the PC、 HDTV(YPBPR) and DVI signals are sent directly into GM1601/GM1501 for processing to form uniform up-screen signal.

2.Accompanying sound flow:

TV accompanying sound: RF signal is demodulated by main demodulator to SIF(companying sound intermediate frequency) signal, SIF is sent into UOCIII for demodulation and sound disposal, then, the output audio signal is zoomed in by D class TPA3002D2PHPR and is sent into the speaker at last.

AV accompanying sound: the audio signal input by AV is directly disposed by UOCIII and zoomed in by TPA3002D2PHPR,then transported to the speaker.



After the accompanying sound of PC、 DVI、 YPbPr are selected by MC74LVX4052DR2 , then they are disposed by UOCIII and zoomed in by TPA3002D2PHPR to make the speaker work.


3.、 TV power supply system:

4 channels voltage are transported from the power supply board, they are +24V, +12V, +5V and +5VS. +24V is provided for inverter of LCD panel, +12V is provided for PA, +5V is transformed by the manostat into 3.3V、 2.5V and 1.8V for IC, it may be turned down under standby mode, while +5VS is provided for MCU、 infrared receiver、 EEPROM.

5V is divided into two ways, one way is provided for other IC and apparatus, the 5V will be turned down under standby mode, but can not be cut off.. The other 5V is provided for MCU、 infrared receiver、 EEPROM and so on, it would not be cut off under standby mode.

The composition and distribution of the TV power supply: (please see the next page)






The Manostat Pin Voltage in Main Board Schedule

Name	Type	PIN1(V)	PIN2(V)	PIN3(V)	PIN4(V)	PIN5(V)
UP7	LM1117-1.8V	0	1.8	5	1.8	
UP1	LM1117-3.3V	0	3.3	5	3.3	
UP6	LM2596-5.0	24	5	0	5	0
U405	LM1117-3.3	0	3.3	5	3.3	
U3	78M08	12	0	8		
U403	LM1117-1.8V	0	1.8	5	1.8	
U503	LM1806-3.3	0	3.3	5	3.3	
U505	LM1117-2.5	0	2.5	5	2.5	
U506	LM1117-3.3	0	3.3	5	3.3	
U501	LM2596-5.0	12	5	0	5	
U502	LM2596-5.0	24	5	0	5	0
U504	LM1117-1.8V	0	1.8	5	1.8	

Main Components and Socket Locations and Definitions:



Outlet Definition:

Number	Name	Connected Object	Function Description
1	JP5	TV plane	
2	JP2	Side AV	
3	JP6	DVD AV output	
4	JP7	Speaker	
5	JP8	loudhailer	
6	JP4	DVD decode board	
7	JP3	outside AV input	
8	JP9	Up screen(screen inverter input)	
9	JP10	Up screen(screen inverter input)	
10	JP12	power supply plane	GND, GND, GND, +12V, +12V, +12V


11	J171	Prepare to use	
13	JP11	power supply plane	+12V, +12V, GND, GND, GND, GND, 24V, 24V
14	JP1	power supply plane	SB, GND, GND, 5V, 5V, 5V, GND, GND, 12V, 12V
15	J700	Prepare to use	
16	CN702	Prepare to use	
17	CN700	remote control	
18	CN701	K plane	
19	CN304	Prepare to use	
20	CN303	Prepare to use	
21	JP701	display	
22	CN306	Prepare to use	
23	AVP303	DVI audio input	
24	CN300	DVI port	
25	AVP300	VGAaudio input	
26	CN301	VGA port	

Main Components explanation:


Number	Name	Components	Function Description
A	U201	TDA15063H-N1B06557	Audio/video decoder
B	U400	TDA8759HV/8/C1	Video signal AD converter
C	U402	SAA7115HL/V1	Sub channel video decoder
D	U600	MT46V2M32LG-4	Frame buffer memorizer
E	U700	GM1601/GM1501-BD	Video processor
F	U305	SM5302AS-G-ET	HD signal filter
G	U801	AM29LV800DT-70EC	Flash, the TV control procedure put in it
H	U6	TPA3002D2PHPR	Audio PA
I	U5	TDA9178T/N1	Video signal image improve
J	K202	K9352N	Sound surface filter
K	K201	K7262N	Sound surface filter
L	UA3	FSAV330QSCX	Select switch
M	U701	24LC32A T/SN	Buffer
N	U307	FSAV330QSCX	Select switch
O	U306	FSAV330QSCX	Select switch
P	U302	24LC21A T/SN	EEPROM
Q	U303	24LC21A T/SN	EEPROM

Main Point Wave Picture:


1 RF input color stripe signal, TV signal wave in the 19th pin of sub tuner UT1, The wave of the 10th of SAA7115 also like this:




2 RF input color stripe signal,the Pin85,Pin86,Pin87 of U201 output R,G,B signal wave,the E pole wave of Q171,Q172,Q173:



3 RF input color stripe signal, I²C bus clock signal UOCIII_SCL, the wave of the 98th pin of U201,the 11th pin of U5,the 4th pin of parent/sub RF tuner:





.4 RF input color stripe signal, UOC vertical sync signal, the wave of the 22th pin of U201,the 105th pin of U400:




.5 RF input color stripe signal, UOC vertical sync signal , the wave of the 22th pin of U201,the 105th pin of U400:


RF input color stripe signal, UOC vertical sync signal , the wave of the 22th pin of U201,the 105th pin of U400:



.6 RF input gray ladder signal, the TV signal wave in the 19th pin of SAA7115:
The wave in the 10th of SAA7115 also like this:




7 The 1KHz sound signal input, the wave of the 60th、61th pin of U201, the wave of the 2th、6th pin of U6 also like this:



8 The 1KHz sound signal input, the wave of 16th、17th、20th、2140th、41th、44th、45th pin of U6 and pins:

CURSORS



Location No.	Type	PIN1(V)	PIN2(V)	PIN3(V)	PIN4(V)	PIN5(V)
UP7	LM1117-1.8V	0	1.8	5	1.8	
UP1	LM1117-3.3V	0	3.3	5	3.3	
UP6	LM2596-5.0	24	5	0	5	0
U405	LM1117-3.3	0	3.3	5	3.3	
U3	78M08	12	0	8		
U403	LM1117-1.8V	0	1.8	5	1.8	
U503	LM1806-3.3	0	3.3	5	3.3	
U505	LM1117-2.5	0	2.5	5	2.5	
U506	LM1117-3.3	0	3.3	5	3.3	
U501	LM2596-5.0	12	5	0	5	
U502	LM2596-5.0	24	5	0	5	0
U504	LM1117-1.8V	0	1.8	5	1.8	

CHAPTER FOUR SYMPTOMS AND CORRECTION

Symptom One: Display card of PC no image in DVI.

Reason and Resolve: If some display card of DVI can not receive the data when turning on the TV, there is no output; if pull out the DVI line abruptly, there is also no DVI output; Before starting PC, connect the DVI line with LCD TV steadily, So DVI can receive the correct date from DDC (Display Data Channel) when turning on the TV,DDC is in chassis 24LC21.

Symptom Two: No picture but sound, on LOGO when turning on the TV, background light is bright.

Reason and Resolve: Check the connect line in up screen, and connect the line.

Symptom Three: No picture、no sound ,no snowflake in TV mode, but AV is normal.

Reason and Resolve: Check the outside of high frequency (also bus and power supply), there is no problem ,but no output from high frequency, so the tuner is disabled.

Symptom Four: LCD TV can not be controlled.(inc red lamp is on but the TV is off, remote control and local keys can not control the TV ,etc.)

Reason and Resolve: the LCD TV can not work abruptly, power off and turning it on again.

CHAPTER FIVE BREAKABLE AND MAINTENANCE PARTS

This list is provided for reference, all the parameters of those maintenance parts are subject to change without notice for future improvement, please refer the latest models and specifications as the standard.

CHD-260F8

NO.	Name	Assembly Code	Assembly Number	PCB Number	Breakable Ratio (%)
1.	Front frame	8807400311J	JUJ8.074.031-1		0.1
2.	Faceplate	8808100160J	JUJ8.081.016		0.1
3.	Back cover	8807400501J	JUJ8.074.050-1		0.1
4.	Base decoration board	8735600050J	JUJ7.356.005		0.1
5.	Base	8807000130J	JUJ8.070.013		0.1
6.	Main board assembly	86690003521J	JUJ6.690.035-21	PCB JUJ7.820.088	1
7.	AV board assembly	8669300150J	JUJ6.693.015	PCB JUJ7.820.103	0.5
8.	TV board assembly	8669700040J	JUJ6.697.004	PCB JUJ7.820.128	1
9.	Remote receive board assembly	8669400180J	JUJ6.694.018	PCB JUJ7.820.104	0.5
10.	Key-press board assembly	8669400190J	JUJ6.694.019	PCB JUJ7.820.091	0.5
11.	Buttons	8833700110J	JUJ8.337.011		0.1
12.	Built-in power supply module	67128017905	FSP179-4F01		0.1
13.	TFT panel	68212600105	LC260W01		1
14.	Electronic tuner	8289100454E	TAD5-C2IP1RW		1
15.	Electronic tuner	8289100063E	TMI4-C22P2RW(JU E2.891.006-3)		2
16.	Electric speaker	56224605080	Y2929-01-5W-8Ω		2
17.	Electric speaker	562D6608082	Y50138-01-8W-8Ω		1
18.	Remote controller				

CHD-W320F8

NO.	Name	Assembly Code	Assembly Number	PCB NO.	Breakable Ratio (%)
1	Front frame	8807400410J	JUJ8.074.041		0.1
2	Back cover	8807400422J	JUJ8.074.042-2		0.1

3	Base decoration board	8735600040J	JUJ7.356.004		0.1
4	Base	8807000160J	JUJ8.070.016		0.1
5	Main board assembly (LG screen)	8669000350J	JUJ6.690.035	PCB JUJ7.820.088	1
6	Main board assembly (SAMSUNG screen)	8669000354J	JUJ6.690.035-4	PCB JUJ7.820.088	1
7	AV board assembly	8669300150J	JUJ6.693.015	PCB JUJ7.820.103	0.5
8	TV board assembly	8669700040J	JUJ6.697.004	PCB JUJ7.820.128	1
9	Remote receive board assembly	8669400180J	JUJ6.694.018	PCB JUJ7.820.104	0.5
10	Key press board assembly	8669400190J	JUJ6.694.019	PCB JUJ7.820.091	0.5
11	Buttons	8833700110J	JUJ8.337.011		0.1
12	Built-in power supply module	67128017905	FSP179-4F01		0.1
13	TFT panel	68219632010	LC320W01	LG screen	
14	Electronic tuner	8289100063E	TMI4-C22P2RW		1
15	Electronic tuner	8289100454B	TAD5-C2IP1RW		1
16	Electric speaker	56224605080	Y2929-01-5W-8Ω		2
17	Electric speaker	562D6608082	Y50138-01-8W-8Ω		2
18	Remote controller		KLC5A		1

CHD-W370F8

NO.	Name	Assembly Code	Assembly Number	PCB NO.	Breakable Ratio (‰)
1	Frame	8807400430J	JUJ8.074.043		0.1
2	Back cover	8807400442J	JUJ8.074.044-2		0.1
3	Base	8807000160J	JUJ8.070.016		0.1
4	Main board assembly	8669000354J	JUJ6.690.035-9	PCB JUJ7.820.088	1
5	AV board assembly	8669300150J	JUJ6.693.015	PCB JUJ7.820.103	0.5
6	TV board assembly	8669700040J	JUJ6.697.004	PCB JUJ7.820.128	1
7	Remote receiver board assembly	8669400200J	JUJ6.694.020	PCB JUJ7.820.104	0.5
8	Key press board assembly	8669400240J	JUJ6.694.024	PCB JUJ7.820.091	0.5
9	Built-in power supply module	67128024105	FSP241-4F01		5
10	TFT panel	68213700105	LC370W01		0.1
11	Suspending screen	886400063E	TMI4-C22P2RW		0.1
12	Electronic tuner	8289100063E	TMI4-C22P2RW		1
13	Electronic tuner	8289100454E	TAD5-C2IP1RW		1

14	Sound boxes	56232971081	Y3297-L-10W-8 Ω		1
15	Sound boxes	56232971082	Y3297-R-10W-8 Ω		1
14	Electric speaker	56232971082	Y3297-R-10W-8 Ω		1
15	Electric speaker	56239390580	Y3939-01-5W-8 Ω		2
16	Remote controller	8201803510L	KLC5A		1

DVD maintenance parts(only for models with DVD module):

DVD touch key label	8661800060J	JUJ6.618.006	
DVD output board assembly	8669300120J	JUJ6.693.012	
DVD decoding board assembly	8669300130J	JUJ6.693.013	
Converter board assembly	8669100080J	JUJ6.691.008	
DVD driver	59C11060850	TDR-085	

CHAPTER SIX FACTORY MODE AND NOTICE

Enter into factory menu

1. Enter into child lock of main menu in TV mode, press “OK, the password input box will appear;
2. Use remote control to input the follows in order:7,red key,9,blue key, then you can enter into factory mode menu. After entering into factory mode menu, sign of the factory menu M will appear.

factory menu and setup

1. factory menu display is below:

M

Index: 1

HWUC_BRI 0x1F

The M denotes entering into factory mode now, the figures of index denotes the index number now,the HWUC_BRI denotes the name of adjusting item now, the 0X1F denotes the numerical value.

2. Each adjusting item have only one index number ,the operator press the numeric key or press P+/P- directly.

3. Optional and adjustable items, the corresponding relation of index number and adjusting item is below:

(Index)	Name	Item Meanings	Operating Key	Remark
1	HWUC_BRI	UoclIII subsidiary brightness	V+/V-	Adjust subsidiary brightness
2	HWUC_SAT	UoclIII saturation	V+/V-	Adjust subsidiary saturation
3	HWUC_CON	UoclIII contrast	V+/V-	Adjust subsidiary contrast
4	HWUC_AGC	UoclIII AGC	V+/V-	Adjust AGC
5	PIP Brightness	7115 subsidiary brightness	V+/V-	Activate sub picture When adjusting it
6	PIP VGA	7115 contrast	V+/V-	Activate sub picture When

	Contrast			adjusting it
7	Balance	Sound balance	V+/V-	The tuning value is 50, -50, 0
8	Volume	Sound Volume	V+/V-	Step is 10
9	Sound System	Sound System	V+/V-	DK/I/BG/M
10	Auto Search	Auto searching	V+/ok	Source of Signal is TV
11	White Balance	White balance	V+/ok	
12	AutoColor	Auto color revise	V+/ok	Source of Signal VGA /YpbPr /TV
13	DVD	DVD preset	V+/V-	1 represents preset
14	BBE	BBE preset	V+/V-	1 represents preset
15	TruSurround	TruSurround preset	V+/V-	1 represents preset
16	SALESFOR	SALESFOR	V+/V-	Set the target country
17	Factory Out	initialization	V+/ok	Leave factory set
18	Clear EEPROM	initialize EEPROM	V+/ok	Initialize the storage date
19	D Mode	Enter into design mode	V+/ok	Adjustable design mode all the parameter
20	DPF	DPF preset	V+/V-	1 represents preset
21	BBE_CONT	BBE plus set	V+/V-	Adjust BBE plus
22	BBE_PROC	BBE plus set	V+/V-	Adjust BBE plus
23	Newcom	Newcom set	V+/V-	1 represents preset

notice:

- 1、if no especial demand, please do not enter into the 20th item(design mode);
- 2、when tuning the 16th item ,the storage data will be cleaned off, therefore, if not necessary ,please do not adjust it, the items of index number 1,2,3,4,5,6 are not necessary to adjust.

Adjustment methods for factory menu

1. Select the adjusting item

You can skip to the adjusting items by pressing the number key, also can select the adjusting item in the order of P+/P-.when pressing the number key, if the adjusting item is 1~9,input the corresponding number keys and press down “OK”, if the adjusting items tens digit, input a tens digit. For example ,press number key 8 when adjusting the volume, you can see the color which become green, then press down “OK”, the color of index number turns red, So you already selected corresponding volume adjusting item.

If adjust DVD preset, first input 1,then input 3,you can adjust DVD preset.

2. Adjustment methods

Adjust it according to the operating key in above list. For one act operation ,press OK/V+.
example Auto Color, for some variable add/reduce, Example Volume, press V+/V- .

3. The illuminate of white balance and AutoColor adjustment method

Index 11 is corresponding to manual balance ,press “OK” or “V+” to display three corresponding variable, press “P+/P-”to select, press “V+/V-” to adjust, press down menu key to exit.

The index of AutoColor is 12,press “OK”or “V+” to do color revision, then the adjusted value will display.

4. BBE plus adjustment

Index number of BBE plus adjustment is 22 and 23, adjust it by adjusting "V+/V-", the value of W270F8E and W320F8E are set 0X09, but the W370F8E is set 0X0F.

5. Press down the【DISPLAY】 first before switching the program number in factory mode, press P+/P- to switch before the display content do not disappear;

6. All menu functions are on in factory mode, if necessary you can use menu to check the items and effect test.

Factory debug item

1. Auto color revise (AutoColor)

Firstly finish auto color revise first before factory debug. Revise in TV、YPBPR and PC respectively.

① Requisite Meter

PC one

HD signal source one

② Debug (Revise in TV、YPBPR and PC respectively)

Park the channel in C-3 under TV mode TV, then do AutoColor.

Input color stripe signal in YPBPR and do AutoColor.

Input window signal in PC, the window is white, black signal around.

The result will appear in screen after AutoColor adjustment, make the adjustment results of Rgain、

Ggain and Bgain close to 0×80 , if the difference is too great, adjust the value of

HWUC_CON(auxiliary saturation), and readjust the AutoColor.

2. White balance, color temperature adjustment

① Requisite Meter

CHROMA 7120 color analyze instrument (or same function instrument, contain color coordinate – chroma diversion card) one

White balance adjusting frock (request the video output range 0-1V is adjustable, 750hm load) one

② Prepare

A. connect all equipments, switch the condition of LCD TV to AV.

B. Set the picture of LCD TV for standard condition

C. Set the distance of light receiver of white balance from center place of LCD display screen for $15\text{cm} \pm 3\text{cm}$.

D. Make sure that the environmental brightness is below 2cd/m^2 .

③ White balance, color temperature adjustment

Before adjusting it, put the first LCD TV in AV condition, and the image in standard condition, white balance adjust frock send the white vertical signal output from video into AV, adjust output range of balance adjust frock, make the brightness of the LCD TV $200 \pm 20\text{cd/m}^2$ (use CHROMA 7120 color analyze instrument to obtain the brightness), then fix the video output range of white balance adjust frock (until all the LCD TV are adjusted).


Enter into white balance adjusting item of factory mode, change R,G,B value (try best to adjust this 3 value biggest).


Make color temperature coordinate value accord with that of the table below (error value within $\pm 4\%$) :


Z	X	Y
---	---	---



K12000	0.270	0.277
--------	-------	-------

Note: The color temperature and color coordinate are contented for above request, you should judge the exist of color windage phenomenon, namely the value of Δuv is 0 or not
If Δuv is not 0 , readjust R,G,B value to 0,and meet color coordinate request.












Pin	Function
1	COMA/NO1A, COMB/NO1B
2	COMA/NO1A, COMB/NO1B
3	COMA/NO1A, COMB/NO1B
4	COMA/NO1A, COMB/NO1B
5	COMA/NO1A, COMB/NO1B
6	COMA/NO1A, COMB/NO1B
7	COMA/NO1A, COMB/NO1B
8	COMA/NO1A, COMB/NO1B
9	COMA/NO1A, COMB/NO1B
10	COMA/NO1A, COMB/NO1B
11	COMA/NO1A, COMB/NO1B
12	COMA/NO1A, COMB/NO1B
13	COMA/NO1A, COMB/NO1B
14	COMA/NO1A, COMB/NO1B
15	COMA/NO1A, COMB/NO1B
16	COMA/NO1A, COMB/NO1B
17	COMA/NO1A, COMB/NO1B
18	COMA/NO1A, COMB/NO1B
19	COMA/NO1A, COMB/NO1B
20	COMA/NO1A, COMB/NO1B
21	COMA/NO1A, COMB/NO1B
22	COMA/NO1A, COMB/NO1B
23	COMA/NO1A, COMB/NO1B
24	COMA/NO1A, COMB/NO1B
25	COMA/NO1A, COMB/NO1B
26	COMA/NO1A, COMB/NO1B
27	COMA/NO1A, COMB/NO1B
28	COMA/NO1A, COMB/NO1B
29	COMA/NO1A, COMB/NO1B
30	COMA/NO1A, COMB/NO1B
31	COMA/NO1A, COMB/NO1B
32	COMA/NO1A, COMB/NO1B
33	COMA/NO1A, COMB/NO1B
34	COMA/NO1A, COMB/NO1B
35	COMA/NO1A, COMB/NO1B
36	COMA/NO1A, COMB/NO1B
37	COMA/NO1A, COMB/NO1B
38	COMA/NO1A, COMB/NO1B
39	COMA/NO1A, COMB/NO1B
40	COMA/NO1A, COMB/NO1B
41	COMA/NO1A, COMB/NO1B
42	COMA/NO1A, COMB/NO1B
43	COMA/NO1A, COMB/NO1B
44	COMA/NO1A, COMB/NO1B
45	COMA/NO1A, COMB/NO1B
46	COMA/NO1A, COMB/NO1B
47	COMA/NO1A, COMB/NO1B
48	COMA/NO1A, COMB/NO1B
49	COMA/NO1A, COMB/NO1B
50	COMA/NO1A, COMB/NO1B


File	Number	Revision
Orcaid D	13-01-2005	Rev. 1
Author	13-01-2005	Rev. 1
Editor	13-01-2005	Rev. 1
Checker	13-01-2005	Rev. 1
Approver	13-01-2005	Rev. 1















Title		
Size	Number	Revision
C		
Date	13-Apr-2005	Sheet of
File	F:\NSP\RMU_P00\VI_Tech\U500_MAIN_00000002721.dwg	




Title		
Size	Number	Revision
A4		
Date:	13-Apr-2005	Sheet of
File:	E:\USER\MNL\PO8\YLT-chn\LS08 MAIN TD\075020050223.Dcb	075020050223.Dcb





Component Video Inputs




Title			
Size B	Number MUX/CONNECTORS		Revision
Date: 13-Apr-2005	Sheet of File: F:\SERIAL POINT\T-Box\SOB\SOB.dtb		








Title		
Size	Number	Revision
A4		
Date:	13-Apr-2005	Sheet of
File:	E:\USER\MNL\P08\YLT-chn\LS08#板-CHINA\02\add by	Drawn By:





Title		
FSP-GROUP		
Size	Number	Revision
A3	FSP205-4E01	
Date:	21-Feb-2006	Sheet of
File:	E:\中间图\FSP205-4E01\CIRCUIT\FSP205-4E01.Ddb	IT (FL)Ddb