

SERVICE MANUAL
CRT DISPLAY
FE2111SB / FE2111SB-BK
(C22BW701)

NEC-MITSUBISHI ELECTRIC VISUAL SYSTEMS CORPORATION
SEPTEMBER 2002

CBB-S5778

X-RADIATION WARNING

The surface of picture tube may generate X-Radiation.

Precaution during servicing, and if possible use of a lead apron or metal for shielding is recommended. To avoid possible exposure to X-Radiation and electrical shock hazard, the high voltage compartment and the picture tube shield must be kept in place whenever the chassis is in operation.

When replacing picture tube use only designated replacement part since it is a critical component with regard to X-Radiation as noted above.

CRITICAL COMPONENT WARNING

- In the schematic diagram/parts list, the components marked "  " are critical components for X-ray radiation.

When replacing these parts, use exactly the same one indication in parts list.

- If one or some of the components listed below are replaced, the high voltage and the operating voltage of high voltage hold-down circuit must be re-adjusted according to Clause 2.4 ADJUSTMENT on page 2-6 :

T701, IC102, IC104, R706, R707

Contents

1. Circuit description	1-1
1.1 Power block	1-1
1.1.1 Outline	1-1
1.1.2 Rectifying circuit and higher harmonics suppression (active filter) circuit	1-1
1.1.3 Sub power circuit	1-2
1.1.4 Main power circuit	1-2
1.1.5 Demagnetizing circuit	1-2
1.1.6 Power management circuit	1-2
1.2 Deflection processor block	1-3
1.2.1 Deflection processor (IC601)	1-3
1.2.2 Pressure-reduction type horizontal deflection power circuit (IC5C0)	1-3
1.2.3 Horizontal width control circuit	1-3
1.2.4 Vertical deflection circuit	1-3
1.2.4.1 Sawtooth waveform generation, vertical size/position control, and linearity control circuit	1-3
1.2.4.2 Vertical output amplification circuit	1-4
1.2.5 High voltage block	1-4
1.2.6 DBF (Dynamic Beam Focus) circuit	1-5
1.3 Video block	1-6
1.3.1 Video signal amplifier circuit	1-6
1.3.1.1 Video clamp	1-6
1.3.1.2 Video blanking	1-6
1.3.1.3 Video mixing/amplifying	1-6
1.3.1.4 Control of contrast and white balance	1-6
1.3.2 Cut-off control circuit	1-7
1.3.2.1 Control of brightness	1-7
1.3.2.2 Control of BIAS	1-7
1.3.3 OSM (On Screen Manager)	1-7
1.3.4 Asset circuit	1-8
1.3.5 AUTO-SIZE function	1-8
1.3.6 SB MODE (Super Bright Mode) function	1-8
1.3.6.1 Adjustment item/operating function in selecting SB Mode	1-8
1.3.6.2 Circuit (cathode) operation in selecting SB Mode [Window pattern] ..	1-9
1.3.6.3 SB Mode setting data and control method	1-9
1.3.7 CONSTANT BRIGHTNESS function	1-9
1.4 CRT compensation block	1-10
1.4.1 Rotation circuit	1-10
1.4.2 Corner purity circuit	1-10
1.4.2.1 Corner purity circuit operation	1-11

1.4.3 Digital dynamic convergence clear (DDCC) circuit	1-11
1.4.3.1 Production of compensation current waveform	1-11
1.4.3.2 Waveform, and operation on the picture	1-12
1.4.3.3 Adjustment method	1-12
1.4.3.4 Block diagram	1-12
1.5 Control block.....	1-17
1.5.1 Function of control circuit	1-17
1.5.2 Auto-tracking process	1-17
1.5.3 EEPROM	1-17
1.5.4 On-Screen-Manager (OSM) controller	1-17
1.5.5 Heater voltage control.....	1-17
1.5.6 Protection circuit operation	1-17
1.5.6.1 X-ray protector	1-17
1.5.6.2 High voltage data error detection	1-18
1.5.6.3 Beam current protector	1-18
1.5.6.4 Power-On Indicator (LED) flickering pattern in each protector operating	1-18
1.5.6.5 Operating time	1-18
1.5.6.6 The DDC communication.....	1-18
1.5.6.7 Microcomputer pin assignment	1-19
1.6 Safety protection circuit and X-ray protection circuit	1-20
1.6.1 X-ray protection circuit.....	1-20
1.6.2 Beam current protection circuit	1-20
1.6.3 IC701 overcurrent protection circuit	1-20
1.6.4 IC701 overload protection circuit	1-20
1.6.5 IC902 overcurrent protection circuit	1-20
1.6.6 Short-circuit protection circuit on secondary power side	1-20
1.6.7 Overvoltage protection circuit	1-20
1.7 Adjustment	1-21
1.7.1 Adjustment mode	1-21
1.7.2 User mode (Normal mode)	1-21
1.7.3 Factory mode.....	1-24
1.7.3.1 How to entering to Factory mode	1-24
1.7.3.2 How to cancel Factory mode	1-24
1.7.3.3 How to enter FACTORY-HV mode	1-24
2. Adjustment procedure	2-1
2.1 Measuring instruments	2-1
2.2 Preparatory inspections	2-1
2.3 Names of each monitor part	2-2
2.3.1 Configuration of front control panel	2-2
2.3.2 Configuration of rear input connector (signal input)	2-2

2.3.3 OSM display matrix	2-3
2.3.3.1 User mode	2-3
2.3.3.2 Factory mode	2-4
2.4 Adjustment	2-7
2.4.1 How to select the factory adjustment (FACTORY) mode	2-7
2.4.1.1 Selecting with front panel switches	2-7
2.4.2 Adjustments before aging	2-7
2.4.2.1 Adjusting the high voltage and high voltage protector	2-7
2.4.2.2 FOCUS adjustment (Rough adjustment)	2-8
2.4.2.3 Shock test	2-8
2.4.2.4 Preadjustment before aging	2-8
2.4.2.5 Adjusting the landing (ITC/4 corner purity adjustment)	2-9
2.4.3 Adjusting the picture size, position and distortion, DBF amplitude and phase	2-9
2.4.3.1 Adjusting the picture inclination	2-9
2.4.3.2 Adjusting the back raster position	2-9
2.4.3.3 Adjusting the left/right distortion, picture width, picture position (LEFT/ RIGHT) and vertical linearity (all preset)	2-10
2.4.3.4 Adjusting the DBF amplitude and phase	2-10
2.4.4 Adjusting the cut off	2-11
2.4.4.1 Adjusting BTCEN (BRIGHT-CENT), BTMAX (BRIGHT-MAX) and BS1 (BIAS-H)	2-11
2.4.4.2 Adjusting BS2 (BIAS-M) / BS3 (BIAS-L)	2-12
2.4.5 Setting CONSTANT BRIGHTNESS circuit (Factory mode)	2-13
2.4.5.1 Reading beam current default data	2-13
2.4.5.2 Confirming CONSTANT BRIGHTNESS function	2-13
2.4.6 Adjusting the RGB drive signal	2-13
2.4.6.1 Adjusting GN1 (GAIN-H) (adjustment of 9300K)	2-13
2.4.6.2 Adjusting ABL	2-15
2.4.7 Adjusting the focus	2-15
2.4.8 Adjusting the convergence	2-16
2.4.8.1 Adjusting with ITC	2-16
2.4.8.2 Adjusting DDCP	2-18
2.4.9 Default settings (With factory mode)	2-23
2.5 Inspections (In normal mode)	2-24
2.5.1 Electrical performance	2-24
2.5.1.1 Withstand voltage	2-24
2.5.1.2 Grounding conductivity check	2-24
2.5.1.3 Degaussing coil operation	2-24
2.5.1.4 IPM OFF MODE function operation (Set the AC power input to 230V)	2-24
2.5.1.5 Confirming the GLOBAL SYNC (CORNER-Purity) function	2-25
2.5.1.6 Focus, picture performance	2-25

2.5.1.7 Misconvergence	2-25
2.5.1.8 Picture distortion	2-26
2.5.1.9 Linearity	2-28
2.5.1.10 Adjustment value list	2-29
2.5.1.11 Checking the functions during Composite Sync input	2-30
2.5.1.12 Confirming the reset operation	2-30
2.5.1.13 Confirming the full white luminance/color coordination	2-30
2.5.1.14 Confirming CONVERGENCE compensation function	2-30
2.5.1.15 Confirming ROTATION compensation function	2-30
2.5.1.16 Luminance/color coordination uniformity	2-30
2.5.1.17 Confirming the color tracking	2-31
2.5.1.18 CRT installation position	2-31
2.5.1.19 Confirming SB MODE operation	2-31
2.5.1.20 Confirming AUTO-ADJUST operation	2-32
2.5.1.21 Others	2-32
2.6 DDC function, check of asset management	2-33
2.6.1 DDC write data contents	2-34
2.6.2 Self-diagnosis shipment setting	2-35
2.7 Default inspection	2-35
2.7.1 Default setting of switches	2-35
2.7.2 Default setting of OSM	2-35
2.7.3 Checking the labels	2-35
2.7.4 Packaging	2-35
2.8 Degaussing with handy-demagnetizer	2-36
2.8.1 General precautions	2-36
2.8.2 How to hold and use the handy-demagnetizer	2-36
2.9 Caution	2-36
2.10 Timing chart	2-37
2.11 Adjustment timing	2-38

3. Trouble shooting

4. Wave form

5. Schematic diagram

6. Removal Instruction Sheet of Bezel and Back cover

7. Exploded view/Packing view

<Appendix>

Serial number information

Specification

User's guide

All parts list

1. Circuit description

1. 1 Power block

1.1.1 Outline

The power block is compatible with the business electric power, 100 to 120VAC/220 to 240VAC (50/60Hz). The active filter circuit is adopted to suppress the higher harmonic current.

The circuit block is composed of two switching regulators, the main power which is the configuration used the flyback converter system of pseudo resonance operation and the sub power which is the configuration used PWM (pulse wise modulation) system.

The output on the secondary side is shown in Table 1.

Power block	Output voltage	Mai load
Main power side	+215V	H. deflection circuit, Cu-off circuit
	+80V	Video circuit, DBF circuit, High voltage circuit
	+15V	H. deflection circuit, Rotation circuit
	-15V	Convergence circuit, Corner purity circuit
	+12V	Video circuit, H. deflection circuit
	+8V	Heater
Sub power side	+5V	Microcomputer (MPU)
	P-OFF+5V	VIDEO circuit

Table 1

1.1.2 Rectifying circuit and higher harmonics suppression (active filter) circuit

The AC input voltage is rectified in the full wave mode with the diode bridge in D901 and input to pin 5 of L903. The voltage of both end of C911 is the DC voltage approx. 390VDC boosted with the booster circuit (active filter circuit) composed of IC901, Q901, L903 and D902. The active filter circuit compares the voltage input to pin 1, pin 3 and pin 4 of IC901 and controls Q901 ON/OFF period so that the current flows to L903 be sine-waved. The AC input current is sine-waved in the same phase with the input voltage so as to improve the power factor, and the harmonic current is controlled consequently.




Fig. 1

1.1.3 Sub power circuit

When the power switch is turned ON, the rectified and smoothed DC voltage ($AC \text{ voltage} \times \sqrt{2}$) is supplied to pin 5 of IC903, and is charged to C930 through pin 1. When pin 1 reaches 5.7V, oscillation is started in IC903, and the built-in output FET is put into operation to add the pulse voltage between pin 5 and pin 3 on the primary side of T902. The flyback voltage in proportion to the voltage on the primary side is generated on the secondary side, then the DC voltage is generated with the half-wave rectifier circuit composed of D971 and C971. The DC voltage generated at the secondary side is monitored by IC922 through R976, R977 and R978. This information detected at IC922 is fed back to pin 1 of IC903 via PC902, and the ON period of output FET internal IC903 is controlled to keep the DC voltage on the secondary side constantly. The flyback voltage in proportion to the voltage on the primary side is also generated at pin 2 of T902. The pulse voltage generated at pin 2 of T902 is converted to the DC voltage at D932 and C931, and supplied to pin 8 of IC901 and pin 4 of IC902 via Q902.

1.1.4 Main power circuit

When the P-SUS signal from microcomputer is turned to HI, Q902 is turned to ON, and the voltage approx. +18V is supplied to pin 4 (Vcc terminal) of IC902 from pin 2 of T902.

When the voltage of pin 4 of IC902 reaches approx. +16V, oscillation is started in the circuit, and the built-in output FET is put into operation to add the pulse voltage between pin 5 and pin 2 on the primary side of T901. The flyback voltage generated at the secondary side in proportion to the one in the primary side is rectified at D961, D963, D964, D965 and D967 and smoothed at C961, C963, C964, C965 and C969 to generate the DC voltage. The DC voltage generated at the secondary side is monitored by IC921 through R960, R961, R962 and R985. The information detected at IC921 is fed back to pin 1 of IC902 via PC901, and the ON period of output FET internal IC902 is controlled to keep the DC voltage on the secondary side constantly.

1.1.5 Demagnetizing circuit

When the power is turned ON or the manual demagnetizing function on OSM menu is set to ON, pin 47 of IC102 on the main board is turned to HI, and Q950 and RL901 are also turned ON.

When RL901 is turned ON, the current flows to the demagnetizing coil, however, the demagnetizing current gradually converges with the fever of TH902.

1.1.6 Power management circuit

This monitor carries the power management function. This function is effective only when being connected with the personal computer carrying the power management function.

Mode	H-SYNC	V-SYNC	State	Display
NORMAL	ON	ON	Displaying a picture	Displaying a picture
SUSPENSION	OFF ON OFF	ON OFF OFF	No picture CRT heater is decreased voltage mode (approx. 1.5V)	No raster

The power consumption and the indication of Power-On Indicator for each mode are as follows.

Mode	Power consumption	Power-On Indicator
NORMAL	125W	Green
SUSPEND	2W or less	Orange

The control signal executes the power management function is output from microcomputer IC102. The control signal is composed of two signals, SUSPEND and P-OFF. The operating state of each signal is as follows.

Control signal name	Pin of IC102	Normal	Suspension
SUSPEND	Pin 5	H	L
P-OFF	Pin 42	H	L

1.2 Deflection processor block

1.2.1 Deflection processor (IC601)

Deflection processor IC601 horizontally compensates wise, position and distortion, and vertically controls heights, position and linearity.

IC601 automatically tracks the frequency to output the appropriate horizontal/vertical drive pulse.

IC601 also outputs the horizontal parabola waveform for focus and the waveform for convergence compensation.

1.2.2 Pressure-reduction type horizontal deflection power circuit (IC5C0)

IC5C0 compares the parabola waveform output from pin 64 of IC601 (this waveform controls the horizontal width and distortion) with the sawtooth waveform (this waveform is synchronized with the horizontal frequency) in order to output the +B drive pulse. The +B drive pulse output from pin 9 of IC5C0 will accumulate the 215V energy in T550 during Q5F1 ON period. During Q5F1 OFF period, the accumulated energy will be released, and integrated by T550 and the S-shaped compensation capacitor. The duty of this drive pulse depends on the DC level of the parabola waveform that is output from IC601.

1.2.3 Horizontal width control circuit

Q550 is controlled by the horizontal drive pulse that is output from IC601. When Q550 is ON, the energy will be accumulated in the horizontal deflection yoke. When Q550 is OFF, the energy will flow into C550. While repeating this operation, horizontal deflection will be carried out.

The collector pulse of Q550 will be subject to voltage division by C590 and C591, and the voltage-divided pulse will be used for switching synchronization of the high-voltage control IC701 and also used as the AFC pulse.

The duty of the +B drive pulse output from pin 9 of IC5C0 will be subject to change in order to control the horizontal width. The parabola waveform output from IC601 is compared with the feedback waveform output from T5C0 to obtain the comparison waveform, and this comparison waveform threshes the sawtooth waveform inside IC5C0 in order to control the duty. If the duty is changed, the rectified voltage of the S-shaped compensation capacitor will be changed, and the horizontal width will be also changed. The vertical parabola waveform is generated inside IC601, and then mixed with the DC level for horizontal width control. After that, the mixed parabola waveform will be output from 64 pin of IC601, and added to IC5C0. This parabola output will be used for compensation of pin-cushion distortion, barrel distortion, trapezoidal distortion, and upper/lower distortion.

1.2.4 Vertical deflection circuit

1.2.4.1 Sawtooth waveform generation, vertical size/position control, and linearity control circuit

If the vertical synchronization signal is input to 42 pin of IC601, the bipolar sawtooth waveform having the same frequency as the input will be output from pins 1 and 11 of IC601. IC601 receives compensation data from the MPU (IC102) to compensate the vertical size, vertical position, vertical raster position, vertical linearity, and vertical linearity balance, and then outputs the compensated sawtooth waveforms from pins 1 and 11. Pin 2 outputs the voltage to show the vertical deflection intermediate point.

The OP amplifier at the next stage outputs a signal to show the difference of the bipolar sawtooth waveform. For this output, the RC low pass filter is adopted to eliminate the digital gradation of the output waveform. In addition, pins 62 and 63 of IC601 will be turned ON during retracing operation in order to prevent deterioration of the linearity and dispersion of scanning lines. Moreover, Q603 and Q604 are switched depending on the vertical frequency in order to improve the linearity.




Fig. 2 Vertical sawtooth waveform output circuit

1.2.4.2 Vertical output amplification circuit

A current proportional to the waveform of the voltage input to IC401 will flow to the vertical deflection coil (V-DY). R410 reads out the voltage waveform of the vertical deflection current, and then feeds back it to IC401.




Fig. 3 Vertical output amplifier circuit

1.2.5 High voltage block

The high voltage block applies PWM control system that controls ON/OFF time of the high voltage generation FET.

IC701 is the control IC that executes PWM control. The pulse voltage generated at Q701 is boosted at T701 (FBT) to generate 27kV. To keep the high voltage stably, the feedback voltage from pin 10 of T701 is adopted, the control voltage from pin 56 of microcomputer IC102 is returned to pin 5 of IC701 and the pulse wise of PWM output is controlled. PWM synchronizes with the horizontal frequency. Trigger pulse for synchronizing is output from the divided collector pulse of the horizontal deflection output TR Q550, and is input to pin 8 of IC701.

For adjustment of high voltage value, the voltage of pin 56 of IC102 is adjusted with the adjustment item HV-ADJ-CAUTION on the OSM menu.

1.2.6 DBF (Dynamic Beam Focus) circuit

The horizontal/vertical DBF voltage is respectively generated and amplified, then synthesized at T7A1. As for the horizontal DBF voltage waveform, the parabola waveform voltage (approx. 0.5Vp-p) is output with IC601, and amplified about 10 times with OP-AMP IC6A2. After that, it is amplified to 50-60Vp-p with Q7B5 (the amplification factor is about 10 times), then it is amplified about 10 times with T7A1. On the other hand, as for the vertical DBF voltage waveform, the parabola waveform voltage (approx. 1.0Vp-p) is output from IC601. It is amplified about 40 times at Q7A1, and the vertical parabola wave is superposed to the horizontal parabola wave on the secondary side of T7A1, then consequently synthesized. The collector pulse voltage of the high voltage output TR (Q701) rectified at D7A1 and C7A1 is used for the power source of Q7A1. The synthesized DBF waveform is input to pin 12 of T701.

1.3 Video block

1.3.1 Video signal amplifier circuit




Fig. 4 Video signal amplifier circuit

1.3.1.1 Video clamp

The clamp signal (positive polarity, 3.3 Vo-p) output from pin 35 of the MPU (IC102) is input to pin 13 of IC211. The clamp signal is normally set to the back of the video signal (clamp position of OSM menu: BACK). To correspond to the Sync on Green signal, the clamp signal can be set to the front of the video signal (clamp position of OSM menu: FRONT). If the signal is a separate signal, changing the clamp position of the OSM menu to FRONT or BACK will not change anything.

1.3.1.2 Video blanking

The horizontal/vertical retrace line (blanking) signal (positive polarity, 3.3 Vo-p) output from pin 40 of IC601 is input to pin 13 of IC215. IC215 reverses the polarity and amplifies the waveform (positive polarity, 3.3Vo-p -> negative polarity, 5.0Vo-p), and then reverses the polarity again (negative polarity, 5.0Vo-p -> positive polarity, 5.0Vo-p) to output the blanking signal. This blanking signal is input to pin 14 of IC211 to perform blanking operation during horizontal/vertical retracing operation.

To perform image blanking at switching the signal mode or at turning ON or OFF the power, the contrast and the brightness will be set to MINIMUM.

1.3.1.3 Video mixing/amplifying

IC211 mixes the video signal with the OSM signal (G, R, and B signals of pins 9, 10, and 11) and with the video blanking signal described in Sec. 1.3.1.2. I2C bus (pins 16 and 17 of SCL and SDA) fixes the black level of the mixed video signal to 1.8V, and amplifies the mixed video signal (0.7Vp-p -> approx. 2.6Vp-p). After that, the B, R, and G signals are output from pins 25, 27, and 29, respectively. The video signal output from IC211 is input to IC210, where the signal is amplified (approx. 2.6Vp-p -> approx. 36Vp-p), and the black level is fixed to 67V. After that, the B, R, and G signals are respectively output from pins 1, 3, and 5.

1.3.1.4 Control of contrast and white balance

The MPU (IC102) sends the 8-bit contrast/white balance control data to IC211 with I2C bus (SCL, SDA line). The contrast data simultaneously control 3 channels to simultaneously control the gains of the R, G, and B, and the white balance data respectively controls the gains of the R, G, and B.

1.3.2 Cut-off control circuit




Fig. 5 Cut-off control circuit

The cut-off control circuit consists of Q250R, Q250G, Q250B, Q251R, Q251G, and Q251B, and simultaneously adjusts 3 colors (brightness), or individually adjusts 3 colors (biases of R, G, and B). The microcomputer controls both types of adjustment.

1.3.2.1 Control of brightness

To simultaneously adjust 3 colors (brightness), the DAC voltage (0 to 5V, variable) line of microcomputer pin 55 is connected to the emitters of Q250R, Q250G, and Q250B via IC213. This connection enables simultaneous control of three TR collector currents and adjustment of the brightness.

1.3.2.2 Control of BIAS

To individually adjust 3 colors (biases of R, G, and B), the DAC output (1.5 to 5.5V, variable) lines (pins 19, 20, and 21 of IC211) are respectively connected to the emitters of Q250R, Q250G, and Q250B via I2C bus of the microcomputer. This connection enables respective control of three TR collector currents and adjustment of biases of the R, G, and B.

1.3.3 OSM (On Screen Manager)

IC212 is the OSM (On-Screen Manager), and displays the screens for screen adjustment, etc. The data to be displayed on the OSM screens is sent to the MPU (IC102) via I2C bus.

1.3.4 Asset circuit

If the monitor power is turned OFF, 5V power will be supplied to pin 8 of EEPROM (IC218) from the PC via pin 9 of CN216, and the data stored in the EEPROM (IC218) can be read out from I2C bus.


1.3.5 AUTO-SIZE function

The AUTO-SIZE function detects the phase data of RGB OR signal (output to pin 11 of OSM (IC212) from pin 15 of AMP (IC211) from H-OSM and V-S signals input to pins 5 and 16 of IC212 in order to automatically adjust the screen to the optimum width and position.

Using the OSM, select AUTO SIZE ADJUST, and then press (+) button to perform automatic size adjustment.

1.3.6 SB MODE (Super Bright Mode) function

1.3.6.1 Adjustment item/operating function in selecting SB Mode




	User adjustment items related to luminance/color coordination				
	Adjustment of brightness	Adjustment of contrast	Color mode selection	Color temperature selection	Individual GAIN adjustment
SUPER BRIGHT MODE OFF	Adjustable (*1)	Adjustable (*1)	Selectable	Selectable (*2)	Adjustable (*4)
SUPER BRIGHT MODE-1 ON	Adjustable (*1)	Adjustable (*1)	Not-selectable	Selectable (*2)	Not-adjustable
SUPER BRIGHT MODE-2 ON	Adjustable (*1)	Adjustable (*1)	Not-selectable	Selectable (*2)	Not-adjustable

(*1): Brightness and contrast are common among three display mode.

(*2): For color temperature, the adjustment value is memorized in every display mode.

	Back raster luminance	GAIN UP	compensation	Sharpness
SUPER BRIGHT MODE OFF	Normal	Normal	---	---
SUPER BRIGHT MODE-1 ON	Normal	UP	Presence	---
SUPER BRIGHT MODE-2 ON	UP	UP	Presence	Presence

1.3.6.2 Circuit (cathode) operation in selecting SB Mode [Window pattern]



1.3.6.3 SB Mode setting data and control method

(OSM FACT3)	Data name	Data (hex)	
Setting of back raster luminance	SBBR1	0	BRT UP value in SUPER BRIGHT MODE-1 ON "0"=No UP
	SBBR2	32	BRT UP value in SUPER BRIGHT MODE-2 ON
Setting of GAIN UP	SBCN1	3C	Amplified value in SUPER BRIGHT MODE-1 ON (see the following formula)
	SBCN2	3C	Amplified value in SUPER BRIGHT MODE-2 ON (see the following formula)

GAIN UP formula = GAIN adjustment value (hex)(*3) x {1+ (Data (hex) of SBCN1 or SBCN2)/FF (hex) }

(*3): GAIN adjustment value is the following data (in OSM FACT3).

9300K	R-GN1	G-GN1	B-GN1
6500K	R-GN2	G-GN2	B-GN2
5000K	R-GN3	G-GN3	B-GN3

(*4): When the SUPER BRIGHT MODE-1 or MODE-2 is ON, the GAIN cannot be adjusted as shown in the table in Sec. 1.3.6.1 "Adjustment item/operating function in selecting SB Mode". However, when the SUPER BRIGHT MODE is OFF, the MAX GAIN value calculated with the following formula will be written in the following EEP address so that the GAIN value cannot be increased above that of the SUPER BRIGHT MODE-1 and MODE-2 ON status.

MAX GAIN = Maximum value (hex) for R/G/B GAIN adjustment (Note 5) x {1 + (SBCN1 or SBCN2 data (hex))/FF (hex)}

(*5): R/G/B GAIN MAX value is the maximum one among GAIN adjustment value mentioned (*3) above.

EEP address (hex)

	R	G	B
MAX GAIN	89	8a	8b

* Every R/G/B MAX GAIN data applied to the address listed above table are totally same.

In case of repair, after CRT, Pre-AMP (IC211), MAIN-AMP (IC210), etc. are replaced and the luminance/color coordination is adjusted, the MAX GAIN value mentioned above should be rewritten.

1.3.7 CONSTANT BRIGHTNESS function

The brightness and color coordination of the screen will be deteriorated due to secular deterioration of the

CRT. The CONSTANT BRIGHTNESS function, however, will recover the deteriorated brightness close to the initial level (level ensured at outgoing the factory).

If the CONSTANT BRIGHTNESS function is activated, operation will be performed at 106kHz horizontally and at 85Hz vertically while ignoring the input signal, and the OSM-IC (IC212) will output the reference image signal. In this condition, R744 detects the beam current flowing to pin 9 of the flyback transformer T701. This beam current is inverted and amplified by IC703, and then converted into a voltage value by the current/voltage conversion circuit. After that, the converted voltage value will be input to the A/D converter (pin 27 of IC102 (microcomputer)). To individually detect the beam current values of 3 colors (R, G, and B), the desired color only will be brightened by increasing the cut-off voltages of the other 2 colors. After obtaining the beam current values of 3 colors in this way, the obtained beam current values will be compared with the beam current values used for factory adjustment (beam current values stored in the EEPROM). After that, the cut-off voltage values of 3 colors (R, G, and B) will be adjusted so that the beam current values close to the factory adjustment values can be obtained. In this way, the cut-off conditions of the CRT will be recovered close to the factory adjustment level.

In addition, if the CONSTANT BRIGHTNESS function is activated, the C_TIME_SEL signal input to the base of Q704 will be set to the low level, Q704 is turned OFF, and the bias voltage will be applied to pin 5 of IC703. As a result, voltage proportional to the beam current value will be output from pin 7 of IC703. By the way, difference in the flyback transformer or the CRT may cause difference in the beam current. To eliminate such difference in the beam current, the DAC voltage (commonly used for the 6H-DC signal) can adjust the bias voltage input to pin 5 of IC703 described above. During normal operation, the C_TIME_SEL signal is set to the high level, Q704 is turned ON, and pin 5 of IC703 is grounded via the GND line so that the output of IC703 pin 7 can be kept at the low level. The signal output from pin 7 of IC703 is added to ABL signal with MD717 (Diode). When the CONSTANT BRIGHTNESS function is activated, the ABL signal is input to pin 27 of IC102 as the beam current signal.

1.4 CRT compensation block

1.4.1 Rotation circuit

The rotation circuit is a circuit to compensate the picture inclination caused by the earth magnetism by letting DC current flow to the rotation coil wound on the front side of DY for adjustment. It is controlled to 0 to 5V with the reference of 2.5V by IC102 pin 45 (PWM_DAC), and DC current of +/-100mA (max) is made to flow to the rotation coil by IC804 pin 2.

1.4.2 Corner purity circuit

The corner purity circuit is a circuit to compensate for the color shade and color deviation of the picture corner. On the rear side of CRT, it is adjusted by DC current flowing to the corner purity coils installed in the four corners on the display surface.

The compensation circuit is composed of the following three functions of (1) User adjustment (OSM display), (2) Aging variation compensation and (3) High/low temperature drift compensation.

(1) User adjustment (OSM display)

The user causes DC current of +/-120mA (max) to flow to the purity coil of each corner according to the value displayed on OSM.

(2) Aging variation compensation

As the electronic beam collides with the aperture grille, it is thermally expanded and contracted. The thermal expansion/contraction is varied according to the elapse of the power ON/OFF time of the monitor. The color shade and deviation of the picture corner thus generated are automatically adjusted.

The voltage of the beam current supply pin (T701 pin 9) is detected with R723/R724, and the voltage that detects the time elapse of the power ON/OFF of the monitor is read from the CR charge (integration) circuit composed of C723 and R738, and CR discharge (integration) circuit composed of C723 and R737 through IC702 (buffer amplifier) by IC102 pin 26 (CPU_ADC), then, the DC current of +/-19mA (max) flows to the purity coil on each corner according to the specified control program.

(3) High/low temperature drift compensation

The front panel (glass) is thermally expanded and contracted as the temperature varies in the installation environments of the monitor. The color shade and deviation of the picture corner are automatically adjusted. The voltage that detects the temperature variation of the installation environments of the monitor is read from the environment temperature detection circuit composed of TH100 (thermistor) arranged near the front panel (glass) by IC102 pin 25 (CPU_ADC), and DC current of +/-13mA (max) is made to flow to the purity coil on each corner according to the specified control

program.

1.4.2.1 Corner purity circuit operation

<TL: Upper left corner>

Pin 50 (PWM_DAC) of IC102 controls the TL in the range of 0 to 5V while regarding 2.5V as the reference voltage, and the DC current of the above value will flow from pin 2 of IC803 to the upper left corner purity coil.

<TR: Upper right corner>

Pin 49 (PWM_DAC) of IC102 controls the TR in the range of 0 to 5V while regarding 2.5V as the reference voltage, and the DC current of the above value will flow from pin 8 of IC803 to the upper right corner purity coil.

<BL: Lower left corner>

Pin 52 (PWM_DAC) of IC102 controls the BL in the range of 0 to 5V while regarding 2.5V as the reference voltage, and the DC current of the above value will flow from pin 2 of IC801 to the lower left corner purity coil.

<BR: Lower right corner>

Pin 51 (PWM_DAC) of IC102 controls the BR in the range of 0 to 5V while regarding 2.5V as the reference voltage, and the DC current of the above value will flow from pin 8 of IC801 to the lower right corner purity coil.

1.4.3 Digital dynamic convergence clear (DDCC) circuit

In the digital dynamic convergence clear (hereafter called DDCC) circuit, the convergence compensating current waveform is produced and amplified, and the convergence is compensated by the compensation current flowing to the sub yoke that is installed as the rear unit of the deflection yoke.

Though the principle of the convergence compensation with the sub yoke is same as the CP ring, the CP ring is used for the static variation with the parallel movement in the whole picture in the uniform magnetic field with the permanent magnet but the sub yoke is used for dynamic variation that compensates a desired position on the picture by controlling the current waveform that flows to the coil of the electric magnet. (See Fig. 7)

1.4.3.1 Production of compensation current waveform

There are 30 kinds of compensation elements, and they are programmed in IC601 one by one using the function. Inputting the compensation coefficient into the function controls the amplitude of the current.




Fig. 6 DDCC compensation image

Examples of the functions and current waveform/compensation operation of YH (YHTT, THTB, YHJT, YHJB) are shown as follows.

In the above formulas, b11T, b11B, b12T and b12B express the compensation coefficients, and y and y² express the primary and secondary functions of the vertical frequencies.

The other parts except the compensation coefficients are programmed, and desired amplitudes (= compensation amount) are gained by varying the coefficients.

YHTT and YHTB compensate the upper and lower parts of the picture of the characteristic components of their DYs to compensate the upper and lower parts of the picture of the axis deviation component. The component gained by adding YHT and YHJ is multiplied by the offset compensation coefficient a11. The resultant component is regarded as 4H_SC, and is output from IC601 pin 61.

1.4.3.2 Waveform, and operation on the picture

The case in which the currents flow through 4H coils of the sub yoke is explained. Regarding YHT (secondary function in the vertical frequency), in case of Fig. 6 as an example, the current is large in the same direction at the start (upper end of the picture) and the end (lower end of the picture) of the vertical frequency, and is zeroed on the X axis of the picture. Therefore, the magnetic field that is proportional to it is generated, and RED and BLUE vary in the same direction only at the upper and lower ends of the picture.

As aforementioned, YHT can be independently controlled at the upper part (b11t · y²) and lower part (b11B · y²).

Moreover, regarding YHJ (primary function in the vertical frequency), if the flowing direction of the current is opposite at the start (upper end of the picture) and the end (lower end of the picture) of the vertical frequency as an example, RED and BLUE vary in the opposite direction only at the upper and lower ends of the picture. Making the current flow to the 4V coil can do compensation in the vertical direction.

Fig. 8 (a) and (b) shows the image of each adjustment item of the DDCC adjustment.

1.4.3.3 Adjustment method

Before the adjustment with the compensation circuit, it is necessary that they are properly adjusted at the center (H-STATIC and V-STATIC), on the X axis (XH slider, B-Bow 4P, XV differential coil) and on the Y axis (YH volume, YV volume).

Though DC current is superimposed on the sub yoke, H-STATIC and V-STATIC are pushed to the greatest possible extent by the adjustment with CP ring in order to reduce the stress of the driver IC8A1 (STK391-110).

Moreover, since 4H and 4V coils alone are installed on the chassis, it is first necessary that the convergence of RED, BLUE and GREEN (6H, 6V) satisfy the specifications for the performance of ITC (CRT&DY).

As the adjustment procedure, the adjustment values of 30 elements are not respectively zeroed but they are adjusted to nearest to zero with a total balance in good order.

In other words, the balance (compromise) adjustment with each adjustment item is applied.

The correspondence of the names of DDCC adjustment mode to the coefficients of all 30 elements is shown below.

<Factory mode>

4H Coil	b11T	YHTT	y^2	b11B	YHTB	y^2	b12T	YHJT	y	b12B	YHJB	y
	b21L	XHL	x^2	b21R	XHR	x^2						
	b31TL	S3HTL	$x^2 \cdot -(y^3+y^4+y^5+y^6)$	b31TR	S3HTR	$x^2 \cdot -(y^3+y^4+y^5+y^6)$	b31BL	S3HBL	$x^2 \cdot -(y^3+y^4+y^5+y^6)$	b31BR	S3HBR	$x^2 \cdot -(y^3+y^4+y^5+y^6)$
	b41TL	PQHTL	$x^2 \cdot y^4$	b41TR	PQHTR	$x^2 \cdot y^4$	b41BL	PQHBL	$x^2 \cdot y^4$	b41BR	PQHBR	$x^2 \cdot y^4$
4V Coil	c11T	YVTT	y^2	c11B	YVTB	y^2	c12T	YVJT	y	c12B	YVJB	y
	c21L	XVL	x^2	c21R	XVR	x^2						
	c31TL	S3VTL	$x^2 \cdot -(y^3+y^4+y^5+y^6)$	c31TR	S3VTR	$x^2 \cdot -(y^3+y^4+y^5+y^6)$	c31BL	S3VBL	$x^2 \cdot -(y^3+y^4+y^5+y^6)$	c31BR	S3VBR	$x^2 \cdot -(y^3+y^4+y^5+y^6)$
	c41TL	PQVTL	$x^2 \cdot y^4$	c41TR	PQVTR	$x^2 \cdot y^4$	c41BL	PQVBL	$x^2 \cdot y^4$	c41BR	PQVBR	$x^2 \cdot y^4$

<User & Factory mode>

4H Coil	a11	H-CONVERGENCE	DC
4V Coil	a12	V-CONVERGENCE	DC

1.4.3.4 Block diagram

Fig. 9 shows the block diagram of the DDCC circuit.

The components 4H_DC (pin 6), 4H_SC (pin 61), 4V_DC (pin 8) and 4V_SC (pin 60) supplied from IC601 to 4H-Coil and 4V-Coil are output, the dynamic component (4H_DC, 4V_DC) is amplified with IC6A2, and the static component (4H_SC, 4V_SC) is amplified with IC6A3.

DDC (pin 7) output from IC601 and DEFL_+3.3V (pin 3) output from IC602 are respectively the reference

voltage of Op-Amp (IC6A2) that amplifies the above dynamic component (4H_DC, 4V_DC) and the reference voltage of Op-Amp (IC6A3) that amplifies the static component (4H_SC, 4V_SC). On each of 4H and 4V, the waveform added with the dynamic component and static component is input to IC8A1 pin 3 and pin 4, and it allows the specified current to flow to each convergence compensation coil.




Fig. 7 The principle of DDCC compensation




Fig. 8 (a) DDCC adjustment item

RED —
BLUE - - -




Fig. 8 (b) DDCC adjustment item




Fig. 9 DDCC circuit diagram

1.5 Control block

1.5.1 Function of control circuit

The control block is mainly on MAIN board and DEFL-SUB board, and the function is as follows.

- (1) Auto-tracking
- (2) Control of picture size, distortion and position
- (3) Adjustment data memory
- (4) Sync. signal detection
- (5) OSM control
- (6) Video pre-amp control and clamp pulse position control
- (7) Power ON/OFF control
- (8) Heater voltage control
- (9) DDC 1 / 2B / 2Bi
- (10) Operating time display

The control block is composed of the following four components.

- | | |
|-------------------------|---------------------|
| (1) Microcomputer: | IC102 (MAIN board) |
| (2) OSM IC: | IC212 (VIDEO board) |
| (3) EEPROM: | IC104 (MAIN board) |
| (4) Sync. signal input: | IC215 (VIDEO board) |

1.5.2 Auto-tracking process

The microcomputer (IC102) calculates the frequency of the sync. signal input and outputs the distortion compensation data corresponding to the input signal timing to the deflection IC (IC600). Control with IC600 is carried out via I2C bus.

1.5.3 EEPROM

The capacity of the EEPROM (IC104) is 32 kilobits (4 kilobytes). The factory adjustment data, user adjustment data, and EDID data are stored in the EEPROM. Up to 9 items can be stored as the factory preset data, and up to 16 items can be stored as the user preset data. Regarding the factory preset timing, if the user reset the memory, the factory adjustment data will be called up.

The EDID data is stored in the last 128-byte area.

1.5.4 On-Screen-Manager (OSM) controller

The On-Screen-Manager (OSM) controller IC IC212 displays the picture used for picture adjustment and so on. OSM display data is sent from the microcomputer (IC102) via I2C bus.

1.5.5 Heater voltage control

In the normally ON status, the heater voltage is supplied from the +8V line of the main power circuit. Heater resistor R203H connected in series adjusts this supplied voltage to +6.15V (typ) (rated voltage for the CRT) before application. In the suspend mode, the sub-power circuit applies the voltage so that the screen can be instantaneously recovered. (In the suspend mode, the heater voltage is low compared with that of the normally ON status.)

1.5.6 Protection circuit operation

This monitor can detect the following problems, and can stop the monitor operation after detection of a problem. If the protector function is activated, the Power-On Indicator (LED) will flicker so that you can localize the activated protector.

1.5.6.1 X-ray protector

The CRT monitor radiates X-rays, and exposure to too much radiation is very dangerous. For this reason, the CRT monitor incorporates an X-ray protector. If the high voltage value rises above the specified value, the protector will automatically stop applying the high voltage. For this model, the X-ray protector activation point is set to 31.0kV (entirely black screen).

To disable the X-ray protector for the reason of repair, etc., set the monitor in the factory mode.

1.5.6.2 High voltage data error detection

Important safety data, such as the high voltage adjustment value and the X-ray protector activation voltage, are stored in the EEPROM. For each safety data, there is backup data. If both data values differ from each other, the monitor will enter the power saving mode (the high voltage will not be applied).

1.5.6.3 Beam current protector

If too much beam current flows (1.5mA or more), "H" will be input to the ABL terminal (pin 27 of the microcomputer (IC102)). From this terminal, the microcomputer will detect overflow of the beam current, and will set the monitor in the power saving mode.

1.5.6.4 Power-On Indicator (LED) flickering pattern in each protector operating

If a protector is activated, the Power-On Indicator (LED) will flicker as shown below to indicate the activated protector (to show the cause of the problem).

Table 2 Power-On Indicator (LED) flickering pattern in each protector operating

Protector state	Power-On Indicator (LED) state	
	Short (0.5s) lighting times	Long (2s) lighting times
X-ray protector	1	1
High voltage circuit latch detection	2	1
Data protector	3	1
Beam protector	5	1
+B short-circuit	7	1

1.5.6.5 Operating time

If "DIAGNOSIS" is selected from the menu in the factory mode, the monitor operation time will appear. 0.5 hours will be added to this value every 30 minutes.

P: Indicates the power-on time (including the operation time in the power saving mode).

K: Indicates the heater power-on time.

1.5.6.6 The DDC communication

The microcomputer carries out the DDC communication. For this communication, the microcomputer reads out the EDID data from the EEPROM, and stores the data in the RAM. When receiving a request from the PC, the microcomputer will output the data from pins 8 and 11.

1.5.6.7 Microcomputer pin assignment

#	PORT	ASSIGN	I/O	FUNCTION	#	PORT	ASSIGN	I/O	FUNCTION
1	H_LOCK	IRQ2/P40	I	H_UNLOCK detection	64	CS8	P37	O	CS switching 8
2	USB-SPARK USB-RESET	IRQ1/P41	I/O	For FLASH writing	63	CS7	P36	O	CS switching 7
3	INPUT SEL	IRQ0/P42	O	Power cut detection	62	CS6	P35	O	CS switching 6
4	HSK	RD/P43	O	SOA output	61	CS5	P34	O	CS switching 5
5	SUSPEND	WR/P44	O	Suspend	60	CS4	P33	O	CS switching 4
6	C TIME SEL	IOS/AS/P45	O		59	CS3	P32	O	CS switching 3
7	OPTION	EXCL/o/P46	I	(available as input port)	58	CS2	P31	O	CS switching 2
8	DDC_DATA	SDA0/WAIT	I/O	DDC data	57	CS1	P30	O	CS switching 1
9	FLASH_TX	TxD0/P50	O	PZTAT	56	HVADJ	P10/PWMX0	P	HVADJ
10	BEAM/SHORT	RxD0/P50	I	Beam protector	55	BRIGHTNESS	P11/PWMX1	P	Brightness
11	DDC_SCL	SCL0/SCK0	I/O	DDC clock	54	SW LIN2	P12/PW2	O	SW LIN2
12	RESET	RES	I	Reset	53	SW LIN1	P13/PW3	O	SW LIN1
13	NMI	MNI	I	NMI	52	PURITY_BL	P14/PW4	P	Corner purity BL
14	(+) 5V	Vcc			51	PURITY_BR	P15/PW5	P	Corner purity BR
15	STBY	STBY	I		50	PURITY_TL	P16/PW6	P	Corner purity TL
16	GND	GND			49	PURITY_TR	P17/PW7	P	Corner purity TR
17	X'TAL	XTAL			48	GND	Vss		
18	X'TAL	EXTAL			47	DEGAUSS	P20/PW8	O	DEGAUSS
19	MODE SW1	SW1		Mode setting	46	V_CANCEL	P21/PW9	P	V. magnetic field cancel output
20	MODE SW2	SW2		Mode setting	45	ROTATION	P22/PW10	P	Rotation
21	GND	AVss			44	IIC_SDA	SDA1	I/O	Internal IIC data
22	KEY1	AN0/P70	A/D	Key input	43	IIC_SCL	SCL1	I/O	Internal IIC clock
23	KEY2	AN1/P71	A/D	Key input	42	P OFF	P25/PW13	O	POWER OFF
24	X RAY PRO	AN2/P72	A/D	X-ray protector	41	LIN PWM1	P26/PW14	P	H. linearity
25	TEMP	AN3/P73	A/D	Temp. detection	40	6H	P27/PW15	P	6H
26	BEAM TIME	AN4/P74	A/D	Time detection	39	Vcc	Vcc		
27	ABL/C TIME	AN4/P75	A/D	Heater voltage detection	38	Hsync OUT	P67/HSYNCO	O	H. sync. output
28	EW_SENSE	AN6/P76	A/D	H. magnetic field detection	37	SOG IN	P66/CSYNCl	I	SYNC ON G input
29	SN_SENSE	AN7/P77	A/D	V. magnetic field detection	36	HSYNC IN	P65/HSYNCl	I	H. sync. input
30	Vcc	AVcc			35	CLAMP OUT	P64/CLAMPO	O	CLAMP OUT
31	LED	HFBACK/P60	O	LED output	34	HSYNC SEL	P63/VFBACKI	O	HSYNC SEL
32	VSYNC OUT	VSYNCO/P61	O	V. sync. output	33	VSYNC IN	V_SYNCI	I	V. sync. input

1.6 Safety protection circuit and X-ray protection circuit

1.6.1 X-ray protection circuit

This circuit prevents X-ray radiation from exceeding the dangerous level due to the abnormal rise of high voltage.

Do not modify the high voltage circuit and the safety protection circuit.

The upper limit of the high voltage value and the beam current value are determined by the X-ray radiation upper limit curve of CRT.

In the X-ray protection circuit, the X-ray protector activation voltage depends on the beam current. The X-ray protector, however, is normally activated at approximately 30kV (when the beam current is approximately 1mA). D709 and C704 rectify the increase in the pulse voltage output from pin 6 of T701. Pin 24 of IC102 detects this rectified voltage. If the detected voltage exceeds the specified value, the SUSPEND signal output from pin 5 of IC102 will be set to 'Low', and the P-OFF signal output from pin 42 will be also set to 'Low' (power-off mode). In addition, operation of IC701 will be stopped. This condition of the protection circuit will be retained until the power switch is turned OFF.

1.6.2 Beam current protection circuit

When the current supplied to the high voltage generating winding of FBT exceeds approx. 1.5mA, the protection circuit functions. The detection of the beam current is executed by the voltage fall of R722 connected between T901 pin 9 and the 12V.

Resistors R723 and R724 divide the potential of this voltage. The divided voltage is then input to pin 27 of IC102 via IC703. If the input voltage exceeds the specified value, the SUSPEND signal output from pin 5 of IC102 will be set to 'Low', and the P-OFF signal output from pin 42 will be also set to 'Low' (power-off mode). In addition, operation of IC701 will be stopped. This condition of the protection circuit will be retained until the power switch is turned OFF.

1.6.3 IC701 overcurrent protection circuit

The peak value of the drain current of Q701 and the both-end voltages of source resistors R708 and R709 are detected by pin 2 of IC701. If the voltage of this pin exceeds 1.2V (typ), pin 9 of IC701 will stop outputting the drive waveform. If the voltage of IC701 pin 2 drops below 1.2V (typ), pin 9 of IC701 will output the drive waveform again.

1.6.4 IC701 overload protection circuit

If overload occurs consecutively and the overcurrent protection circuit is activated consecutively, this overload protection circuit will enter the latch mode to stop operation. If the voltage of IC701 pin 2 exceeds 1.0V (typ), C709 will be charged. If the voltage of IC701 pin 13 exceeds 2.5V (typ), IC701 will enter the latch mode to stop the control operation. This condition of the protection circuit will be retained until the power switch is turned OFF.

1.6.5 IC902 overcurrent protection circuit

IC902 is equipped with an overcurrent protection circuit. R928 detects the drain current of the incorporated FET. If the voltage of IC902 pin 1 exceeds approximately 0.7V, this overcurrent protection circuit will be activated.

1.6.6 Short-circuit protection circuit on secondary power side

The output line of each secondary power (+215V, +80V, +15V, +8V, -15V) is equipped with a short-circuit detection circuit. If a secondary line is overloaded and the output voltage drops by 30 to 40% of the normal voltage, this short-circuit protection circuit will be activated.

1.6.7 Overvoltage protection circuit

The harmonic suppression circuit (active filter circuit) and the main power circuit are respectively equipped with an overvoltage protection circuit. If the voltage between both ends of C911 rises by 10% of the normal voltage, or if the voltage of the main power secondary output line rises by 30 to 40% of the normal voltage,

operations of IC901 and IC902 will be stopped.

1.7 Adjustment

1.7.1 Adjustment mode


This monitor has the following adjustment modes.

- (1) User mode (Normal mode)
- (2) Factory mode (Factory adjustment mode)

1.7.2 User mode (Normal mode)


This is the mode user executing the adjustment and setting. When pressing button of EXIT, (<), (>), (-), (+) and SELECT on the front panel, the following menu picture is displayed on the screen.

The adjusted data in the user mode is memorized to EEPROM automatically.



The adjustment group can be selected with (<), (>), (-) and (+) buttons. (+) and (-) buttons have the functions of the variable of the adjustment value. The items can be adjusted in the user mode are as following table.

OSM menu (User mode)

Group icon	Item icon	Item		Adjustment	
				—	+
 Group 1		BRIGHTNESS		To decrease the brightness.	To increase the brightness.
		CONTRAST		To decrease the contrast.	To increase the contrast.
		DEGAUSS		N/A	To eliminate possible color shading or impurity.
		CONSTANT BRIGHTNESS		N/A	Activates the constant brightness function.
		RESET		Restore to factory preset level with RESET button.	
 Group 2		AUTO ADJUST		N/A	To adjust the screen size automatically based on input timing.
		LEFT / RIGHT		To move the image to the left.	To move the image to the right.
		DOWN / UP		To move the image down.	To move the image up.
		NARROW / WIDE		To narrow the width of the image on the screen.	To expand the width of the image on the screen.
		SHORT / TALL		To narrow the height of the image on the screen.	To expand the height of the image on the screen.
		RESET		Restore to factory preset level with RESET button.	
 Group 3	1 2 3 sRGB5	COLOR TEMPERATURE ADJUSTMENT (9300K, 8200K, 7500K, SRGB, 5000K)		N/A	N/A
	For each color temperature		COLOR TEMPERATURE	To decrease the color temperature.	To increase the color temperature.
		R	RED	To decrease the red color.	To increase the red color.
		G	GREEN	To decrease the green color.	To increase the green color.
		B	BLUE	To decrease the blue color.	To increase the blue color.
		RESET		Restore to factory preset level with RESET button.	
 Group 4		IN / OUT (PIN CUSHION)		Forms a pin.	Forms a barrel.
		LEFT / RIGHT (PIN CUSHION BALANCE)		Distorts the screen leftward.	Distorts the screen rightward.
		TILT (PARALLELOGRAM)		Distorts the upper section leftward.	Distorts the upper section rightward.
		ALIGN (TRAPEZOIDAL)		Narrows the upper section.	Narrows the lower section.
		ROTATE (RASTER ROTATION)		To rotate the image counterclockwise.	To rotate the image clockwise.
		TOP		The upper section forms a pin.	The upper section forms a barrel.
		TOP-BALANCE		Distorts the upper section leftward.	Distorts the upper section rightward.
		BOTTOM		The lower section forms a pin.	Lowers the lower section.
		BOTTOM-BALANCE		Distorts the lower section leftward.	Distorts the lower section rightward.
		RESET		Restore to factory preset level with RESET button.	

Group icon	Item icon	Item	Adjustment	
			—	+
 Group 5		MOIRE CLEAR	Reduces the moire value.	Increases the moire value.
		CONVERGENCE (HOR.)	The red moves to the left side of the green.	The red moves to the right side of the green.
		CONVERGENCE (VER.)	The red moves below the green.	The red moves above the green.
		LINEARITY (VER.)	Contracts the center area.	Elongates the center area.
		VERTICAL BALANCE	Elongates the lower section of the screen.	Elongates the upper section of the screen.
		GLOVAL SYNC (TL)	The green screen will be reddish.	The green screen will be bluish.
		GLOBAL SYNC (TR)	The green screen will be reddish.	The green screen will be bluish.
		GLOBAL SYNC (BL)	The green screen will be reddish.	The green screen will be bluish.
		GLOBAL SYNC (BR)	The green screen will be reddish.	The green screen will be bluish.
		RESET	Restore to factory preset level with RESET button.	
 Group 6		LANGUAGE	Selects the left items.	Selects the right item.
		OSM POSITION	C→BR→BL→TR→TL	C→TL→TR→BL→BR
		OSM TURN OFF	Reduces the time.	Increases the time.
		OSM LOCK OUT	N/A	Turns ON (+: SELECT key)
		IPM OFF MODE	ON	OFF
		EDGE LOCK	FRONT	BACK
		HOT KEY	ON	OFF
		FACTORY PRESET	N/A	Restores all items to the factory preset level.
		RESET	Restore to factory preset level with RESET button.	
 Group 7	MODE	DISPLAY MODE	N/A	N/A
		MONITOR INFO	N/A	N/A
	Hz	REFRESH NOTIFIER	ON	OFF
	Group 7	RESET	Restore to factory preset level with RESET button.	

* Reset: Select an adjustment item and press the RESET key, then, it restores to factory preset level.


1.7.3 Factory mode

This mod can adjust all of items, and also change the factory default adjustment data (reset data).

1.7.3.1 How to entering to Factory mode

The setting of the factory mode is executed by the following procedures.

(1) Power ON with EXIT button pressed, and confirm that the following OSM picture appears.




- (3) Press (-) button once to set the data value to 255.
- (4) Press (+) button to set the data value to 5.
- (5) Press SELECT button to move to the factory mode.
- (6) As shown below, the adjustment data (hexadecimal number) and the adjustment group of FAC1, FAC2 and FAC3.

FACTORY-1		
CPDIS	PRDIS	HYZER
Y-PUR	HPR-G	DBF2T
DBF2B	DBF4T	DBF4B
HFOCS	YFOCS	HFOCD
SOG-E	DIREC	WPDDC
HPURC	YPURC	6H-DC

1.7.3.2 How to cancel Factory mode

Follow the procedure below to cancel the factory mode:

(1) Using the (>) button, select the FAC3 group, and then press the (>) button again. The following OSM picture will appear.




- (2) Press the (+) or (-) button to set the data value to '10'.
- (3) Press the (SELECT) button. The factory mode will be canceled.

1.7.3.3 How to enter FACTORY-HV mode

Follow the procedure below to enter the FACTORY-HV mode:

(1) Using the (>) button, select the FAC3 group, and then press the (>) button again. The following OSM picture will appear.



- (2) Press the (-) button to set the data value to '250'.
- (3) Press the (SELECT) key to enter the FACTORY-HV mode.



- (4) Press the (>) or (<) button. The FACTORY-HV mode will be canceled.

2. Adjustment procedure

2.1 Measuring instruments


- | | |
|---|---|
| (1) Signal generator A: | Astro Design VG-812 or equivalent |
| (2) Signal generator B: | Astro Design VG-829 or equivalent |
| (3) DC voltmeter: | 150V 0.5 Class or digital voltmeter |
| (4) High voltage meter: | 0.5 Class that can measure 40KV |
| (5) Luminance meter: | Minolta color analyzer CA-100 or equivalent |
| (6) AC voltmeter: | 150V/300V 0.5 Class or equivalent |
| (7) Oscilloscope: | Scope with band of 100MHz or more |
| (8) Landing measuring device: | Felmo product |
| (9) Double scale: | For width and distortion measurement |
| (10) Withstand voltage meter: | Kikusui Model TOS8650 or equivalent |
| (11) Grounding conductivity measuring instrument: | CLARE U.K. product |
| (12) Convergence meter: | MINOLTA CC-100 |

2.2 Preparatory inspections

- (1) There must be no cracks or remarkable contamination on the PWB.
- (2) There must be no remarkable lifting or inclination of the parts on the PWB, and the parts must not be touching.
- (3) The connectors must be securely inserted without crimping faults.
- (4) The CRT socket, anode cap and focus lead must be securely mounted.
- (5) The lead wires must not be pressed against the edges of the board.
- (6) The lead wires must not touch the high temperature parts such as the R-METAL, R-CEMENT or TR with FIN.
- (7) The board must not be bent, remarkably contaminated or scratched.
- (8) The CRT has no scratch or chipping.
- (9) Each potentiometer must turn smoothly.
- (10) Always set each potentiometer to the following positions before turning the power ON.

Potentiometer default settings

PWB name	IC sources	Name (symbol)	Default adjustment position	Remarks
PWB-MAIN	VR5A1	H-POSI	Center	
		FOCUS1	Center	FBT
		FOCUS2	Center	FBT
		SCREEN	Completely counterclockwise	FBT



* look at inside of the monitor from upper side.

2.3 Names of each monitor part

2.3.1 Configuration of front control panel




Figure 1 Front control panel

2.3.2 Configuration of rear input connector (signal input)




Figure 2 Rear input connector

2.3.3 OSM display matrix

2.3.3.1 User mode

Adjustment items	Setting contents	Default setting	Setting classification	
			By timings	Common
OSM group USER1				
BRIGHTNESS	0.0 ~ 100.0%	30.1%		○
CONTRAST	0.0 ~ 100.0%	100.0%		○
DEGAUSS	< + >			
CONSTANT BRIGHTNESS	< + >			○
OSM group USER2				
AUTO-ADJUST	< + >		○	
LEFT/RIGHT	0.0 ~ 100.0%		○	
DOWN/UP	0.0 ~ 100.0%	50%	○	
NARROW/WIDE	0.0 ~ 100.0%		○	
SHORT/TALL	0.0 ~ 100.0%		○	
OSM group USER3				
COLOR	COLOR1,2,3,sRGB,5	COLOR1		○
COLOR TEMP1,2,3,5	5000K-9300K	COLOR1:9300K		○
RED (GAIN)1,2,3,5	0.0 ~ 100.0%			○
GREEN (GAIN)1,2,3,5	0.0 ~ 100.0%			○
BLUE (GAIN)1,2,3,5	0.0 ~ 100.0%			
OSM group USER4				
IN/OUT	0.0 ~ 100.0%		○	
LEFT/RIGHT	0.0 ~ 100.0%		○	
TILT	0.0 ~ 100.0%		○	
ALIGN	0.0 ~ 100.0%		○	
ROTATE	0.0 ~ 100.0%	Adjustment value		○
TOP	0.0 ~ 100.0%		○	
TOP BALANCE	0.0 ~ 100.0%		○	
BOTTOM	0.0 ~ 100.0%		○	
BOTTOM BALANCE	0.0 ~ 100.0%		○	
OSM group USER5				
MOIRE CANCELER	0.0 ~ 100.0%	0.0%	○	
CONVERGENCE(HOR.)	0.0 ~ 100.0%	Adjustment value(16.8~82.7%)		○
CONVERGENCE(VER.)	0.0 ~ 100.0%	Adjustment value(27.8~71.7%)		○
LINEARITY(VER.)	0.0 ~ 100.0%		○	
VERTICAL BALANCE	0.0 ~ 100.0%		○	
GLOBAL SYNC(TL)	0.0 ~ 100.0%	Adjustment value(33.3~66.2%)		○
GLOBAL SYNC(TR)	0.0 ~ 100.0%	Adjustment value(33.3~66.2%)		○
GLOBAL SYNC(BL)	0.0 ~ 100.0%	Adjustment value(33.3~66.2%)		○
GLOBAL SYNC(BR)	0.0 ~ 100.0%	Adjustment value(33.3~66.2%)		○
OSM group USER6				
LANGUAGE	ENG/DEU/FRA/ESP/ITA/JPN	ENG		○
OSM POSITION	<- /+>	(OSM is at the center of picture)		○
OSM TURN OFF	5SEC ~ 120SEC	45SEC		○
OSM LOCK OUT	ON/OFF	OFF		○
IPM OFF MODE	ENABLE/DISABLE	ENABLE		○
EDGE LOCK	FRONT/BACK	BACK	○	
HOT KEY	OFF/ON	OFF		○
FACTORY PRESET	< + >			
OSM group USER7				
DISPLAY MODE				
MONITOR INFO		FE2111SB		
REFRESH NOTIFIER	OFF/ON	OFF		○

2.3.3.2 Factory mode

Adjustment items	Setting contents	Default setting	Setting classification	
			By timings	Common
OSM group USER1				
BRIGHTNESS	0.0 ~ 100.0%	30.1%		○
CONTRAST	0.0 ~ 100.0%	100.0%		○
DEGAUSS	<+>			
CONSTANT BRIGHTNESS	<+>			○
OSM group USER2				
AUTO-ADJUST	<+>			
LEFT/RIGHT	0.0 ~ 100.0%		○	
DOWN/UP	0.0 ~ 100.0%	50%	○	
NARROW/WIDE	0.0 ~ 100.0%		○	
SHORT/TALL	0.0 ~ 100.0%		○	
OSM group USER3				
COLOR	---			△
COLOR TEMP1,2,3,5	---			○
R GAIN1,2,3,5	---			○
G GAIN1,2,3,5	---			○
B GAIN1,2,3,5	---			○
OSM group USER4				
IN/OUT	0.0 ~ 100.0%		○	
LEFT/RIGHT	0.0 ~ 100.0%		○	
TILT	0.0 ~ 100.0%		○	
ALIGN	0.0 ~ 100.0%		○	
ROTATE	0.0 ~ 100.0%	Adjustment value		○
TOP	0.0 ~ 100.0%		○	
TOP BALANCE	0.0 ~ 100.0%		○	
BOTTOM	0.0 ~ 100.0%		○	
BOTTOM BALANCE	0.0 ~ 100.0%		○	
PCC CENTER	0.0 ~ 100.0%		○	
PCC SINE	0.0 ~ 100.0%		○	
OSM group USER5				
MOIRE CANCELER	0.0 ~ 100.0%	0.0%	○	
CONVERGENCE(HOR.)	16.8 ~ 82.7%	Adjustment value		○
CONVERGENCE(VER.)	27.8 ~ 71.7%	Adjustment value		○
LINEARITY(VER.)	0.0 ~ 100.0%		○	
VERTICAL BALANCE	0.0 ~ 100.0%		○	
GLOBAL SYNC(TL)	33.3 ~ 66.2%	Adjustment value		○
GLOBAL SYNC(TR)	33.3 ~ 66.2%	Adjustment value		○
GLOBAL SYNC(BL)	33.3 ~ 66.2%	Adjustment value		○
GLOBAL SYNC(BR)	33.3 ~ 66.2%	Adjustment value		○
OSM group USER6				
LANGUAGE	ENG/DEU/FRA/ESP/ITA/JPN	ENG		○
OSM POSITION	<- /+>	(OSM is at the center of picture)		○
OSM TURN OFF	5SEC ~ 120SEC	45SEC		○
OSM LOCK OUT	---	OFF		○
IPM OFF MODE	ENABLE/DISABLE	ENABLE		○
EDGE LOCK	FRONT/BACK	BACK	○	
HOT KEY	OFF/ON	OFF		○
FACTORY PRESET	< + >			
OSM group USER7				
DISPLAY MODE				
MONITOR INFO		FE2111SB		
REFRESH NOTIFIER	OFF/ON	OFF		○
DESTINATION	USA/EUR	USA: for North America EUR: for Europe		

Adjustment items		Setting contents	Default setting	Setting classification	
				By timings	Common
FACT 1					
C-PURITY-DIS	CPDIS	0(OFF)/1(ON)	1(ON)		○
PURITY-DIS	PRDIS	0(OFF)/1(ON)	1(ON)		○
MAG-ZERO-HV	HVZER	PRO(EEh)			
V-CANCEL	V-PUR	000 ~ 0FF			○
H-CANCEL	HPR-G	000 ~ 0FF			○
DBFV2 TOP	DBF2T	000 ~ 7F			○
DBFV2 BOTTOM	DBF2B	000 ~ 7F			○
DBFV4 TOP	DBF4T	000 ~ 7F			○
DBFV4 BOTTOM	DBF4B	000 ~ 7F			○
DBF-H-AMP	HFOCS	000 ~ 0FF		○	
DBF-V-AMP	VFOCS	000 ~ 7F		○	
DBF-H-PHASE	HFOCD	000 ~ 64		○	
SYNC-ON-GREEN	SOG-E	0(OFF)/1(ON)	0(OFF)		○
DIRECT-KEY	DIREC	0(OFF)/1(ON)	1(ON)		○
DDC-EEP-WP	WPDDC	0(Unwritable)/1(Writable)	0(Unwritable)		○
H PURITY CHECK	HPURC	000 ~ 002	0		
V PURITY CHECK	VPURC	000 ~ 002	0		
FACT 2					
YHTT	YH-TT	000 ~ 0FF			○
YHTB	YH-TB	000 ~ 0FF			○
YHJT	YH-JT	000 ~ 0FF			○
YHJB	YH-JB	000 ~ 0FF			○
XH-L	XH-L	000 ~ 0FF			○
XH-R	XH-R	000 ~ 0FF			○
PQH-TL	PQH-TL	000 ~ 0FF			○
PQH-TR	PQH-TR	000 ~ 0FF			○
PQH-BL	PQH-BL	000 ~ 0FF			○
PQH-BR	PQH-BR	000 ~ 0FF			○
S3H-TL	S3H-TL	000 ~ 0FF			○
S3H-TR	S3H-TR	000 ~ 0FF			○
S3H-BL	S3H-BL	000 ~ 0FF			○
S3H-BR	S3H-BR	000 ~ 0FF			○
YVTT	YV-TT	000 ~ 0FF			○
YVTB	YV-TB	000 ~ 0FF			○
YVJT	YV-JT	000 ~ 0FF			○
YVJB	YV-JB	000 ~ 0FF			○
XV-L	XV-L	000 ~ 0FF			○
XV-R	XV-R	000 ~ 0FF			○
PQV-TL	PQV-TL	000 ~ 0FF			○
PQV-TR	PQV-TR	000 ~ 0FF			○
PQV-BL	PQV-BL	000 ~ 0FF			○
PQV-BR	PQV-BR	000 ~ 0FF			○
S3V-TL	S3V-TL	000 ~ 0FF			○
S3V-TR	S3V-TR	000 ~ 0FF			○
S3V-BL	S3V-BL	000 ~ 0FF			○
S3V-BR	S3V-BR	000 ~ 0FF			○
FACT 3					
R-BIAS-H	R-BS1	000 ~ 0FF			○
G-BIAS-H	G-BS1	000 ~ 0FF			○
B-BIAS-H	B-BS1	000 ~ 0FF			○
R-BIAS-M	R-BS2	000 ~ 0FF			○
G-BIAS-M	G-BS2	000 ~ 0FF			○
B-BIAS-M	B-BS2	000 ~ 0FF			○
R-BIAS-L	R-BS3	000 ~ 0FF			○
G-BIAS-L	G-BS3	000 ~ 0FF			○
B-BIAS-L	B-BS3	000 ~ 0FF			○

2.4 Adjustment

2.4.1 How to select the factory adjustment (FACTORY) mode

2.4.1.1 Selecting with front panel switches

- (1) Turn the power ON while holding down EXIT button.
- (2) After step (1), release EXIT button after one to two seconds.
- (3) Confirm that 255 is displayed for the counter of FACT DATA on OSM display.
- (4) Set to 05 with (+) button.
- (5) When SELECT S/B MODE button is pressed, the factory mode will be entered.

This factory adjustment mode is entered with the above steps.

*The factory adjustment mode remains valid even after the power is turned OFF.

Note that steps (3) to (4) must be carried out within ten seconds. If ten seconds are exceeded, the mode will return to the user mode.

<Returning to the user mode from the factory mode>

- (1) Display FACT DATA on OSM picture with the group selection.
- (2) Set the counter value to 010 with (-) (+) buttons.
- (3) When SELECT S/B MODE button is pressed, the mode will return to the user mode.

2.4.2 Adjustments before aging

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Before aging		The only the sync. signal of No. 12:106.25kHz / 85Hz, 1600x1200

2.4.2.1 Adjusting the high voltage and high voltage protector

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	High voltage and high voltage protector		The only the sync. signal of No. 12:106.25kHz / 85Hz, 1600x1200

(Timing No. 12 (106.25 kHz/85 Hz, 1600x1200) SYNC signal is only input)

- (1) Turn the monitor power OFF and connect a high voltage indicator to the anode of CRT before turning the monitor power ON.
- (2) Select "FACT DATA****" on OSM and set to 250 using (-) button before pushing the SELECT S/B MODE button.
- (3) Select HVADJ (HV-ADJ CAUTION) on OSM to adjust the high voltage to 27.0kV $\pm$ 0.5kV.
- (4) Select XPCAL (XPRO-CALIBRATION) on OSM and turn the screen VR all the way down counterclockwise before adjusting the high voltage to 31.0kV $\pm$ 0.5kV by manipulating (+) (-) buttons.
- (5) With SELECT S/B MODE button pushed, the protector operation point is set, causing the high voltage to return to 27.0kV $\pm$ 0.5kV.
- (6) Rotate the screen VR so that OSM can be confirmed.
- (7) Select XPROT (XPRO-TST CAUTION) on OSM by the manipulation shown above and turn the screen VR all the way down counter-clockwise.
- (8) Raise the voltage manipulating (+) button and make sure that the high-voltage protection circuit gets activated at 31.0kV $\pm$ 0.5kV.

2.4.2.2 FOCUS adjustment (Rough adjustment)

- (1) Set the brightness so that the raster can be confirmed with the FBT picture potentiometer (screen VR).
- (2) Adjust the focus pack "FOCUS 1, 2" so that both edges of the picture are clear.

2.4.2.3 Shock test

- (1) Display the "color bar" with the signal generator A.
- (2) Confirm that there is no abnormality in the image when shock is applied on the monitor.

2.4.2.4 Preadjustment before aging

- (1) Change to FACTORY MODE (aging mode) in advance.
- (2) Display a full white with the signal generator A.
- (3) Confirm that the R, G and B channel images are output.
- (4) Confirm that the picture position, picture size, PCC and balance can be controlled, and roughly adjust.

- (5) Adjustment of BTCEN (BRIGHT-CENT), BTMAX (BRIGHT-MAX), BS1 (BIAS-H)
 - a) Input timing No. 12 (1600x1200 106.25K/85) with the signal generator (R, G and B OFF).


- b) Set each adjustment item to the following value.

BRIGHTNESS	: 7F
(FACT3)	
R-BS1(R-BIAS-H)	: 00
G-BS1(G-BIAS-H)	: 8A
B-BS1(B-BIAS-H)	: 00
BTCEN (BRIGHT-CENT)	: 5E0
BTMAX (BRIGHT-MAX)	: 800

- c) Connect PWB-CRT TP (R200G lead wire) to the probe.

- d) Select BTCEN (BRIGHT-CENT) in FACT3, set the black level voltage of PWB-CRT TP (R200G lead wire) to $70 \pm 0.5V$ with the oscilloscope (refer to the following picture).

* In use of the digital voltage meter, set it to $73 \pm 0.5V$.



- e) Set the back raster luminance to $0.5 \pm 0.3 \text{ cd/cm}^2$ with BRIGHTNESS adjustment.

- f) Adjust the back raster color coordination to the following value with R-BS1 (R-BIAS-H) and B-BS1 (B-BIAS-H).

x: 0.283 ± 0.02 / y: 0.297 ± 0.02

* Do not adjust BTCEN (BRIGHT-CENT) after the adjustment of back raster color coordination carried out at f) above, but it can be adjusted in main adjustment mentioned after 2.4.3.

* BRIGHTNESS should be adjusted when the back raster is varied in adjustment of purity and convergence.

- (6) Confirm that OSM power management is OFF.

- (7) Disconnect the signal and confirm that the following picture appears on OSM. Then adjust OSM picture luminance with BRIGHTNESS adjustment, and carry out heat run for 60 minutes or more.

OWN VER
S2-OW-** 1.*.**
(Initial data file name)

2.4.2.5 Adjusting the landing (ITC/4 corner purity adjustment)

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	landing		No. 12:106.25kHz / 85Hz, 1600x1200
			Full green

- Input the timing No. 12 (106.25kHz/85Hz, 1600x1200) full green signal.
- Turn OFF the monitor power to carry out hand degaussing.
- Select GLOBAL SYNC (TL) on OSM.
- Adjust to the best condition using (-) (+) buttons. Here, make sure that the adjusted value is within the range of OSM display value = 55h (85) to A9h (169).
- Carry out similar adjustment for TR/BL/BR (GLOBAL SYNC).
Note) When the substrate is replaced at the time of repair, set TL/TR/BL/BR to the values before replacement before carrying out adjustment.
- Input the timing No.12 (106.25kHz/85Hz, 1600x1200) full white signal.

2.4.3 Adjusting the picture size, position, distortion, DBF amplitude and phase

The manual adjustment methods are explained below. The adjustments are executed in the factory adjustment (factory) mode.

Adjust the picture size to the value indicated in the list of adjustment values.(Refer to 2.5.1.10 Adjustment value list.)

Adjust the distortion to the value indicated in the picture performance inspection item. (Refer to 2.5.1.8 Picture distortion.)

2.4.3.1 Adjusting the picture inclination


Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Picture inclination	Factory	No. 12:106.25kHz / 85Hz, 1600x1200
			Crosshatch with frame

Set OSM to ROTATE, and using (-) (+) buttons, set the raster inclination to be horizontal to the CRT face surface.

2.4.3.2 Adjusting the back raster position

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Back raster position	Factory	No. 12:106.25kHz / 85Hz, 1600x1200
			Only the sync. signal input

- Set BRIGHTNESS to 100% to show the back raster.
- Select LEFT/RIGHT and DOWN/UP, adjust the horizontal back raster position to the center of the bezel using (-) (+) buttons.
At this time, the raster width should be $|L1-L2| \leq 2.0\text{mm}$.



2.4.3.3 Adjusting the left/right distortion, picture width, picture position (LEFT/RIGHT) and vertical linearity (all preset)

- (1) Set DOWN/UP of the user mode to 50%.

<Setting in the factory mode with the following steps>


- (2) Adjust the vertical size to approx. 297mm, and the vertical position to the approximate center.
- (3) Select LINEARITY (VER.) and VERTICAL BALANCE with OSM, and adjust so that the vertical linearity is equal at the very top of the picture, at the very bottom of the picture, and at the center of the picture.
- (4) Select SHORT/TALL and DOWN/UP with OSM, and adjust the vertical width and vertical position to the specified values using (-) (+) buttons.
- (5) Select IN/OUT, ALIGN, PCC CENTER, TOP and BOTTOM with OSM, and adjust the vertical line at both side of the picture to the straight line using (-) (+) buttons.
- (6) If the left and right distortions differ, select LEFT/RIGHT (PIN VAL), TILT, TOP-BALANCE and BOTTOM-BALANCE with OSM, and adjust so that the distortions are visually balanced.
- (7) Select LEFT/RIGHT with OSM, and adjust the horizontal raster position to the center of the picture using (-) (+) buttons.
- (8) Select NARROW/WIDE with OSM, and adjust the horizontal raster width to the value given in the adjustment list using (-) (+) buttons. (Refer to 2.5.1.10 Adjustment value list.)


*Note (1) PCC SINE, LEFT/RIGHT (PIN VAL) and PCC CENTER are used only for touch up.

Note (2) The picture position and distortion must be within the ranges given in the picture performance inspection items. (Refer to 2.5.1.8 Picture distortion.)

2.4.3.4 Adjusting the DBF amplitude and phase

- (1) Connect the oscilloscope to the lead of R7A2 (SG702 side) on PWB-MAIN and to one of the signal outputs for the signal sources full R, G, B (VIDEO).
- (2) Set OSM to the select picture of HFOCUS (DBF-H-AMP) in FACT 1, and using (-) (+) buttons adjust the horizontal parabola wave amplitude (image area) to the value given in the list of adjustment values. (Refer to 2.5.1.10 Adjustment value list.)





DBF-H-AMP / PHASE adjustment

- (3) Set the output of the signal generator to crosshatch (white/normal).
- (4) Set OSM to the select picture of HFOCD (DBF-H-PHASE) in FACT1, and adjust the focus balance of point 1 and point 3 in the above figure using (-) (+) buttons.
- * (3) and (4) should be carried out with all preset timing.
- (5) Set OSM to the select picture of DBF2T (DBFV2 TOP) in FACT1, and adjust using (-) (+) buttons so that the focus level of point 4 and point 2 in the above figure can be balanced.
- (6) Set OSM to the select picture of DBF2B (DBFV2 BOTTOM) in FACT1, and adjust using (-) (+) buttons so that the focus level of point 2 and point 5 in the above figure can be balanced.
- * (5) and (6) should be carried out with timing No. 12 (106.25kHz/85Hz, 1600x1200).

2.4.4 Adjusting the cut off

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Cut off	Factory	No. 12:106.25kHz / 85Hz, 1600x1200

2.4.4.1 Adjusting BTCEN (BRIGHT-CENT), BTMAX (BRIGHT-MAX) and BS1 (BIAS-H)

<In case pre-adjustment before aging is carried out >

- (1) Input timing No. 12 (106.25kHz/85Hz, 1600x1200) with the signal generator (R, G and B OFF).
- (2) Set each adjustment item to the following value.

BRIGHTNESS	: 7F
(FACT3)	
R-BS1(R-BIAS-H)	: 00
G-BS1(G-BIAS-H)	: 8A
B-BS1(B-BIAS-H)	: 00
BTMAX (BRIGHT-MAX)	: 800
- (3) Set the back raster luminance to 0.3 +/- 1cd/m² with FBT screen VR.
- (4) Adjust the back raster color coordination to the value listed in the following table with R-BS1 (R-BIAS-H) and B-BS1 (B-BIAS-H).
- (5) Adjust the back raster luminance to 0.3 +/- 0.1cd/m² with BTCEN.
- (6) If the back raster color coordination is deviated from the values listed in the following table, repeat steps (4) and (5).
- (7) Adjust the back raster luminance to 3.0 +/- 0.2cd/m² with BTMAX.

<In case pre-adjustment before aging is not carried out >

(1) Input timing No. 12 (106.25kHz/85Hz, 1600x1200) with the signal generator (R, G and B OFF).


(2) Set each adjustment item to the following value.

BRIGHTNESS	: 7F
(FACT3)	
R-BS1(R-BIAS-H)	: 00
G-BS1(G-BIAS-H)	: 8A
B-BS1(B-BIAS-H)	: 00
BTCEN (BRIGHT-CENT)	: 5E0
BTMAX (BRIGHT-MAX)	: 800

(3) Connect PWB-CRT TP (R200G lead wire) to the probe.

(4) Select BTCEN (BRIGHT-CENT) in FACT3, set the black level voltage of PWB-CRT TP (R200G lead wire) to $70 \pm 0.5V$ with the oscilloscope (refer to the following picture).

* In use of the digital voltage meter, set it to $73 \pm 0.5V$.



(5) Set the back raster luminance to $0.3 \pm 1cd/m^2$ with FBT screen VR.

(6) Adjust the back raster color coordination to the value listed in the following table with R-BS1 (R-BIAS-H) and B-BS1 (B-BIAS-H).

(7) Adjust the back raster luminance to $0.3 \pm 0.1cd/m^2$ with BTCEN.

(8) If the back raster color coordination is deviated from the values listed in the following table, repeat steps (6) and (7).

(9) Adjust the back raster luminance to $3.0 \pm 0.2cd/m^2$ with BTMAX.

* The following table is applicable for the monitor without the back cover.

Adjustment value of BS1 (BIAS-H)

Adjustment item		BS1 (BIAS-H)
Color temperature		(9300K)
Color coordination	x	0.283 ± 0.015
	y	0.297 ± 0.015

2.4.4.2 Adjusting BS2 (BIAS-M) / BS3 (BIAS-L)

(1) Set R-BS2 (R-BIAS-M), G-BS2 (G-BIAS-M) and B-BS2 (B-BIAS-M) to the value listed in the following table.

(2) Set R-BS3 (R-BIAS-L), G-BS3 (G-BIAS-L) and B-BS3 (B-BIAS-L) to the value listed in the following table.

As the values listed in the following table are the finite differences from the values of BS1 (BIAS-H), this adjustment should be carried out after adjustment of BS1 (BIAS-H).

Adjustment data of BS2 (BIAS-M) / BS3 (BIAS-L)

(*The following data is the finite difference from BS 1 (BIAS-H).)

Adjustment item		BS2 (BIAS-M)	BS3 (BIAS-L)
Color temperature		(6500K)	(5000K)
Data	R-BS	+3	+5
	G-BS	same value	same value
	B-BS	-4	-8

2.4.5 Setting CONSTANT BRIGHTNESS circuit (Factory mode)

Note) This operation should be carried out after the adjustment of cut-off. In addition, heat-running should be fully carried out.

2.4.5.1 Reading beam current default data

- (1) Input timing No. 12 (106.25kHz/85Hz, 1600x1200) crosshatch signal with the signal generator.
- (2) Select CONSTANT BRIGHTNESS and push (-) button, then it starts to read the beam current default data.
- (3) When the reading is completed, OSM standard voltage DAC (Digital Analog Converter) data and the beam current default data of each color (R/G/B) are indicated. Then, confirm that the data is within the following value range.

Standard voltage DAC data	: 50-F0 (HEX)
Red beam current default data	: 73-8C (HEX)
Green beam current default data	: 73-8C (HEX)
Blue beam current default data	: 73-8C (HEX)
- (4) If the above data could not be within the value range specified above (3), carry out steps (2) and (3) mentioned above once.
- (5) Measure the luminance and color coordination of the back raster.

2.4.5.2 Confirming CONSTANT BRIGHTNESS function

- (1) Select COSTANT BRIGHTNESS. Push (+) button, and it decrements the BRIGHTNESS data to imitate the deteriorated condition due to elapsed time, then compensation function starts to operate.
- (2) Measure the color coordination and luminance of the back raster after compensation. Compare them to the data measured in 2.4.5.1 (5) to confirm that the differences are within the following value range.

Color coordination of x and y	: within +/- 0.020
Luminance	: within +/- 0.05cd/m ²
- (3) If the color coordination and luminance of the back raster could not be within the value range specified in (2) above, select CONSTANT BRIGHTNESS and push RESET button, then carry out step 2.4.5.1 (2) once.
- (4) Select CONSTANT BRIGHTNESS, and push RESET button.

2.4.6 Adjusting the RGB drive signal

2.4.6.1 Adjusting GN1 (GAIN-H) (adjustment of 9300K)

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	GN1 (GAIN-H)	Factory	No. 12:106.25kHz / 85Hz, 1600x1200
			Full white

- (1) Input the following adjustment timing with the signal generator.
Pattern: Full white (Input amplitude = 0.7Vp-p)
Adjustment timing: No.12 (106.25kHz/85Hz, 1600x1200)
- (2) Select CONTRAST with OSM, and set to MAX using (+) button.
- (3) Select BRIGHTNESS, and set the data to 7F using (-) (+) buttons.
- (4) Output the solid color for the picture from Signal generator A, and input GREEN only.
- (5) Set G-GN1 (G-GAIN-H) with OSM, and adjust the luminance of full green picture to the specified value listed in the following table with (-) (+) buttons.
- (6) Input BLUE, RED and GREEN, and select B-GN1 (B-GAIN-H), R-GN1 (R-GAIN-H) and G-GN1 (G-GAIN-H) appropriately, then adjust each data to the specified value listed in the following table with (-) (+) buttons.
- (7) Confirm that the variation of the color coordination data of x and y is within +/- 0.015 when CONTRAST is set to 25cd/m² with OSM.

- (8) Adjust GN2 (GAIN-M) and GN3 (GAIN-L) to the specified value listed in the following table in the same manner as GN1 (GAIN-H).

COLOR TEMPERATURE		GN1 (GAIN-H)	GN2 (GAIN-M)	GN3 (GAIN-L)	TOLERANCE
Color temperature		(9300K)	(6500K)	(5000K)	
Full green luminance		77.0	66.0	54.0	±1.0
Full White color coordination	x	0.283	0.313	0.345	±0.005
	y	0.297	0.329	0.359	±0.005
Full white luminance(cd/m ²)		105 or more	90 or more	75 or more	

(9) Setting R/G/B MAX GAIN

Set the MAX GAIN value for the following formula to the following address (all setting values are indicated by HEX).

Firstly hexadecimal number should be converted to decimal number to be calculated, then the result figured out is return to hexadecimal numbers to be written into the applicable address.

How to write into address is described below.

MAX GAIN = MAX value of R/G/B GAIN adjustment value (*1) x {1 + (MAX value of SBCN1, 2 (*2) /FF)

Address (HEX): 89 (R-GAIN-MAX), 8a (G-GAIN-MAX), 8b (B-GAIN-MAX)

(*1): MAX value of R/G/B GAIN adjustment value is the maximum one among R-GN1, G-GN1, B-GN1, R-GN2, G-GN2, B-GN2, R-GN3, G-GN3 and B-GN3 in OSM (FACTORY-3) adjusted according to the procedure (1) to (8) mentioned above.

(*2): MAX value of SBCN1, 2 is the maximum one between SBCN1 and SBCN2 in OSM (FACTORY-3).


Note) All of (MAX GAIN), (MAX value R/G/B GAIN) and (SBCN1 and SBCN2) are indicated by hexadecimal number (HEX), the value is to be converted to the decimal number (DEC) first to be calculated, then, converted to the hexadecimal number (HEX).

<How to rewrite into address>

(a) Change to FACTORY MODE in advance.

(b) Set the counter of FACT DATA on OSM to 99 using (-) (+) buttons, and push SELECT button.

(c) Press either (◀) or (▶) button, and confirm that the following picture appears.



(d) Using (-) (+) buttons rewrite the counter for every hexadecimal data to the one figured out with the calculation mentioned above (decimal data is to be rewritten following to hexadecimal one synchronously).

(e) Press EXIT button, then the rewritten data is to be registered.

(f) To disable this rewriting function, turn the power OFF. However, FACTORY MODE is still alive even if the power was turned off.

NOTE) Be careful NOT to wrongly rewrite the data since this rewriting function is available for all of the EDID data.

2.4.6.2 Adjusting ABL

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	ABL	Factory	No. 12:106.25kHz / 85Hz, 1600x1200
			Full white

- (1) Input the following adjustment timing with the signal generator.

Pattern: Full white (input amplitude = 0.7Vp-p)


Adjustment timing: No.12 (106.25kHz/85Hz, 1600x1200)

- (2) Select ABLAJ (ABL) with OSM, and adjust to 115cd/m² +/- 5.

Here, the picture size should follow 2.5.1.10 Adjustment value list.

2.4.7 Adjusting the focus

NOTE) For adjustment of focus with FOCUS VR, be sure to use ISOLATED alignment driver.

	Normal or reverse display	Point to align with
Vertical line	Reverse display (Green)	 Adjust to FOCUS JUST at the circled sections using FBT FOCUS1-VR mainly and FBT FOCUS2-VR with well balancing. The ratio of core : Halo of the vertical lines at both sides should be 1 : 1.
Horizontal line	Normal display	 Adjust to FOCUS JUST at the center of screen (circled section) using FBT FOCUS1-VR mainly and FBT FOCUS2-VR with well balancing. Adjust to halo condition once, then adjust to FOCUS JUST.

* Adjust halo to a quarter of core with camera adjustment.

Halo should be a half of core maximum.

<Adjusting the static focus>

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Static focus		No. 12:106.25kHz / 85Hz, 1600x1200
			H character, crosshatch

For steps (1) and (2), use the timing No. 12 (106.25kHz/85Hz, 1600x1200) H character pattern and crosshatch pattern.

For step (3), use all preset timing H character patterns and crosshatch patterns.

- Display a green or white crosshatch pattern, and adjust the focus according to the procedure mentioned above.
- If the DBF voltage is insufficient or excessive, select HFOCS (DBF-H-AMP) from OSM, and readjust with (-) (+) buttons. Then repeat step (1), and adjust so that the following judgement conditions are satisfied.
- For all of the other preset timings, if the DBF voltage is insufficient or excessive, select HFOCS (DBF-H-AMP) from OSM, and readjust with (-) (+) buttons.
- If the focus is unbalanced at right side and left side with other preset timings. Select HFOCD (DBF-H-PHASE) and readjust with (-) (+) buttons.
- If the focus is unbalanced at top and bottom with timing No. 12 (106.25kHz/85Hz, 1600 x 1200), select DBF2T (DBFV2 TOP) and DBF2B (DBFV2 BOTTOM) and readjust with (-) (+) buttons.

- (6) After inputting check timing No. 5 in user mode and operates AUTO-ADJUST function, confirm the focus with "e" character pattern in reverse. If "e" character is indistinct, repeat step (1) to readjust.

*Adjustment voltage max value:

DBF-H-AMP H width: 396mm: 430V

DBF-V-AMP V width: 297mm: 200V

The focus is judged as follows.

Timing	Judgment pattern (Note 1) (Note 2)
Normal display (All preset)	Crosshatch pattern
Reverse display Resolution: $\leq 1600 \times 1200$ Resolution: $> 1600 \times 1200$	Judge with pattern A Judge with pattern B

(Note 1) Pattern A: Font 7 × 9, Cell 10 × 11, e character

Pattern B: Font 7 × 9, Cell 10 × 11, H character


(Note 2) Focus judgement: Crosshatch pattern should be used for normal display judgement

The ratio of core : Halo is as follows.

Should be 1 : 0.5 or less at the center of the picture.

Should be 1 : 1.5 or less at the both sides of the picture

To judge the reverse display, do not carry out a relative evaluation with the other point on the screen. Instead, judge whether the e (H) character can be read distinctly at that point.



2.4.8 Adjusting the convergence

2.4.8.1 Adjusting with ITC

Before adjusting the center mis-convergence and axial mis-convergence, carry out sufficient full white aging (100cd/m² or more, for one hour or more). Then, adjust with the following timing.



Timing: No. 12 (106.25kHz/85Hz, 1600x1200) crosshatch pattern

Confirm that the following DDCCP default setting is as shown in the table of 2.3.2.2 Factory mode (OSM display matrix).












All items of OSM group USER5 and FACT2 of Factory mode


Adjust the horizontal and vertical convergence to the optimum setting with the CRT CP ring, etc.

(Refer to following drawings.)












Adjusting the center misconvergence and axial misconvergence









Adjustment item name	Problem	Adjustment point	Adjustment procedure
H-STATIC V-STATIC			Adjust to +/- 0.1mm or less with CP-ASSY 4P.
YH axial deviation			Adjust so that TOP+BOTTOM are +/- 0.1mm or less with YH volume.
YV axial deviation			Adjustment making much of horizontal trapezoidal distortion Adjust optimally using DY left/right shaking YV volume. The remaining YV misconvergence should be adjusted with DDCP.
XH axial deviation			Adjust so that LEFT-RIGHT is +/- 0.1mm or less with XH slider.
XV characteristics			Only when XV (B-Bow) is +/- 0.15mm or more, adjust so that LEFT-RIGHT is +/- 0.15mm or less with the interlock of B-Bow 4P and CP-ASSY 4P.
XV axial deviation			Adjust so that LEFT+RIGHT is +/- 0.15mm or less with XV differential coil.











2.4.8.2 Adjusting DDCP









- (1) Input the timing No. 12 (106.25kHz/85Hz,1600x1200) crosshatch pattern.
- (2) Enter the factory mode.
- (3) Adjust in the following order. (It is assumed that the center and axial misconvergence on the previous page have already been adjusted.)









Adjustment order	Adjustment item name	Problem	Adjustment point	Adjustment procedure
4H-COIL				
1	CONVERGENCE HOR.			Adjust to 0.05mm or less. (Adjustment target is 0mm.)
2	YH-TT			Adjust YH (Top) to 0.05mm or less with balance adjustment of YH-TT and YH-JT. (Adjustment target is 0mm.) (NOTE) The operating amount at YH-M(Top) when moving YH-TT and YH-JT : YH-TT < YH-JT
	YH-JT			
3	YH-TB			Adjust YH (Bottom) to 0.05mm or less with balance adjustment of YH-TB and YH-JB. (Adjustment target is 0mm.) (NOTE) The operating amount at YH-M (Bottom) when moving YH-TB and YH-JB : YH-TB < YH-JB
	YH-JB			
4	XH-L			Adjust to 0.1mm or less.
5	XH-R			Adjust to 0.1mm or less.

Adjustment order	Adjustment item name	Problem	Adjustment point	Adjustment procedure
4H-COIL				
6	S3H-TL		S3H(Top Left) 	Adjust to 0.3mm or less.
7	S3H-TR		S3H(Top Right) 	Adjust to 0.3mm or less.
8	S3H-BL		S3H(Bottom Left) 	Adjust to 0.3mm or less.
9	S3H-BR		S3H(Bottom Right) 	Adjust to 0.3mm or less.
10	PQH-TL		PQH (Top Left) 	Adjust to 0.3mm or less.
11	PQH-TR		PQH (Top Right) 	Adjust to 0.3mm or less.

Adjustment order	Adjustment item name	Problem	Adjustment point	Adjustment procedure
4H-COIL				
12	PQH-BL		 PQH (Bottom Left)	Adjust to 0.3mm or less.
13	PQH-BR		 PQH (Bottom Right)	Adjust to 0.3mm or less.

Adjustment order	Adjustment item name	Problem	Adjustment point	Adjustment procedure
4V-COIL				
1	CONVERGENCE VER.			Adjust to 0.05mm or less. (Adjustment target is 0mm.)
2	YV-TT YV-JT		 YV (TOP) YV-M (TOP)	Adjust YV (Top) to 0.05mm or less with balance adjustment of YV-TT and YV-JT. (Adjustment target is 0mm.) (Note) The operating amount at YV-M (Top) when moving YV-TT and YV-JT. YV-TT < YV-JT
3	YV-TB YV-JB		 YV-M (BOTTOM) YV (BOTTOM)	Adjust YV (Bottom) to 0.05mm or less with balance adjustment of YV-TB and YV-JB. (Adjustment target is 0mm.) (Note) The operating amount at YV-M (Bottom) when moving YV-TB and YV-JB. YV-TB < YV-JB

Adjustment order	Adjustment item name	Problem	Adjustment point	Adjustment procedure
4V-COIL				
4	XV-L		XV(Left) 	Adjust to 0.1mm or less.
5	XV-R		XV(Right) 	Adjust to 0.1mm or less.
6	S3V-TL		S3V(Top Left) 	Adjust to 0.3mm or less.
7	S3V-TR		S3V(Top Right) 	Adjust to 0.3mm or less.
8	S3V-BL		S3V(Bottom Left) 	Adjust to 0.3mm or less.
9	S3V-BR		S3V(Bottom Right) 	Adjust to 0.3mm or less.

Adjustment order	Adjustment item name	Problem	Adjustment point	Adjustment procedure
4V-COIL				
10	PQV-TL			Adjust to 0.3mm or less.
11	PQV-TR			Adjust to 0.3mm or less.
12	PQV-BL			Adjust to 0.3mm or less.
13	PQV-BR			Adjust to 0.3mm or less.

* Specify the adjustment value range of the following adjustment items in general DDCP adjustment.

Adjustment items	Adjustment value range (Factory mode))
CONVERGENCE (HOR.)	2Bh (43) - D3h (211) (OSM display value=DAC output value)
CONVERGENCE (VER.)	47h (71) - B7h (183) (OSM display value=DAC output value)

2.4.9 Default settings (With factory mode)

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Default settings	Factory mode	Each adjustment timing

- (1) Set the default values as shown in the table (user mode) given in OSM display (Refer to 2.3.2.1 User mode).
If the setting class is an item with each timing, carry out with each adjustment timing.
- (2) Return to the user mode with the front panel.
- (3) Execute FACTORY PRESET to confirm that each OSM setting is as shown in the table (user mode) given in OSM display (Refer to 2.3.2.1 User mode).
Only CONTRAST will be set to 100% when RESET button is pressed in the normal mode.
- (4) How to set OSM BRIGHTNESS RESET value (30.1%) in user mode.
 - (a) Change to FACTORY MODE in advance.
 - (b) Set the counter of FACT DATA on OSM to 99 using (-) (+) buttons, and push SELECT button.
 - (c) Using (◀) (▶) buttons to set ADDR to 0B1.
 - (d) Using (-) (+) buttons set DATA to 04D.
 - (e) Press EXIT button to record 04D set in (d) mentioned above.
 - (f) To disable this rewriting function, turn the power OFF (FACTORY MODE is still alive even if the power was turned OFF).

Return to USER MODE.

Select BRIGHTNESS with OSM, and press RESET button, then the data (04D = 30.1%) set in (d) mentioned above is called.

(For your information; when (-) and (+) buttons are pressed simultaneously, the data is set to 50%.)

- (5) After setting the default values, turn the power button OFF.

2.5 Inspections (In normal mode)

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Inspections	Normal mode	

2.5.1 Electrical performance

Inspect the electrical performance after confirming that the contrast is set to MAX and the bright is set to center (by pressing (-) (+) buttons simultaneously).

After inspection, carry out FACTORY PRESET operation.

2.5.1.1 Withstand voltage

There must be no abnormality when 1500VAC is applied for two seconds between both ends of the AC input terminal and chassis, and between the DG coil terminal and chassis.

The cut-off current should be 20mA.

2.5.1.2 Grounding conductivity check

Check that the resistance value is 100ohms or less when 25A is passed between the AC input terminal grounding GND and chassis GND.

2.5.1.3 Degaussing coil operation

Confirm that when OSM DEGAUSS is executed, the picture vibrates and then stops.

2.5.1.4 IPM OFF MODE function operation (Set the AC power input to 230V)

Confirmation timing
Timing No. 12 (106.25kHz / 85Hz, 1600x1200)

Use the full white pattern without R, G, B signals.

Select IPM OFF MODE from OSM, and set to 1:ENABLE.

(1) IPM OFF MODE ENABLE

- (a) Confirm that when H and V SYNCs are removed, the system waits for approx. five seconds, displays IPM OFF MODE for approx. three seconds, and then the picture darkens.

Also confirm that Power Indicator changes to orange and the power consumption is as follows.

Power consumption	2W or less
-------------------	------------

- (b) Confirm that when H and V SYNCs are input again, the high voltage is recovered, and the picture appears in approx. five seconds.

2.5.1.5 Confirming the GLOBAL SYNC (CORNER-Purity) function

Confirmation timing
Timing No. 12 (106.25kHz / 85Hz, 1600x1200)

Input a (full white display), and press (-)(+) buttons to change GLOBAL SYNC (TR/TL/BR/BL). Confirm that the color coordination around the picture changes.

2.5.1.6 Focus, picture performance

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Focus, picture performance		Check timing No.5, "e" character reverse display Check timing No.6, chrosshatch normal display

The picture must be evenly bright with check timing No. 5 "e" character reverse display and check timing No. 6 chosshatch normal display.


2.5.1.7 Misconvergence

After heat running for 20 minutes or more, the mis-convergence amount in the horizontal and vertical directions must be below the following values.

The mis-convergence amount is the value between the two colors of R, G and B separated the most in the horizontal (X) and vertical (Y) directions when a 15 vertical lines x 11 horizontal lines crosshatch is displayed.

This adjustment should be carried out with the convergence meter MINOLTA CC-100.

Zone	Mis-convergence amount				
A	0.25mm or less				
B	0.35mm or less				
Measurement timing (Timing No.)	12				










2.5.1.8 Picture distortion

When the picture distortion is measured, each distortion of the preset timing must be less than the following values.

<Picture performance inspection items> Inspect the following items for the picture distortion.

[illegible]

No.	Item	Judgement reference value	Input signal
4.	Line curve (crosshatch pattern outer contour)  Δx: Curve within 50mm range (horizontal) Δy: Curve within 50mm range (vertical)	$\Delta x \leq 1.0\text{mm}$ $\Delta y \leq 1.0\text{mm}$	Crosshatch pattern
5.	Horizontal trapezoid (top/bottom), vertical trapezoid (left/right)  $\Delta y = y1 - y2$ $\Delta x = x1 - x2$ - Control with the above right value for each the top, bottom, left and right.	$\Delta y \leq 2.0\text{mm}$ $\Delta x \leq 1.8\text{mm}$	
6.	Top/bottom pin and barrel, left/right pin and barrel 	$\Delta yb \leq 1.3\text{mm}$ $\Delta yp \leq 1.5\text{mm}$ $\Delta x \leq 1.0\text{mm}$	
7.	Parallelogram distortion  Measure the larger of x1 and x2.	$x \leq 0.8\text{mm}$	
8.	Inclination  Measure $\Delta y = y1 - y2$.	$\Delta y \leq 2.0\text{mm}$	

No.	Item	Judgement reference value	Input signal
9.	Distortion Must be within the following frame.* (Note, excluding ROTATION) 	$y \leq 2.0\text{mm}$ $x \leq 2.0\text{mm}$	Crosshatch pattern
10.	Picture position Display picture 	$ L1-L2 \leq 5.0\text{mm}$ $ L3-L4 \leq 3.0\text{mm}$	Full white

2.5.1.9 Linearity

Measure the linearity with a 17 horizontal line x 13 vertical line crosshatch.

Horizontal linearity : fH=30-40kHz whole : 15% or less, adjacent : 7% or less

fH=40-60kHz whole : 12% or less, adjacent : 7% or less

fH=60-115kHz whole : 10% or less, adjacent : 7% or less

Vertical linearity : whole : 10% or less, adjacent : 7% or less

Calculation expression : $\frac{(X_{\max} - X_{\min})}{(X_{\max} + X_{\min})/2} \times 100(\%)$

* If any doubts arise about the judgment, judge with the horizontal/vertical width tolerance of $\pm 3\text{mm}$, picture position: $|L1-L2| \leq 3.0\text{mm}$ and $|L3-L4| \leq 3.0\text{mm}$.

2.5.1.10 Adjustment value list

The horizontal width, vertical width and DBF-H/V amplitude must be within the following ranges.

Timing	Horizontal width (mm)	Vertical width (mm)	DBF-H amplitude (H)		DBF-V amplitude (V)	
No.	Adj. value	Adj. value	Standard Adj. value	Max. Adj. value	Standard Adj. value	Max. Adj. value
1						
2	396±5	297±4	400±5	430	135±20	200
3						
4						
5	396±5	297±4	400±5	430	135±20	200
6						
7	396±5	297±4	400±5	430	135±20	200
8	396±5	297±4	400±5	430	135±20	200
9	396±5	297±4	400±5	430	135±20	200
10	396±5	297±4	400±5	430	135±20	200
11	396±5	297±4	400±5	430	135±20	200
12	396±5	297±4	400±5	430	135±20	200
13						
14						
15	396±5	297±4	400±5	430	135±20	200
16						
17						
18						
19						
20						
21						
22						
23						
24						
25						
26						
27						
28						

Standard adjustment value: in case of determining DBF voltage

Maximum adjustment value: the value impossible to set the maximum of DBF voltage

2.5.1.11 Checking the functions during Composite Sync input

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Checking the functions during Composite Sync input		Check 2 : 35kHz / 66Hz
			Full white

[Composite Sync]

Timing: Check 2 (35kHz/66Hz), full white

In the normal mode, input the above timing to confirm that the operation is normal.

2.5.1.12 Confirming the reset operation

Confirmation timing
Timing No. 12 (106.25kHz / 85Hz, 1600x1200)

After varying NARROW/WIDE somewhat, press RESET button to confirm that the data returns to the original value.

2.5.1.13 Confirming the full white luminance/color coordination

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Confirming the full white luminance / color coordination	Factory mode	No.12: 106.25kHz / 85Hz, 1600x1200
			Full white

Timing No. 12 (106.25kHz/85Hz, 1600x1200), input amplitude = 0.7Vp-p, BRIGHT : 7F (50%)

Confirm that the full white luminance/color coordination is the following value.

*9300K: should be confirmed with COLOR 1.

*5000K: should be confirmed with COLOR 5.

*6500K: should be confirmed using color temperature 6500K with color temperature adjustment (⦿⦿⦿).

Confirmed item		9300K	6500K	5000K
Luminance		105 or more	90 or more	77 or more
Color temperature	x	0.283 ± 0.007	0.313 ± 0.007	0.345 ± 0.007
	y	0.297 ± 0.007	0.329 ± 0.007	0.359 ± 0.007

Confirmation of OSM color temperature (9300K)

$x=0.283 \pm 0.04$ $Y=0.297 \pm 0.05$

*Confirmation should be carried out at white section on OSM picture.

2.5.1.14 Confirming CONVERGENCE compensation function

Confirm that CONVERGENCE changes by varying CONVERGENCE (HOR.) and CONVERGENCE (VER.).

2.5.1.15 Confirming ROTATION compensation function

Confirm that the picture rotates by changing ROTATE.

2.5.1.16 Luminance/color coordination uniformity

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Luminance/color coordination uniformity		No.12: 106.25kHz / 85Hz, 1600x1200

The luminance ratio between the center and periphery must be 80% or more with timing No. 12 (106.25kHz/85Hz, 1600x1200) COLOR 1.

The color coordination difference between the center and periphery must be $\Delta x, y < \pm 0.012$ with COLOR 1.

2.5.1.17 Confirming the color tracking

Status indicator	Adjustment item	Adjustment mode/set	Input signal/pattern
	Confirming color tracking	Factory mode	No.12 : 106.25kHz/85Hz, 1600x1200
			BRIGHTNESS : 7F (50%)

Confirm with the timing No. 12 (106.25kHz/85Hz, 1600x1200), BRIGHTNESS : 7F (50%) and COLOR1 (9300K) in factory mode.

Measure the color coordination at the center of the picture using a full white pattern (input amplitude = 0.7Vp-p).

Confirm that the color coordination change is within the ± 0.015 range when the CONTRAST is set to 25cd/m² with OSM.

2.5.1.18 CRT installation position

CRT installation position tolerance Within ± 3 mm in vertical direction Within ± 2.5 mm in horizontal direction
Inclination: Within ± 2.5 mm at bezel reference

2.5.1.19 Confirming SB MODE operation

Timing No.12 (106.25kHz/85Hz, 1600x1200)

Input amplitude = 0.7Vp-p (white window)

The following items should be confirmed with CONTRAST: MAX and BRIGHTNESS: 50%.

SB MODE	Confirmation item		9300K
SB-MODE2	W-Window luminance		150 or more
	W-Window color coordination	x	0.283 ± 0.015
		y	0.297 ± 0.015
	Back raster luminance		Approx. 0.8cd/m ²

* Confirm that the color is not saturated with the white window picture during SB MODE2 operating.

* Confirm the following items during SB MODE2 operating.


(1) Compensation of γ :

Confirm that A and B of the following test pattern become similar black color.

Confirm that C and D of the following test pattern become similar white color.

(2) Compensation of outline:


Confirm that the overshoot (ringing) appears on the left edge of C of the following test pattern.



2.5.1.20 Confirming AUTO-ADJUST operation

(Timing No. 22 (114kHz/85Hz, 1600X1280))

- (1) Select AUTO ADJUST with OSM in user mode, and press (+) button.
- (2) Confirm that AUTO ADJUST function operates and the crosshatch frame should be within phosphor area.



2.5.1.21 Others

- (1) When any button is pressed, the changes must be smooth, and there must be no abnormalities such as noise.
- (2) Synchronization must not flow when the power button is turned ON and OFF.
- (3) Confirm that Power Indicator is lit.

2.6 DDC function, check of asset management

This writing operation should be carried out with the service tool (refer to the followings for detail of service tool).

The version of the service tool software used is as follows.

Service tool S/W folder name: SVT312NM210

Service tool S/W version: Ver3.12-2.1-0

Be sure to read "Read me first" first in using the service tool.

For concrete use, refer to the service tool manual attached to the service tool.

Lower 5 digits of S/N → converted to hex. Numbers → registered in ascending order

Upper 3 digits of S/N → 0 (according to VESA standard)

(Ex.) 512002978 → 00000BA2 → Models having NO ASSET function Models having ASSET function

MPU side Address (H)	Dedicated EEPROM side Address (H)	Data (H)
78C	0C	A2
78D	0D	0B
78E	0E	00
78F	0F	00

[ASCII conversion]

Using the barcode system read the serial numbers (9 digits) assigned at NMV (Nagasaki), then establish the serial number through the following conversion.

S/N → converted to ASCII code → registered (to Monitor Descriptor #4) in descending order

(ex.) 512A02978

↓
35 31 32 41 30 32 39 37 38

↓
Models having NO ASSET function Models having ASSET function

MPU side Address (H)	Dedicated EEPROM side Address (H)	Data (H)
E81	71	35
E82	72	31
E83	73	32
E84	74	41
E85	75	30
E86	76	32
E87	77	39
E88	78	37
E89	79	38
E8A	7A	0A → shows the end of S/N data*
E8B	7B	20 → shows blank*
E8C	7C	20 → shows blank*
E8D	7D	20 → shows blank*

*Fixed data (set according to the number of digits of S/N)

2.6.1 DDC write data contents

The contents of DDC write data must be as follows.

EDID DATA DUMP HEX 00 FF FF FF FF FF FF 00 38 A3 DA 61 SN SN SN SN WW YY 01 03 0C 28 1E 78 EB 9C 68 A0 57 4A 9B 26 12 48 4C FF EF 80 31 59 45 59 61 59 71 4F 81 99 A9 4F C1 4F D1 4F A6 59 40 30 62 B0 32 40 40 C0 13 00 8C 29 11 00 00 1E 00 00 00 FD 00 32 A0 1E 73 21 00 0A 20 20 20 20 20 20 00 00 00 FC 00 4E 45 43 20 46 45 32 31 31 31 53 42 0A 00 00 00 FF 00 S2 S2 S2 S2 S2 S2 S2 S2 S2 S2 S2 S2 S2 00 CS	Established Timings: 720x400 @ 70 Hz 720x400 @ 88 Hz 640x480 @ 60 Hz 640x480 @ 67 Hz 640x480 @ 72 Hz 640x480 @ 75 Hz 800x600 @ 56 Hz 800x600 @ 60 Hz 800x600 @ 72 Hz 800x600 @ 75 Hz 832x624 @ 75 Hz 1024x768 @ 60 Hz 1024x768 @ 70 Hz 1024x768 @ 75 Hz 1152x870 @ 75 Hz 1280x1024 @ 75 Hz	Detailed Timing (block #1): ---Preferred Timing Mode--- Pixel Clock: 229.50 MHz Horizontal Active: 1600 pixels Horizontal Blanking: 560 pixels Vertical Active: 1200 lines Vertical Blanking: 50 lines (Horizontal Frequency: 106.25 kHz) (Vertical Frequency: 85.0 Hz) Horizontal Sync Offset: 64 pixels Horizontal Sync Width: 192 pixels Vertical Sync Offset: 1 lines Vertical Sync Width: 3 lines Horizontal Border: 0 pixels Vertical Border: 0 lines Horizontal Image Size: 396 mm Vertical Image Size: 297 mm Interlaced: NO Image: Normal Display Sync: Digital Separate Bit 1: ON Bit 2: ON
SN: Serial number WW: Week of Manufacture YY: Year of Manufacture S2: ASCII Serial Number CS: Check Sum	Standard Timing #1: Horizontal Active Pixels: 640 Aspect Ratio: 4:3 (480 active lines) Refresh Rate: 85 Hz	Monitor Range Limits (block #2): Minimum Vertical Rate: 50 Hz Maximum Vertical Rate: 160 Hz Minimum Horizontal Rate: 30 kHz Maximum Horizontal Rate: 115 kHz Maximum Pixel Clock: 330 MHz GTF Data: 00 0a 20 20 20 20 20 20
-- EDID DATA DUMP TEXT -- Manufacturer Code: NEC Product Code (HEX): 61DA Product Code (DEC): 25050 (Microsoft INF ID: NEC61DA) Serial Number (HEX): SN Week of Manuf: WW Year of Manuf: YY	Standard Timing #2: Horizontal Active Pixels: 800 Aspect Ratio: 4:3 (600 active lines) Refresh Rate: 85 Hz	Monitor Name (block #3): NEC FE2111SB
EDID Version: 1 EDID Revision: 3 Extension Flag: 0	Standard Timing #3: Horizontal Active Pixels: 1024 Aspect Ratio: 4:3 (768 active lines) Refresh Rate: 85 Hz	Monitor Serial Number (block #4): S2
Video: Input Singal: ANALOG Setup: NO Sync on Green: NO Composite Sync: YES Separate Sync: YES V Sync Serration: NO V Signal Level: 0.700V/0.300V (1V p-p)	Standard Timing #4: Horizontal Active Pixels: 1152 Aspect Ratio: 4:3 (864 active lines) Refresh Rate: 75 Hz	SN: Serial number WW: Week of Manufacture YY: Year of Manufacture S2: ASCII Serial Number
Max Image Size H: 40 cm Max Image Size V: 30 cm DPMS Stand By: YES DPMS Suspend: YES DPMS Active Off: YES GTF Support: YES Standard Default Color Space: NO Preferred Timing Mode: YES Display Type: RGB Color	Standard Timing #5: Horizontal Active Pixels: 1280 Aspect Ratio: 5:4 (1024 active lines) Refresh Rate: 85 Hz	EDID EDITOR V1.45 (010514) Copyright (C) Mitsubishi Electric 1995-2000
Color: Gamma: 2.20 Red x: 0.627 Red y: 0.341 Green x: 0.292 Green y: 0.605 Blue x: 0.149 Blue y: 0.072 White x: 0.283 White y: 0.297	Standard Timing #6: Horizontal Active Pixels: 1600 Aspect Ratio: 4:3 (1200 active lines) Refresh Rate: 75 Hz	
	Standard Timing #7: Horizontal Active Pixels: 1792 Aspect Ratio: 4:3 (1344 active lines) Refresh Rate: 75 Hz	
	Standard Timing #8: Horizontal Active Pixels: 1920 Aspect Ratio: 4:3 (1440 active lines) Refresh Rate: 75 Hz	

2.6.2 Self-diagnosis shipment setting

The shipment settings for self-diagnosis data area (region) are given below.

ADR	Shipment Setting (H)	LABEL NAME
0x08C to 0x08F	0x00	Heater operating time
0x0B6 to 0x0B9	0x00	Operating time
0x0C0	0x00	High voltage error rate
0x0C1	0x00	High voltage suspension rate
0x0C2	0x00	Short circuit rate
0x0C3	0x00	High voltage data error rate
0x0C4	0x00	Deflection suspension rate
0x0C5	0x00	Heater error rate
0x0C6	0x00	ABL error

2.7 Default inspection

2.7.1 Default setting of switches

Confirm that the following switch is set as follows.

- (1) Power switch: OFF

2.7.2 Default setting of OSM

Confirm that each OSM setting is as shown in OSM display (section 2.3.3) table (user mode/factory mode).

If the setting class is an item for each timing, carry out for each adjustment timing.

- * Only CONTRAST will be set to MAX (100%) when RESET button is pressed in the normal mode.

2.7.3 Checking the labels

Confirm that the "SERVICEMAN WARNING", "rating label", "manufacturing date stamp", "SERIAL NO. label", etc., are attached to the specified position, and have been checked.

2.7.4 Packaging

- (1) There must be no remarkable contamination, tearing or scratches, etc.
- (2) The model name must be accurately displayed.
- (3) The SERIAL NO. must be attached. (Must be the same No. as the set.)
- (4) The package must be accurately sealed.

2.8 Degaussing with handy-demagnetizer

2.8.1 General precautions

- (1) Carry this procedure out with the monitor power ON.
- (2) When degaussing with handy-demagnetizer, the demagnetizer power must be turned ON and OFF at a position at least 1m away from CRT tube.
- (3) Use a bar type demagnetizer instead of a ring type.
Carefully and slowly (1m/3 sec.) demagnetize the CRT tube and bezel side surface.
When separating the degaussing coil at the end, separate as slow as possible with the following procedure.
If separated quickly, stripes could remain at the picture corners.


2.8.2 How to hold and use the handy-demagnetizer

- (1) Approach the demagnetizer as carefully and slowly (approx. 1m/3 sec.) as possible, and move around the bezel side periphery two to three times.
- (2) Next, gradually (approx. 1m/3 sec.) move to the CRT tube side, and move around the CRT tube four to five times with the following procedure.
- (3) Finally, leave the CRT tube as slowly (approx. 1m/3 sec.) as possible, and turn the handy-demagnetizer unit switch OFF at a position 1 to 1.5m away.

(NOTE): The monitor should be degaussed as whichever following conditions.

- (1) Degauss by handy demagnetizer in off condition.
- (2) Degauss by handy demagnetizer in power management condition.
- (3) Degauss by handy demagnetizer with monitor set degauss operation.


Looking from side of set



<Holding the handy - demagnetizer>

Face the handy - demagnetizer so that the longitudinal direction is vertical in respect to the CRT.

Do not hold the handy - demagnetizer so that the longitudinal direction is parallel in respect to the CRT.




2.9 Caution

Do not input the user timing before factory adjustments.

(The automatic tracking of the FOCUS could be adversely affected.)

2.10 Timing chart



※ Refer to after the next page for the preset timing details.

2.11 Adjustment timing

[illegible]

NO	Fh (kHz)	Clock (MHz)	Th (μSEC) (dot)	Tsh (μSEC) (dot)	Tfh (μSEC) (dot)	Tbh (μSEC) (dot)	Tdh (μSEC) (dot)	Utili- zation	H re- trace s+f+b	Fv (Hz)	Tv (mSEC) (line)	Tsv (mSEC) (line)	Ttv (mSEC) (line)	Tbv (mSEC) (line)	Tdv (mSEC) (line)	V re- trace	Hs	Vs	VIDEO level (V)	set up level (V)	Serra- tion	Remarks
1	31.470	28.322	31.777 (800)	3.813 (96)	0.635 (16)	1.907 (48)	25.422 (640)	80.00	6.356	70.090	14.268 (449)	0.064 (2)	0.381 (12)	1.112 (35)	12.711 (400)	1.557	-	+	0.7	-	-	ODS(720*400)70Hz
2	31.469	25.175	31.778 (800)	3.813 (96)	0.636 (16)	1.907 (48)	25.422 (640)	80.00	6.356	59.940	16.683 (525)	0.064 (2)	0.318 (10)	1.048 (33)	15.253 (480)	1.112	-	-	0.7	-	○1	VGA(640*480)60Hz
3	31.500	31.500	28.667 (840)	2.032 (64)	0.508 (16)	3.810 (120)	20.317 (640)	76.19	6.350	75.000	13.333 (500)	0.080 (3)	0.027 (1)	0.427 (16)	12.800 (480)	0.506	-	-	0.7	-	-	VESA(640*480)75Hz
4	43.269	36.000	23.111 (800)	1.556 (56)	1.556 (56)	2.222 (60)	17.778 (640)	76.92	5.334	85.008	11.764 (509)	0.069 (3)	0.023 (1)	0.579 (25)	11.093 (480)	0.647	-	-	0.7	-	-	VESA(640*480)85Hz
5	46.875	49.500	21.333 (800)	1.616 (80)	0.323 (16)	3.232 (160)	16.162 (800)	75.76	5.171	75.000	13.333 (625)	0.064 (3)	0.021 (1)	0.448 (21)	12.800 (600)	0.512	+	+	0.7	-	○2	VESA(800*600)75Hz
6	53.674	56.250	18.631 (1048)	1.138 (64)	0.569 (32)	2.702 (152)	14.222 (800)	76.34	4.409	85.061	11.756 (631)	0.056 (3)	0.019 (1)	0.503 (27)	11.179 (600)	0.559	+	+	0.7	-	-	VESA(800*600)85Hz
7	60.023	78.750	16.660 (1312)	1.219 (96)	0.203 (16)	2.235 (176)	13.003 (1024)	78.05	3.657	75.029	13.328 (800)	0.050 (3)	0.017 (1)	0.466 (28)	12.795 (768)	0.516	+	+	0.7	-	○3	VESA(1024*768)75Hz
8	68.677	94.500	14.561 (1376)	1.016 (96)	0.508 (48)	2.201 (208)	10.836 (1024)	74.42	3.725	84.997	11.765 (808)	0.044 (3)	0.015 (1)	0.524 (36)	11.183 (768)	0.568	+	+	0.7	-	○4	VESA(1024*768)85Hz
9	79.976	135.000	12.504 (1688)	1.067 (144)	0.119 (16)	1.837 (248)	9.481 (1280)	75.82	3.023	75.025	13.329 (1066)	0.038 (3)	0.013 (1)	0.475 (38)	12.804 (1024)	0.513	+	+	0.7	-	○5	VESA(1280*1024)75Hz
10	91.146	157.500	10.971 (1728)	1.016 (160)	0.406 (64)	1.422 (224)	8.127 (1280)	74.08	2.844	85.027	11.761 (1072)	0.033 (3)	0.011 (1)	0.483 (44)	11.235 (1024)	0.516	+	+	0.7	-	○6	VESA(1280*1024)85Hz
11	93.750	202.500	10.667 (2160)	0.948 (192)	0.316 (64)	1.501 (304)	7.901 (1600)	74.07	2.765	75.000	13.333 (1250)	0.032 (3)	0.011 (1)	0.491 (46)	12.800 (1200)	0.523	+	+	0.7	-	○7	VESA(1600*1200)75Hz
12	106.250	229.500	9.412 (2160)	0.837 (192)	0.279 (64)	1.325 (304)	6.972 (1600)	74.08	2.441	85.000	11.765 (1250)	0.028 (3)	0.009 (1)	0.433 (46)	11.294 (1200)	0.461	+	+	0.7	-	○8	VESA(1600*1200)85Hz
13	106.270	261.00	9.41 (2456)	0.828 (216)	0.278 (64)	1.349 (352)	6.866 (1792)	72.96	2.545	74.997	13.334 (1417)	0.028 (3)	0.009 (1)	0.649 (69)	12.647 (1344)	0.677	-	+	0.7	-	-	VESA(1792*1344)75Hz
14	112.500	288.000	8.889 (2560)	0.778 (224)	0.444 (128)	1.222 (352)	6.444 (1856)	72.49	2.444	75.000	13.333 (1500)	0.027 (3)	0.009 (1)	0.924 (104)	12.373 (1392)	0.951	-	+	0.7	-	-	ESA(1856*1392)75Hz
15	112.500	297.000	8.889 (1640)	0.754 (224)	0.485 (144)	1.185 (352)	6.4654 (1920)	72.73	2.424	75.000	13.333 (1500)	0.027 (3)	0.009 (1)	0.498 (56)	12.800 (1440)	0.525	-	+	0.7	-	○9	VESA(1920*1440)75Hz
16	35.00	30.240	28.571 (864)	2.116 (64)	2.116 (64)	3.175 (96)	21.164 (640)	74.08	7.407	66.67	15.000 (525)	0.086 (3)	0.086 (3)	1.114 (39)	13.714 (480)	1.2	-	-	0.7	-	-	APPLE13(640*480)
17	49.710	57.270	20.115 (1152)	1.118 (64)	0.559 (32)	3.910 (224)	14.528 (1856)	72.22	5.587	74.530	13.417 (667)	0.060 (3)	0.020 (1)	0.785 (39)	12.552 (624)	0.845	-	-	0.7	-	-	APPLE16(832*624)
18	60.240	80.000	16.600 (1328)	1.200 (96)	0.400 (32)	2.200 (176)	12.800 (1024)	77.11	3.800	74.930	13.346 (804)	0.050 (3)	0.049 (3)	0.498 (30)	12.749 (768)	0.548	-	-	0.7	-	-	APPLE19(1024*768)
19	68.680	100.000	14.560 (1456)	1.280 (128)	0.320 (32)	1.440 (144)	11.520 (1152)	79.12	3.040	75.060	13.322 (915)	0.044 (3)	0.043 (3)	0.568 (39)	12.667 (870)	0.612	-	-	0.7	-	-	APPLE21(1152*870)
20	100.200	219.638	9.980 (2192)	0.801 (176)	0.546 (120)	1.348 (296)	7.285 (1600)	73.00	2.695	75.000	13.333 (1336)	0.03 (3)	0.01 (1)	0.519 (52)	12.774 (1280)	0.549	-	-	0.7	-	-	GTF(1600*1280)75Hz
21	107.200	234.982	9.328 (2192)	0.749 (176)	0.511 (120)	1.260 (296)	6.809 (1600)	73.00	2.520	80.000	12.5 (1340)	0.028 (3)	0.009 (1)	0.522 (56)	11.94 (1280)	0.55	-	-	0.7	-	-	GTF(1600*1280)80Hz
22	114.240	252.242	8.754 (2208)	0.698 (176)	0.507 (128)	1.205 (304)	6.343 (1600)	72.46	2.410	85.000	11.765 (1344)	0.026 (3)	0.009 (1)	0.525 (60)	11.204 (1280)	0.551	-	-	0.7	-	-	GTF(1600*1280)85Hz
23	105.675	261.229	9.463 (2472)	0.766 (200)	0.521 (136)	1.286 (336)	6.891 (1800)	72.82	2.573	75.000	13.333 (1409)	0.028 (3)	0.009 (1)	0.52 (55)	12.775 (1350)	0.548	-	-	0.7	-	-	GTF(1800*1350)75Hz
24	113.040	279.435	8.846 (2472)	0.716 (200)	0.487 (136)	1.202 (336)	6.442 (1800)	72.82	2.405	80.000	12.5 (1413)	0.027 (3)	0.009 (1)	0.522 (59)	11.943 (1350)	0.549	-	-	0.7	-	-	GTF(1800*1350)80Hz
25	120.455	299.667	8.303 (2488)	0.667 (200)	0.481 (144)	1.148 (344)	6.007 (1800)	72.35	2.296	85.000	11.765 (1417)	0.025 (3)	0.008 (1)	0.523 (63)	11.208 (1350)	0.548	-	-	0.7	-	-	GTF(1800*1350)85Hz
26	112.725	278.656	8.871 (2472)	0.718 (200)	0.488 (136)	1.206 (336)	6.460 (1800)	72.82	2.412	75.000	13.333 (1503)	0.027 (3)	0.009 (1)	0.523 (63)	12.774 (1440)	0.55	-	-	0.7	-	-	GTF(1800*1440)75Hz
27	120.560	299.953	8.295 (2488)	0.667 (200)	0.480 (144)	1.147 (344)	6.001 (1800)	72.34	2.294	80.000	2.5 (1507)	0.025 (3)	0.008 (1)	0.523 (63)	11.944 (1440)	0.548	-	-	0.7	-	-	GTF(1800*1440)80Hz
28	80.530	105.656	12.418 (1312)	1.060 (112)	0.303 (32)	1.363 (144)	9.692 (1024)	78.05	2.726	100.000	10.0 (805)	0.037 (3)	0.012 (1)	0.410 (33)	9.537 (768)	0.463	-	-	0.7	-	-	ELSA(1024*768)100Hz
29	137.020	388.041	7.298 (2832)	0.577 (224)	0.433 (168)	1.010 (392)	5.278 (2048)	72.18	2.020	85.000	11.765 (1612)	0.022 (3)	0.007 (1)	0.525 (72)	11.210 (1536)	0.555	-	-	0.7	-	-	GTF(2048*1536)85Hz

Mark O: Factory adjustment. The number after the mark is the preset number.
Mark □: Factory adjustment [Though they are presets, it does not apply to the specification of the picture distortion. The sync. signals are reference to the above. (It is possible to reset with the above timings.)]
Mark ▲: Initial data [So long as initial data, the sync. signals are reference to Hs: + and Vs: -. However, it is necessary to adjust only the NARROW/WIDE, LEFT/RIGHT, DBF-H-AMP and DBF-H-PHASE in factory mode.
The numbers after the marks are the number of preset.

3. TROUBLE SHOOTING


This chapter for troubleshooting is useful if any normal conditions cannot be secured even after the confirmation of “Troubleshooting” presented in the User’s Manual and the completion of “Chapter 2. Adjustment procedures” presented in this Service Manual.


The equipment units related to the possible cause of “Picture bounces or a wavy patterns is present in the picture” described in “Troubleshooting” presented in the User’s Manual include the electrical equipment such as portable telephones, etc., which may generate electromagnetic waves. Therefore, troubleshooting actions should be taken after turning off the portable telephones, etc., and such electrical equipment that may generate electromagnetic waves, or in a place distant from such equipment.

Contents

	Page
3.1 No Raster Generated	3-2
3.2 Abnormal Picture	3-4
3.2.1 Raster Brightness Failure	3-4
3.2.2 Image Color Failure or Contrast Failure	3-4
3.2.3 Sync Failure	3-5
3.2.3.1 Horizontal Sync Unstable	3-5
3.2.3.2 Vertical Sync Unstable	3-6
3.2.4 Screen Size and Screen Position Failure	3-7
3.2.4.1 Horizontal Size Failure	3-7
3.2.4.2 Horizontal Position Failure	3-8
3.2.4.3 Vertical Size and Position Failure	3-8
3.2.5 Linearity Failure	3-9
3.2.5.1 Horizontal Linearity Failure	3-9
3.2.5.2 Vertical Linearity Failure	3-10
3.2.6 Distortion Compensation Circuit Failure	3-11
3.2.6.1 IN/OUT (pincushion), ALIGN (trapezoidal) and TOP/BOTTOM (corner correction) Failure ---	3-11
3.2.6.2 LEFT/RIGHT (pincushion balance), TILT (parallelogram), and TOP BALANCE/BOTTOM BALANCE (corner correction) Failure	3-11
3.2.6.3 ROTATE (raster rotation) Failure	3-11
3.2.7 Focus Failure	3-12
3.3 Functional Errors	3-14
3.3.1 OSM Failure	3-14
3.3.2 Power Management Functional Operation Error	3-15
3.3.3 Plug & Play (DDC2B) Operation Error	3-16
3.3.4 Degaussing Functional Operation Error	3-16
3.3.5 Key Operation Error	3-17
3.4 Circuit Errors	3-18
3.4.1 Power Circuit Failure	3-18
3.4.2 Horizontal Oscillation / Deflection Circuit Failure	3-19
3.4.3 Vertical Oscillation / Deflection Circuit Failure	3-20
3.4.4 HV Circuit Failure	3-21
3.4.5 Video Circuit Failure	3-22
3.4.6 Static Convergence Compensation Circuit Failure	3-24
3.4.7 Corner Purity Compensation Circuit Failure	3-25
3.4.8 MPU Operation Error	3-26
3.4.9 Self-Diagnostic Functions	3-27


3.1 No Raster Generated






3.2 Abnormal Picture

3.2.1 Raster Brightness Failure




3.2.2. Image Color Failure or Contrast Failure




3.2.3 Sync Failure

3.2.3.1 Horizontal Sync Unstable




3.2.3.2 Vertical Sync Unstable




3.2.4 Screen Size and Screen Position Failure

3.2.4.1 Horizontal Size Failure




3.2.4.2 Horizontal Position Failure


(1) Video



(2) Horizontal raster centering (VR5A1) failure




3.2.4.3 Vertical Size and Position Failure




3.2.5 Linearity Failure

3.2.5.1 Horizontal Linearity Failure




3.2.5.2 Vertical Linearity Failure




3.2.6 Distortion Compensation Circuit Failure


3.2.6.1 IN/OUT (pincushion), ALIGN (trapezoidal) and TOP/BOTTOM (corner correction) Failure




3.2.6.2 LEFT/RIGHT (pincushion balance), TILT (parallelogram), and TOP BALANCE/BOTTOM BALANCE (corner correction) Failure




3.2.6.3 ROTATE (raster rotation) Failure



3.2.7 Focus Failure






3.3 Functional Errors


3.3.1 OSM Failure

Note: See “3.2 Abnormal picture” if a screen is not available even though a video signal input is entered.




3.3.2 Power Management Functional Operation Error


First of all, disconnect the signal cables from the signal source.
(If a signal input is removed, the high voltage (HV) falls and the LED turns to ORANGE.)




3.3.3 Plug & Play (DDC2B) Operation Error



3.3.4 Degaussing Functional Operation Error




3.3.5 Key Operation Error




3.4. Circuit Errors

3.4.1 Power Circuit Failure




3.4.2 Horizontal Oscillation /Deflection Circuit Failure

(Check “3.1 No Raster Generated” and “3.2.3.1 Horizontal Sync Unstable” before this item)




3.4.3 Vertical Oscillation / Deflection Circuit Failure

(Check “3.2.3.2 Vertical Sync Unstable” before checking of this item)




3.4.4 High Voltage (HV)Circuit Failure


(Check “3.1 No Raster Generated” before this item)




3.4.5 Video Circuit Failure

(Check “3.2.2 Image Color Failure or Contrast Failure” before this item)







3.4.6 Static Convergence Compensation Circuit Failure



3.4.7 Corner Purity Compensation Circuit Failure



3.4.8 MPU Operation Error



3.4.9 Self-Diagnostic Functions


This model is provided with the functions that a circuit error is detected by the MPU and this error is indicated by the LED blink frequency.

When the protector is in operation, the LED is made to blink as shown below in order to indicate the factor of protector operation.

LED Blinking Patterns for Each Protector Operation (List of Protector Indicators)

Protector condition	LED condition	
	Short (0.5s) lighting frequency	Long (2s) lighting frequency
HV data error	3	1
HV latch (fall)	2	1
Beam protector	5	1
Secondary power short	7	
X-lay protector	1	1

(1) How to count the LED lighting frequency [Example: HV data error (3 times)]




(2) Diagnostic mode and error circuit

- 3 times --- HV data error ----- Power OFF/ON and data recovery
(HV adjustment value is destroyed or IC104 is failure).
- 2 times --- HV latch (falls) ----- Check Item 3.4.4
- 5 times --- Beam protector ----- Check Item 3.4.4
- 6 times --- Secondary power short ----- Check Item 3.4.1


4. Wave form

- 1. POWER**
- 2. CONTROL (MAIN)**
- 3. DEFL (MAIN)**
- 4. DEFL-SUB & COIL-DRIVE (MAIN)**
- 5. VIDEO**











FE211SB/RDF223H


SCHEMATIC DIAGRAM
POWER



IC102(22) KEY1/(23) KEY2のSW動作が当て
 KEY1 - SW103(3.7V) KEY2 - SW102(3.7V)
 - SW103(1.3V) - SW105(1.7V)
 - SW104(2.6V) - SW107(0V)
 - SW106(0V)



FE211SB/RDF223H
 SCHEMATIC DIAGRAM
 MAIN (CONTROL)



FE2111SB/RDF223H

SCHEMATIC DIAGRAM MAIN (DEFL-SUB&COIL-DRIVE)

