

7. Electrical Parts List

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
P001	AK92-01374A	ASSY PCB;DVD-R155/XAX,JACK I/O	1	SA	
AC16	2203-000315	C-CER,CHIP;0.12nF,5%,50V,COG,1	1	SA	
AC17	2203-000315	C-CER,CHIP;0.12nF,5%,50V,COG,1	1	SA	
AC405	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
AC406	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
AC407	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,T	1	SA	
AC408	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,T	1	SA	
AC409	2203-000315	C-CER,CHIP;0.12nF,5%,50V,COG,1	1	SA	
AC410	2203-000315	C-CER,CHIP;0.12nF,5%,50V,COG,1	1	SA	
AC413	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
ACC2	2203-000315	C-CER,CHIP;0.12nF,5%,50V,COG,1	1	SA	
ACC3	2203-000315	C-CER,CHIP;0.12nF,5%,50V,COG,1	1	SA	
AD1	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,	1	SA	
AD2	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,	1	SA	
AD3	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,	1	SA	
AE404	2401-003107	C-AL;47uF,20%,16V,GP,TP;5x7,5	1	SA	
AE405	2401-003107	C-AL;47uF,20%,16V,GP,TP;5x7,5	1	SA	
AE412	2401-002165	C-AL;100uF,20%,16V,GP,TP;6.3x7	1	SA	
AE42	2401-000922	C-AL;22uF,20%,16V,GP,TP;5x5,5	1	SA	
AE46	2401-000922	C-AL;22uF,20%,16V,GP,TP;5x5,5	1	SA	
AIC4	1201-000163	IC-OP AMP;4560,SOP8P;173MIL,D	1	SA	
AIM1	0203-001601	TAPE-PAPER;#FB-300,0.16,6,2000	1	SNA	
AIM2	0203-001599	TAPE-KRAFT;#53110,0.16,2000M,	1	SNA	
AL1	3811-001868	WIRE-NO SHEATH CU;SnCuFe,-,52m	1	SNA	
AQ1	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,	1	SA	
AQ3	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,	1	SA	
AQ4	0504-000128	TR-DIGITAL;-NPN,200MMW,22K/22K	1	SA	
AQ5	0504-000156	TR-DIGITAL;KSR2103,PNP,200MMW,2	1	SA	
AQ51	0504-000128	TR-DIGITAL;-NPN,200MMW,22K/22K	1	SA	
AQ52	0504-000156	TR-DIGITAL;KSR2103,PNP,200MMW,2	1	SA	
AQ6	0504-000128	TR-DIGITAL;-NPN,200MMW,22K/22K	1	SA	
AQ7	0504-000156	TR-DIGITAL;KSR2103,PNP,200MMW,2	1	SA	
AR105	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,	1	SA	
AR106	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,	1	SA	
AR107	2007-000129	R-CHIP;27Kohm,5%,1/10W,TP,1608	1	SA	
AR108	2007-000129	R-CHIP;27Kohm,5%,1/10W,TP,1608	1	SA	
AR26	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1	1	SA	
AR4	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA	
AR40	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1	1	SA	
AR403	2007-001010	R-CHIP;51Kohm,5%,1/10W,TP,1608	1	SA	
AR404	2007-001010	R-CHIP;51Kohm,5%,1/10W,TP,1608	1	SA	
AR407	2007-001010	R-CHIP;51Kohm,5%,1/10W,TP,1608	1	SA	
AR408	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,	1	SA	
AR409	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	SA	
AR410	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	SA	
AR411	3811-001868	WIRE-NO SHEATH CU;SnCuFe,-,52m	1	SNA	
AR412	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA	
AR413	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	SA	
AR414	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	SA	
AR415	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	SA	
AR420	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,160	1	SA	
AR421	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA	
AR460	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,160	1	SA	
AR461	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,	1	SA	

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
AR471	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
AR472	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,	1	SA	
AR473	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	SA	
AR474	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	SA	
AR475	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	SA	
AR476	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA	
AR477	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA	
AR5	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA	
AR725	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA	
AR734	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA	
AR735	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	SA	
AVJ1	3722-002449	JACK-PIN;6P+VHS,Ni/Sn,RD-BU-GN	1	SA	
AVJ2	3722-002450	JACK-PIN;6P+VHS,Ni/Sn,RD-WH-YL	1	SA	
AVJ5	3707-001070	CONNECTOR-OPTICAL;PLUG,GP1FA55	1	SA	
BD05	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
BD06	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
BD07	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
BD08	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
BD21	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
BD22	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
BD23	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
BD24	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
C4M17A	2203-000323	C-CER,CHIP;12nF,10%,50V,X7R,TP	1	SA	
C4M18A	2203-000357	C-CER,CHIP;0.15nF,5%,50V,COG,1	1	SA	
C4M19A	2203-000681	C-CER,CHIP;0.027nF,5%,50V,COG,	1	SA	
C603	2203-005065	C-CER,CHIP;100nF,+80-20%,10V,	1	SA	
C616	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
C617	2401-003107	C-AL;47uF,20%,16V,GP,TP;5x7,5	1	SA	
C618	2203-000426	C-CER,CHIP;0.018nF,5%,50V,COG,	1	SA	
C619	2203-000426	C-CER,CHIP;0.018nF,5%,50V,COG,	1	SA	
C620	2203-000626	C-CER,CHIP;0.022nF,5%,50V,COG,	1	SA	
C621	2203-000626	C-CER,CHIP;0.022nF,5%,50V,COG,	1	SA	
C622	2203-005065	C-CER,CHIP;100nF,+80-20%,10V,	1	SA	
C623	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,16	1	SA	
C626	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
C627	2203-001697	C-CER,CHIP;0.082nF,5%,50V,NPO,	1	SA	
C628	2401-002069	C-AL;33uF,20%,16V,GP,TP;6.3x5,	1	SA	
C629	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,16	1	SA	
C630	2401-002165	C-AL;100uF,20%,16V,GP,TP;6.3x7	1	SA	
C631	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,16	1	SA	
C635	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,16	1	SA	
C636	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
C637	2401-002165	C-AL;100uF,20%,16V,GP,TP;6.3x7	1	SA	
C647	2203-000681	C-CER,CHIP;0.027nF,5%,50V,COG,	1	SA	
C651	2202-000216	C-CERAMIC,MLC-AXIAL;0.027NF,5%	1	SA	
C652	2203-000681	C-CER,CHIP;0.027nF,5%,50V,COG,	1	SA	
C658	2203-001683	C-CER,CHIP;0.068nF,5%,50V,NPO,	1	SA	
C701	2401-000118	C-AL;1000uF,20%,10V,GP,TP;10x1	1	SA	
C702	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,16	1	SA	
C703	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,16	1	SA	
C704	2401-000240	C-AL;100uF,20%,10V,GP,TP;5x11,	1	SA	
C707	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,16	1	SA	
C708	2401-000118	C-AL;1000uF,20%,10V,GP,TP;10x1	1	SA	

Electrical Parts List

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
C801	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,16	1	SA	
C802	2401-001915	C-AL;1uF,20%,50V,GP,TP,3x5,5	1	SA	
C803	2401-004136	C-AL;100uF,±20%,16V,WT,TP,8X5	1	SA	
C804	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
C805	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7	1	SA	
C806	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
C807	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	1	SA	
C808	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	1	SA	
C809	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	1	SA	
C810	2401-003645	C-AL;1uF,20%,50V,WT,TP,4X5MM,5	1	SA	
C811	2401-003645	C-AL;1uF,20%,50V,WT,TP,4X5MM,5	1	SA	
C812	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	1	SA	
C813	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	1	SA	
C814	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	1	SA	
C815	2401-003645	C-AL;1uF,20%,50V,WT,TP,4X5MM,5	1	SA	
C816	2401-003645	C-AL;1uF,20%,50V,WT,TP,4X5MM,5	1	SA	
C817	2401-003645	C-AL;1uF,20%,50V,WT,TP,4X5MM,5	1	SA	
C818	2401-003645	C-AL;1uF,20%,50V,WT,TP,4X5MM,5	1	SA	
C819	2401-003645	C-AL;1uF,20%,50V,WT,TP,4X5MM,5	1	SA	
C820	2401-003645	C-AL;1uF,20%,50V,WT,TP,4X5MM,5	1	SA	
C821	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5	1	SA	
C822	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5	1	SA	
C824	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5	1	SA	
C825	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5	1	SA	
CN3	3711-005563	HEADER-BOARD TO BOARD;BOX,30P	1	SA	
CN4	3711-006319	HEADER-BOARD TO BOARD;BOX,16P	1	SA	
CVL1	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
CVL2	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
CVL3	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
D702	0401-000005	DIODE-SWITCHING;1N4148,75V,150	1	SA	
D703	0401-000005	DIODE-SWITCHING;1N4148,75V,150	1	SA	
D704	0401-000005	DIODE-SWITCHING;1N4148,75V,150	1	SA	
D705	0401-000005	DIODE-SWITCHING;1N4148,75V,150	1	SA	
D719	0402-001533	DIODE-RECTIFIER;1N5408,1000V,3	1	SA	
D720	0402-000165	DIODE-RECTIFIER;1N5819,40V,1A,	1	SA	
DAR01	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
DOC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
DOC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
DOC5	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,	1	SA	
DOE1	2401-001915	C-AL;1uF,20%,50V,GP,TP,3x5,5	1	SA	
DOL2	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
DOL3	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	1	SA	
DOR1	2007-000040	R-CHIP;150ohm,1%,1/10W,TP,1608	1	SA	
DOR2	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA	
DOR3	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	SA	
DT701	AK07-00063A	LED DISPLAY;BCD-9051A,DVD-R155	1	SA	
FC10	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,16	1	SA	
FC12	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
FC1S01	3602-000103	FUSE-CLIP;-,-,10mohm	1	SNA	
FC1S02	3602-000103	FUSE-CLIP;-,-,10mohm	1	SNA	
FC0N1	3708-001802	CONNECTOR-FPC/FFC/PIC;10P;1.25	1	SA	
FC0N3	3708-001695	CONNECTOR-FPC/FFC/PIC;13P;1MM,	1	SA	
FD2	0402-000165	DIODE-RECTIFIER;1N5819,40V,1A,	1	SA	
FD3	0402-000165	DIODE-RECTIFIER;1N5819,40V,1A,	1	SA	
FD4	0401-000005	DIODE-SWITCHING;1N4148,75V,150	1	SA	
FD7	0402-000165	DIODE-RECTIFIER;1N5819,40V,1A,	1	SA	
FDJ1	0402-000165	DIODE-RECTIFIER;1N5819,40V,1A,	1	SA	

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
FDJ2	0402-000165	DIODE-RECTIFIER;1N5819,40V,1A,	1	SA	
FE4	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7	1	SA	
FE5	2401-001932	C-AL;2200uF,20%,10V,WT,TP,10X2	1	SA	
FIC5	AC14-12009W	IC-RESET;PST572K,TO-92,R59-176	1	SA	
FL1	3811-001868	WIRE-NO SHEATH CU;SnCuFe,-,52m	1	SNA	
FL2	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	1	SA	
FL3	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	1	SA	
FR24	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	SA	
FR25	2007-000503	R-CHIP;2.2ohm,5%,1/10W,TP,1608	1	SA	
IC601	AK09-00148A	IC-MICOM;MN101D10G-EF,DVD-R157	1	SNA	
IC603	1103-001134	IC-EEPROM;24C040,512x8,SOP,8P,	1	SA	
IC604	1204-002509	IC-SIGNAL PROCESSOR;CXA2207N,S	1	SA	
IC701	1003-001561	IC-LED DRIVER;PT6961,SOP,32P,3	1	SA	
IC801	1204-001763	IC-AUDIO PROCESSOR;LA73024V,SS	1	SA	
JPS07	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	1	SA	
KRMC1	0609-001225	MODULE REMOCOIN;VERTICAL,3.6mm,	1	SA	
L701	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	1	SA	
LB01	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	1	SA	
LB02	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	1	SA	
ME01	2401-003499	C-AL;330uF,20%,16V,LZ,TP,8x11	1	SA	
PACT1	2301-001792	C-FILM,LEAD;150nF,20%,275V,BK,	1	SA	
PACT2	2301-001792	C-FILM,LEAD;150nF,20%,275V,BK,	1	SA	
PADT1	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS	1	SA	
PADT2	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS	1	SA	
PADT3	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS	1	SA	
PADT4	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS	1	SA	
PAFT1	3601-000244	FUSE-CARTRIDGE;250V,2A,SLOW-BL	1	SC	
PALT2	AC29-00003A	FILTER LINE NOISE;-,-,20mH MIN,-	1	SA	
PART1	2002-000121	R-COMPOSITION;1Mohm,10%,1/2W,A	1	SA	
PAVV1	1405-000186	VARIATOR;470V,2500A,17.5x7.5mm	1	SA	
PAVV2	1405-001026	VARIATOR;470V,600A,9x7mm,TP	1	SA	
PAWT1	3711-000203	HEADER-BOARD TO CABLE;1WALL,2P	1	SA	
PBCU1	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,	1	SA	
PBCU2	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,	1	SA	
PBCU3	2201-000828	C-CERAMIC,DISC;3.3NF,20%,400V,	1	SA	
PBCU4	2201-000828	C-CERAMIC,DISC;3.3NF,20%,400V,	1	SA	
PBIZ1	0604-001028	PHOTO-COUPLER;TR,50-600%,250mW	1	SA	
PDCZ1	2301-001654	C-FILM,LEAD-PEF;1000nF,5%,100V	1	SA	
PCF1	2301-000129	C-FILM,LEAD-PEF;100nF,5%,50V,T	1	SA	
PCF21	2307-000104	C-FILM,LEAD-PCF;10nF,5%,50V,TP	1	SA	
PRD1	AC14-12006D	IC;KA431Z,TO-92,TAPING	1	SA	
PRF1	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,	1	SA	
PRF2	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP	1	SA	
PRF3	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1	1	SA	
PRF4	2001-000674	R-CARBON;360OHM,5%,1/8W,AA,TP,	1	SA	
PRF5	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,	1	SA	
PRF6	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,	1	SA	
PRZ1	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1	1	SA	
PL4	3811-001868	WIRE-NO SHEATH CU;SnCuFe,-,52m	1	SNA	
PLCZ1	2301-000129	C-FILM,LEAD-PEF;100nF,5%,50V,T	1	SA	
PLRU1	1404-001361	THERMISTOR-NTC;3ohm,4A,-,35mW/	1	SA	
PLRZ1	2003-000105	R-METAL OXIDE;0.33ohm,5%,2W,AD	1	SA	
PPCD1	2401-003480	C-AL;1000uF,20%,10V,LZ,TP,10X1	1	SA	
PPCD2	2401-001479	C-AL;470uF,20%,10V,GP,TP,6.3*1	1	SA	
PPCF1	2401-003480	C-AL;1000uF,20%,10V,LZ,TP,10X1	1	SA	
PPCF2	2401-003480	C-AL;1000uF,20%,10V,LZ,TP,10X1	1	SA	

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
PPCF3	2401-001479	C-AL;470uF,20%,10V,GP,TP;6.3*1	1	SA	
PPCF4	2401-001250	C-AL;4.7uF,20%,35V,GP,TP;4x5,5	1	SA	
PPCF7	2401-001479	C-AL;470uF,20%,10V,GP,TP;6.3*1	1	SA	
PPCF8	2401-002165	C-AL;100uF,20%,16V,GP,TP;6.3x7	1	SA	
PPC11	2401-001126	C-AL;330uF,20%,25V,WT,TP;10x12	1	SA	
PPC12	2401-001126	C-AL;330uF,20%,25V,WT,TP;10x12	1	SA	
PPC13	2401-003499	C-AL;330uF,20%,16V,LZ,TP;8x11	1	SA	
PPC01	2401-000385	C-AL;10uF,20%,100V,GP,TP;6.3x1	1	SC	
PPC02	2401-002300	C-AL;47•IF,20%,50V,GP,TP;6.3x1	1	SA	
PPD01	0404-001235	DIODE-SCHOTTKY;SHK65-45R,60V,3	1	SA	
PPD02	0401-000005	DIODE-SWITCHING;1N4148,75V,150	1	SA	
PPDF10	0404-001235	DIODE-SCHOTTKY;SHK65-45R,60V,3	1	SA	
PPDF2	0404-001235	DIODE-SCHOTTKY;SHK65-45R,60V,3	1	SA	
PPDF3	0402-001533	DIODE-RECTIFIER;1N5408,1000V,3	1	SA	
PPD11	0402-001624	DIODE-RECTIFIER;SF26,400V,2A,D	1	SA	
PPD01	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,	1	SA	
PPD11	1203-003216	IC-POS.FIXED REG.;69133,T0-22	1	SA	
PPIF2	1203-001589	IC-POS.FIXED REG.;278R05,T0-2	1	SA	
PP11	1203-002183	IC-SWITCH VOL. REG.;278R12,T0-	1	SA	
PPLD1	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q8	1	SA	
PPLF1	AH27-00039A	COIL CHOKE;DR CHOKE(8*6),DVD-R	1	SA	
PPL11	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q8	1	SA	
PPR01	2003-000148	R-METAL OXIDE;100ohm,5%,2W,AE	1	SC	
PPRF2	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1	1	SA	
PPRF4	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
PPRF6	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
PPR01	2001-000062	R-CARBON;470OHM,5%,1/4W,AA,TP,	1	SA	
PPZ01	0403-000390	DIODE-ZENER;UZP33B,31.4-34.6V,	1	SA	
PQ1Z1	1203-003883	IC-PWM CONTROLLER;3B2065P-2,T0	1	SA	
PQ1Z1A	AH62-30122A	HEAT SINK-POWER;1,AL,VO,T1.3,A	1	SNA	
PQTZ1	AC26-00014K	TRANS SWITCHING-RAM RECORDER;E	1	SA	
PRCU1	2401-003842	C-AL;100uF,20%,450V,WT,BK,25.4	1	SA	
PSCX1	2305-001029	C-FILM,LEAD-PEF;10nF,10%,630V,	1	SA	
PSCZ2	2201-000129	C-CERAMIC,DISC;0.1nF,10%,1000V	1	SA	
PSDZ1	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,	1	SA	
PSRZ1	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,	1	SA	
PSR22	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,	1	SA	
PVCL1	2401-002608	C-AL;33uF,20%,35V,GP,TP;5x11,5	1	SA	
PVDL1	0402-001195	DIODE-RECTIFIER;FT14,400V,1A,D	1	SA	
PVRL4	2001-000793	R-CARBON;470HM,5%,1/8W,AA,TP,1	1	SA	
PVZL1	0403-000713	DIODE-ZENER;MTZJ20B,18.63-17.7	1	SA	
PWR09	2007-000119	R-CHIP;560ohm,5%,1/10W,TP;1608	1	SA	
PWR10	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
PZWZ1	3711-004379	HEADER-BOARD TO CABLE;BOX,4P,1	1	SA	
Q4M01	0501-000398	TR-SMALL SIGNAL;KSC945-Y,NPN,2	1	SA	
Q4M02	0501-000398	TR-SMALL SIGNAL;KSC945-Y,NPN,2	1	SA	
R4M06	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP;1608	1	SA	
R4M07	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP;160	1	SA	
R4M08	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP;160	1	SA	
R4M09	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP;160	1	SA	
R4M10	2007-000965	R-CHIP;5.1Kohm,5%,1/10W,TP;160	1	SA	
R4M20	2007-000070	R-CHIP;0ohm,5%,1/10W,TP;1608	1	SA	
R611	2007-000074	R-CHIP;100ohm,5%,1/10W,TP;1608	1	SA	
R621	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,	1	SA	
R622	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,	1	SA	
R623	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP;160	1	SA	
R624	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP;160	1	SA	

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
R633	2007-000106	R-CHIP;220Kohm,5%,1/10W,TP;160	1	SA	
R638	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP;160	1	SA	
R639	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP;160	1	SA	
R652	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP;1608	1	SA	
R653	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R656	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP;1608	1	SA	
R666	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,	1	SA	
R667	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,	1	SA	
R668	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1	1	SA	
R670	2007-000074	R-CHIP;100ohm,5%,1/10W,TP;1608	1	SA	
R673	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R674	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R676	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R677	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1	1	SA	
R678	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,	1	SA	
R680	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP	1	SA	
R6A01	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP;1608	1	SA	
R6A02	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP;1608	1	SA	
R6A04	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R6A05	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R6A10	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP	1	SA	
R701	2007-001010	R-CHIP;51Kohm,5%,1/10W,TP;1608	1	SA	
R702	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R703	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R704	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R705	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R706	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R707	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R708	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R711	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP;1608	1	SA	
R7K1	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP;1608	1	SA	
R7K2	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP;1608	1	SA	
R7K3	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP;1608	1	SA	
R801	2007-001164	R-CHIP;75ohm,1%,1/10W,TP;1608	1	SA	
R802	2007-001164	R-CHIP;75ohm,1%,1/10W,TP;1608	1	SA	
R803	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1	1	SA	
R804	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1	1	SA	
R805	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,	1	SA	
R806	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,	1	SA	
R807	2007-000083	R-CHIP;3Kohm,5%,1/10W,TP;1608	1	SA	
R808	2007-000083	R-CHIP;3Kohm,5%,1/10W,TP;1608	1	SA	
R809	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP;160	1	SA	
R810	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP;160	1	SA	
R811	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R812	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP;1608	1	SA	
R813	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1	1	SA	
R814	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1	1	SA	
RA606	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,	1	SA	
SVL2	3301-001419	BEAD-SMD;220ohm,1608,TP;133ohm	1	SA	
SVLA	3301-001419	BEAD-SMD;220ohm,1608,TP;133ohm	1	SA	
SVR2	3301-001419	BEAD-SMD;220ohm,1608,TP;133ohm	1	SA	
SW701	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6	1	SA	
SW702	3404-001261	SWITCH-TACT;15V DC,20mA,100gf,	1	SA	
TC1	2401-004014	C-AL;4.7•IF,20%,16V,NP,TP;4x5,	1	SA	
TC10	2401-001915	C-AL;1uF,20%,50V,GP,TP;3x5,5	1	SA	
TC11	2401-004014	C-AL;4.7•IF,20%,16V,NP,TP;4x5,	1	SA	
TC12	2202-000253	C-CERAMIC,MLC-AXIAL;4.7nf,20%,	1	SA	

Electrical Parts List

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
TC13	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	1	SA	
TC14	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7	1	SA	
TC15	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	1	SA	
TC16	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	1	SA	
TC17	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y	1	SA	
TC19	2203-001662	C-CER,CHIP;5.6nF,10%,50V,X7R,1	1	SA	
TC2	2203-000531	C-CER,CHIP;2.7nF,10%,50V,X7R,1	1	SA	
TC20	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
TC21	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,16	1	SA	
TC22	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
TC3	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,16	1	SA	
TC4	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2	1	SA	
TC5	2401-001020	C-AL;3.3uF,20%,50V,GP,TP,4x7,5	1	SA	
TC6	2401-004014	C-AL;4.7uF,20%,16V,NP,TP,4x5,	1	SA	
TC74	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
TC9	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	1	SA	
TE12	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	1	SA	
TE8	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7	1	SA	
TL5	3811-001868	WIRE-NO SHEATH CU;SnCuFe,-,52m	1	SNA	
TM1	AK40-00019A	TM BLOCK;VRA05ASE,NTSC,181CH,-	1	SA	
TR1	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,160	1	SA	
TR10	2007-000121	R-CHIP;820ohm,5%,1/10W,TP,1608	1	SA	
TR2	2007-000842	R-CHIP;3Kohm,1%,1/10W,TP,1608	1	SA	
TR3	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,160	1	SA	
TR4	2007-001125	R-CHIP;68Kohm,1%,1/10W,TP,1608	1	SA	
TR5	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	1	SA	
TR6	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,160	1	SA	
TR7	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	SA	
TR8	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	SA	
TR9	2007-000121	R-CHIP;820ohm,5%,1/10W,TP,1608	1	SA	
VC10	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,160	1	SA	
VC17	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
VC6	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,1	1	SA	
VC7	2202-000797	C-CERAMIC,MLC-AXIAL;10nF,30%,1	1	SA	
VC8	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-2	1	SA	
VC9	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-2	1	SA	
VDR1	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	SA	
VDR2	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	SA	
VDR3	2007-001131	R-CHIP;68ohm,1%,1/10W,TP,1608	1	SA	
VDR4	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	SA	
VDR5	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	SA	
VDR6	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	SA	
VDR7	2007-000879	R-CHIP;4.7ohm,1%,1/10W,TP,1608	1	SA	
VE1	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7	1	SA	
VE10	2401-001479	C-AL;470uF,20%,10V,GP,TP,6.3*1	1	SA	
VE2	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	1	SA	
VE4	2401-001479	C-AL;470uF,20%,10V,GP,TP,6.3*1	1	SA	
VE5	2401-001479	C-AL;470uF,20%,10V,GP,TP,6.3*1	1	SA	
VE6	2401-001479	C-AL;470uF,20%,10V,GP,TP,6.3*1	1	SA	
VE7	2401-001479	C-AL;470uF,20%,10V,GP,TP,6.3*1	1	SA	
VE8	2401-001915	C-AL;1uF,20%,50V,GP,TP,3x5,5	1	SA	
VE9	2401-001915	C-AL;1uF,20%,50V,GP,TP,3x5,5	1	SA	
VIC1	1201-002335	IC-VIDEO AMP;MM1692XVBE,TSOP,1	1	SA	
VL1	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
VL11	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	1	SA	
VL12	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	1	SA	

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
VL6	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	SA	
VR30	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	SA	
VR31	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	SA	
VR32	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	SA	
VR33	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	SA	
VR34	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	SA	
VR60	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	SA	
VZ1	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ10	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ11	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ12	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ13	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ14	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ15	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ16	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ17	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ18	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ19	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ2	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ20	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ3	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ4	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ5	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ6	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ7	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ8	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
VZ9	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
W004	6003-000283	SCREW-TAPTITE;BH,-,B,M3,L8,Z	1	SA	
W233	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	1	SA	
W324	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
W868	3301-001689	BEAD-SMD;220ohm,2012,TP,80ohm/	1	SA	
W881	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
W882	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
W889	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	1	SA	
W890	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	1	SA	
W920	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	1	SA	
W921	3811-001868	WIRE-NO SHEATH CU;SnCuFe,-,52m	1	SNA	
W923	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	1	SA	
W946	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
XT4M01	2801-003399	CRYSTAL-UNIT;3.579545MHz,15ppm	1	SA	
XT601	2801-001384	CRYSTAL-UNIT;14.31818MHz,30ppm	1	SC	
XT602	2801-003318	CRYSTAL-UNIT;32.768KHz,20ppm,2	1	SA	
P002	AK92-01381A	ASSY PCB-MAIN DVD;DVD-R150/XAC	1	SA	
AC1	2203-005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
AC18	2203-005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
AE1	2402-001096	C-AL,SMD;220UF,20%,16V,GP,TP,6	1	SA	
AE2	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.	1	SA	
AIC1	1002-001395	IC-D/A CONVERTER;PCM1753,24Bit	1	SA	
AL1	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
CC1	2203-005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
CC2	2203-005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
CC3	2203-005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
CC4	2203-005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
CE1	2402-001248	C-AL,SMD;220UF,20%,6.3V,-,TP,6	1	SA	

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
CE3	2402-001059	C-AL,SMD;220 μ F;20%,6.3V,-,TP,	1	SA	
CN5	3708-001935	CONNECTOR-FPC/FFC/PIC;40P;0.5m	1	SA	
CON1	3710-002445	SOCKET-BOARD TO BOARD;16P2R,2	1	SA	
CON2	3710-002075	SOCKET-BOARD TO BOARD;30P2R,2	1	SA	
CR1	2007-001323	R-CHIP;3KOHM,5%,1/16W,TP;1005	1	SA	
CR10	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP;1005	1	SA	
CR11	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP;1005	1	SA	
CR12	2007-000171	R-CHIP;0ohm,5%,1/16W,TP;1005	1	SA	
CR2	2007-000138	R-CHIP;100ohm,5%,1/16W,TP;1005	1	SA	
CR3	2007-001320	R-CHIP;1.8Kohm,5%,1/16W,TP;100	1	SA	
CR4	2007-001325	R-CHIP;3.3Kohm,5%,1/16W,TP;100	1	SA	
DC1	2203-000386	C-CER,CHIP;0.015nF;5%,50V,COG,	1	SA	
DC15	2203-005138	C-CER,CHIP;1.8nF;10%,50V,X7R,1	1	SA	
DC16	2203-005138	C-CER,CHIP;1.8nF;10%,50V,X7R,1	1	SA	
DC17	2203-005138	C-CER,CHIP;1.8nF;10%,50V,X7R,1	1	SA	
DC18	2203-005138	C-CER,CHIP;1.8nF;10%,50V,X7R,1	1	SA	
DC2	2203-000330	C-CER,CHIP;0.012nF;5%,50V,COG,	1	SA	
DC20	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC22	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC23	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC24	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC25	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC26	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC27	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC3	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC4	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC50	2203-005481	C-CER,CHIP;47nF;10%,10V,X7R,TP	1	SA	
DC51	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC52	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC53	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC54	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC56	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC57	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC58	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC59	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC6	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC60	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC61	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC62	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC63	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC64	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC65	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC66	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC67	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC68	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC69	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC7	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC70	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC71	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC72	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC73	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC74	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC75	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC76	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC77	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC78	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC79	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
DC8	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC80	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC81	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC82	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC83	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC84	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC85	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC86	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC89	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC90	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC91	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC92	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC93	2203-000311	C-CER,CHIP;0.12nF;5%,50V,COG,1	1	SA	
DC94	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC95	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC96	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DC97	2203-005061	C-CER,CHIP;100nF;+80-20%,16V,Y	1	SA	
DE2	2402-000007	C-AL,SMD;220 μ F;20%,6.3V,GP,TP,4	1	SA	
DE5	2402-001248	C-AL,SMD;220UF;20%,6.3V,-,TP,6	1	SA	
DE7	2402-001248	C-AL,SMD;220UF;20%,6.3V,-,TP,6	1	SA	
DE8	2402-001248	C-AL,SMD;220UF;20%,6.3V,-,TP,6	1	SA	
DIC1	1205-002844	IC-CODEC;SSL3210,LQFP;256P;28x	1	SA	
DIC2	1105-001563	IC-DRAM;HYB25D256160CE-6,16Mx1	1	SA	
DIC3	1107-001242	IC-FLASH MEMORY;39VF160,1Mx16,	1	SNA	
DIC5	1103-001134	IC-EEPROM;24C040,512x8,SOP8P,	1	SA	
DIC7	0801-002701	IC-CMOS LOGIC;74VHCT125A,BUFFE	1	SA	
DIC8	0801-002166	IC-CMOS LOGIC;7SHU04,INVERTER,	1	SA	
DR1	2007-000174	R-CHIP;47ohm,5%,1/16W,TP;1005	1	SA	
DR2	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP;100	1	SA	
DR3	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP;100	1	SA	
DR30	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP;100	1	SA	
DR32	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP;100	1	SA	
DR35	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP;1005	1	SA	
DR36	2007-000982	R-CHIP;5.6Kohm,5%,1/16W,TP;100	1	SA	
DR37	2007-000932	R-CHIP;470OHM,5%,1/16W,TP;1005	1	SA	
DR38	2007-000171	R-CHIP;0ohm,5%,1/16W,TP;1005	1	SA	
DR39	2007-000162	R-CHIP;100Kohm,5%,1/16W,TP;100	1	SA	
DR40	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP;100	1	SA	
DR41	2007-000138	R-CHIP;100ohm,5%,1/16W,TP;1005	1	SA	
DR42	2007-000138	R-CHIP;100ohm,5%,1/16W,TP;1005	1	SA	
DR43	2007-001298	R-CHIP;51ohm,5%,1/16W,TP;1005	1	SA	
DR44	2007-001298	R-CHIP;51ohm,5%,1/16W,TP;1005	1	SA	
DR47	2007-001298	R-CHIP;51ohm,5%,1/16W,TP;1005	1	SA	
DR48	2007-001298	R-CHIP;51ohm,5%,1/16W,TP;1005	1	SA	
DR49	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP;1005	1	SA	
DR5	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP;100	1	SA	
DR50	2007-001292	R-CHIP;33ohm,5%,1/16W,TP;1005	1	SA	
DR51	2007-000659	R-CHIP;27OHM,5%,1/10W,TP;1608	1	SA	
DR52	2007-001323	R-CHIP;3KOHM,5%,1/16W,TP;1005	1	SA	
DR55	2007-000138	R-CHIP;100ohm,5%,1/16W,TP;1005	1	SA	
DR6	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP;100	1	SA	
DR64	2007-000171	R-CHIP;0ohm,5%,1/16W,TP;1005	1	SA	
DR65	2007-000171	R-CHIP;0ohm,5%,1/16W,TP;1005	1	SA	
DR66	2007-000171	R-CHIP;0ohm,5%,1/16W,TP;1005	1	SA	
DR67	2007-000171	R-CHIP;0ohm,5%,1/16W,TP;1005	1	SA	
DR68	2007-000171	R-CHIP;0ohm,5%,1/16W,TP;1005	1	SA	

Electrical Parts List

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
DR69	3301-001309	BEAD-SMD;47ohm,1608,TP,-	1	SA	
DR70	3301-001309	BEAD-SMD;47ohm,1608,TP,-	1	SA	
DR71	2007-000174	R-CHIP;47ohm,5%,1/16W,TP,1005	1	SA	
DR72	2007-000174	R-CHIP;47ohm,5%,1/16W,TP,1005	1	SA	
DR74	2007-000173	R-CHIP;22ohm,5%,1/16W,TP,1005	1	SA	
DR75	2007-000173	R-CHIP;22ohm,5%,1/16W,TP,1005	1	SA	
DR76	2007-000173	R-CHIP;22ohm,5%,1/16W,TP,1005	1	SA	
DR79	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SA	
DR8	2007-000170	R-CHIP;1Mohm,5%,1/16W,TP,1005	1	SA	
DR80	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SA	
DR82	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP,100	1	SA	
DR83	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP,100	1	SA	
DR87	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP,100	1	SA	
DR88	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP,100	1	SA	
DR89	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP,100	1	SA	
DR9	2007-000171	R-CHIP;0ohm,5%,1/16W,TP,1005	1	SA	
DR90	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP,100	1	SA	
DR91	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP,100	1	SA	
DR92	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	1	SA	
DR93	2007-000171	R-CHIP;0ohm,5%,1/16W,TP,1005	1	SA	
DRP1	2011-001474	R-NETWORK;47ohm,5%,1/16W,L,CHI	1	SA	
DRP10	2011-001474	R-NETWORK;47ohm,5%,1/16W,L,CHI	1	SA	
DRP11	2011-001261	R-NET;33ohm,5%,1/16W,L,CHIP,8P	1	SA	
DRP12	2011-001261	R-NET;33ohm,5%,1/16W,L,CHIP,8P	1	SA	
DRP13	2011-001261	R-NET;33ohm,5%,1/16W,L,CHIP,8P	1	SA	
DRP14	2011-001261	R-NET;33ohm,5%,1/16W,L,CHIP,8P	1	SA	
DRP15	2011-001478	R-NETWORK;51ohm,5%,1/16W,L,CHI	1	SA	
DRP16	2011-001478	R-NETWORK;51ohm,5%,1/16W,L,CHI	1	SA	
DRP17	2011-001478	R-NETWORK;51ohm,5%,1/16W,L,CHI	1	SA	
DRP18	2011-001478	R-NETWORK;51ohm,5%,1/16W,L,CHI	1	SA	
DRP19	2011-001478	R-NETWORK;51ohm,5%,1/16W,L,CHI	1	SA	
DRP2	2011-001474	R-NETWORK;47ohm,5%,1/16W,L,CHI	1	SA	
DRP20	2011-001478	R-NETWORK;51ohm,5%,1/16W,L,CHI	1	SA	
DRP21	2011-001478	R-NETWORK;51ohm,5%,1/16W,L,CHI	1	SA	
DRP22	2011-001478	R-NETWORK;51ohm,5%,1/16W,L,CHI	1	SA	
DRP23	2011-001478	R-NETWORK;51ohm,5%,1/16W,L,CHI	1	SA	
DRP26	2011-001396	R-NET;4.7KOHM,5%,1/16W,L,CHIP	1	SA	
DRP27	2011-001396	R-NET;4.7KOHM,5%,1/16W,L,CHIP	1	SA	
DRP28	2011-001396	R-NET;4.7KOHM,5%,1/16W,L,CHIP	1	SA	
DRP29	2011-001396	R-NET;4.7KOHM,5%,1/16W,L,CHIP	1	SA	
DRP3	2011-001474	R-NETWORK;47ohm,5%,1/16W,L,CHI	1	SA	
DRP4	2011-001474	R-NETWORK;47ohm,5%,1/16W,L,CHI	1	SA	
DRP5	2011-001474	R-NETWORK;47ohm,5%,1/16W,L,CHI	1	SA	
DRP6	2011-001474	R-NETWORK;47ohm,5%,1/16W,L,CHI	1	SA	
DRP7	2011-001474	R-NETWORK;47ohm,5%,1/16W,L,CHI	1	SA	
DRP9	2011-001474	R-NETWORK;47ohm,5%,1/16W,L,CHI	1	SA	
RIC1	1203-003996	IC-POS.FIXED REG.;KIA78R025F,	1	SA	
RIC2	1203-003806	IC-POS.IA.DJUST REG.;KIA78R000,	1	SA	
TC1	2203-000552	C-CER,CHIP;0.02nF,5%,50V,COG,1	1	SA	
TC16	2203-000278	C-CER,CHIP;0.01nF,0.5pF,50V,CO	1	SA	
TC2	2203-000552	C-CER,CHIP;0.02nF,5%,50V,COG,1	1	SA	
TC3	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
TC4	2203-0005642	C-CER,CHIP;0.22nF,5%,50V,NP0,1	1	SA	
TC5	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
TC6	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
TC7	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
TC8	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
TC9	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
TE1	2402-001238	C-AL,SMD;1uF,20%,50V,HR,TP,4.3	1	SA	
TE2	2402-001248	C-AL,SMD;220UF,20%,6.3V,-,TP,6	1	SA	
TIC1	1205-001988	IC-DATA COMM./GEN.;TSB41AB1-PA	1	SA	
TR10	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SA	
TR11	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SA	
TR12	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SA	
TR13	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SA	
TR14	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SA	
TR15	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SA	
TR16	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SA	
TR17	2007-000145	R-CHIP;6.2Kohm,5%,1/16W,TP,100	1	SA	
TR19	2007-002970	R-CHIP;56ohm,5%,1/16W,TP,1005	1	SA	
TR2	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SA	
TR20	2007-002970	R-CHIP;56ohm,5%,1/16W,TP,1005	1	SA	
TR21	2007-002970	R-CHIP;56ohm,5%,1/16W,TP,1005	1	SA	
TR22	2007-002970	R-CHIP;56ohm,5%,1/16W,TP,1005	1	SA	
TR24	2007-000144	R-CHIP;5.1KOHM,5%,1/16W,TP,100	1	SA	
TR25	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
TR26	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SA	
TR27	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
TR28	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
TR29	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
TR3	2007-001292	R-CHIP;33ohm,5%,1/16W,TP,1005	1	SA	
TR30	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
TR31	2007-000170	R-CHIP;1Mohm,5%,1/16W,TP,1005	1	SA	
TR32	2007-000073	R-CHIP;91ohm,5%,1/10W,TP,1608	1	SA	
TR33	3301-001419	BEAD-SMD;220ohm,1608,TP,133ohm	1	SA	
TR4	2007-001292	R-CHIP;33ohm,5%,1/16W,TP,1005	1	SA	
TR9	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SA	
TY1	2801-004021	CRYSTAL-SMD;24.576MHz,20ppm,28	1	SA	
V29	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC1	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC11	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC12	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC13	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC15	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC16	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC17	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC18	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC2	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC20	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC21	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC22	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC23	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC24	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC25	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC26	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC27	2203-000278	C-CER,CHIP;0.01nF,0.5pF,50V,CO	1	SA	
VC28	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC5	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC6	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC7	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC8	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VC9	2203-0005061	C-CER,CHIP;100nF,+80-20%,16V,Y	1	SA	
VE3	2402-001248	C-AL,SMD;220UF,20%,6.3V,-,TP,6	1	SA	
VE4	2402-001248	C-AL,SMD;220UF,20%,6.3V,-,TP,6	1	SA	

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
VIC1	1204-002419	IC-VIDEO DECODER;TW9906,TQFP,8	1	SA	
VL1	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	SA	
VR14	3301-000314	BEAD-SMD;120ohm,1.6x0.8x0.8mm,	1	SA	
VR15	2007-000137	R-CHIP;2KOHM,5%,1/16W,TP,1005	1	SA	
VR16	2007-000137	R-CHIP;2KOHM,5%,1/16W,TP,1005	1	SA	
VR2	2007-001292	R-CHIP;33ohm,5%,1/16W,TP,1005	1	SA	
VR23	2007-000138	R-CHIP;100ohm,5%,1/16W,TP,1005	1	SA	
VR25	2007-000171	R-CHIP;0ohm,5%,1/16W,TP,1005	1	SA	
VRP3	2011-001344	R-NET;100ohm,5%,1/16W,L,CHIP,8	1	SA	
VRP4	2011-001344	R-NET;100ohm,5%,1/16W,L,CHIP,8	1	SA	
Y1	2801-004621	CRYSTAL-SMD;27MHz,15ppm,-,14pF	1	SA	

P005 AK92-01326A ASSY PCB-FUNCTION;DVD-R157/XAA

AR722	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,	1	SA	
AR740	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,	1	SA	
AVIN2	3722-002384	JACK-PIN;3P,SN/NI,YEL/WHIT/RED,	1	SA	
CN7	3722-002383	JACK-IEEE1394;4P/1,AU,BLK,ANGL	1	SA	
ESD01	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD02	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD03	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD04	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD05	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD06	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD07	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD08	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD09	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD10	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD11	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD12	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD13	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
ESD14	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V	1	SA	
FC0N4	3708-001695	CONNECTOR-FPC/FFC/PIC;13P;1MM,	1	SA	
FL615	3809-001787	FFC CABLE-FLAT;30V,80C,115mm,1	1	SA	
JP36	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	SA	
LD61A	AK61-00531A	HOLDER-LED;DVD-R145,ABS 94HB,T	1	SA	
LD701	0601-001928	LED;ROUND,BLUE,3mm,465nm,3.6x3	1	SA	
PWR01	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,160	1	SA	
PWR02	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA	
QWR01	0501-000398	TR-SMALL SIGNAL;KSC945-Y,NPN,2	1	SA	
R720	2007-000098	R-CHIP;56Kohm,5%,1/10W,TP,1608	1	SA	
SW711	3404-001261	SWITCH-TACT;15V DC,20mA,100gf,	1	SA	
VR40	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1	1	SA	

P007 AK97-01947A ASSY-R157 KEY;-R157/XAA,NEXUS

CN704	3708-001803	CONNECTOR-FPC/FFC/PIC;10P;1.25	1	SA	
FL286	3809-001667	FFC CABLE-FLAT;30V,80C,70mm,10	1	SA	
LD702	0601-001587	LED;ROUND,RED,3.1mm,635nm,3.8x	1	SA	
QWR01	0501-000398	TR-SMALL SIGNAL;KSC945-Y,NPN,2	1	SA	
SW703	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6	1	SA	
SW705	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6	1	SA	
SW706	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6	1	SA	
SW707	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6	1	SA	
SW708	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6	1	SA	
SW709	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6	1	SA	
SW710	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6	1	SA	

Loc.No	Part No	Description ; Specification	Q'ty	S.N.A	Remark
W009	6003-000276	SCREW-TAPTITE,BH,+, -,B,M3,L10,	4	SA	
A001	AK59-00061E	REMOCON-ASSY;DVD-R150/XAX,SEC,	1	SA	
	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	1	SA	
	2203-000192	C-CER,CHIP;100nF,+80-20%,50V,Y	1	SA	
	0601-000519	LED-IR;ROUND,5mm,170mW,4V,940n	1	SA	
	2401-002144	C-AL;47uF,20%,16V,GP,TP;5x11,5	1	SA	
	2802-001184	RESONATOR-CERAMIC;3.64MHZ,0.5%	1	SA	
BOX	AK69-00500F	PACKING CASE;DVD-R150/XAX,PAPE	1	SA	
C011	AK61-00519A	SPRING ETC-DOOR;DVD-SR420,STS3	1	SA	
C022	AK64-01939B	DOOR-FRONT;DVD-R150/XAX,ABS 94	1	SA	
FL655	3809-001906	FFC CABLE-FLAT;30V,80,65mm,40P	1	SA	
IB	AK68-01316E	MANUAL USERS;DVD-R150/XAX,XAZ,	1	SA	
VS203	AK39-00103A	LEAD CONNECTOR-ASSY;DVD-R135A/	1	SA	
W001	6003-000275	SCREW-TAPTITE,BH,+, -,B,M3,L10,	5	SA	
W001	6003-000275	SCREW-TAPTITE,BH,+, -,B,M3,L10,	2	SA	
W009	6003-000276	SCREW-TAPTITE,BH,+, -,B,M3,L10,	4	SA	
W200	6003-001375	SCREW-TAPTITE,BH,+, -,B,M3,L8,Z	2	SA	
W268	6003-000254	SCREW-TAPTITE,BH,+, -,S,M3,L6,Z	1	SA	
W275	6003-001561	SCREW-TAPTITE,BH,+, -,B,M3,L6,Z	3	SA	
	AC39-00073A	CABLE-RCA;SJ01-08-099,1.2MT,3P	1	SA	
	AC39-42001J	CABLE-RF ASSY;-,-,1365,1200mm	1	SA	

MEMO